


characteristics
of
Sylvania
receiving
tubes

the most important tube improvements come from Sylvania



**SARONG
CATHODE
COATING**

**BIKINI
CATHODE
COATING**

and now . . . **LIFE-BOOST CATHODE**

Sylvania has developed a revolutionary new way of forming the cathode material. The result is a startling improvement in tube characteristics — longer tube life, greater uniformity, improved performance. It's called Life-Boost Cathode and it's the most significant advance in electron tubes since Sylvania developed Sarong Cathode. Tubes with cathodes formed this new way, by compacting metal powder, possess many inherent advantages over conventional structures. New Sylvania powder techniques allow desirable chemical additives to be alloyed with pure nickel powder under conditions of exact process control. Absence of unfavoring impurities permits better control of cathode activation, providing greater uniformity of electrical characteristics initially and sustained characteristic levels on life. The important point is this — Sylvania Life-Boost Cathode tubes offer the service dealer greater tube reliability, longer tube life, improved tube performance. Always look to Sylvania for new tube improvements — always insist on Sylvania tubes.

SYLVANIA RECEIVING TUBE CHARACTERISTICS CHART

This booklet contains the very latest television and radio receiving tubes in addition to many industrial tubes. It is intended as a quick reference to pertinent characteristics and basing connections.

Resistance/capacitance coupled amplifier data and a listing of tube types by basing connections are also included. This valuable supplementary information is presented in the latter pages of the booklet.

Please note that all types listed may not be available from Sylvania. They are included for your reference in finding substitutes, etc. Consult our price list for types currently available. The data published here has been compiled from various sources and while believed to be accurate, no responsibility can be assumed in case of error.

The majority of the information presented in the chart is self-explanatory, requiring only a few footnotes for clarification. The *Bulb Size or Style* column and the *Emitter* column are the only columns requiring additional comment.

BULB SIZE OR STYLE COLUMN

T-1 to T-18—Numbers 1 to 18 indicate nominal bulb diameter in eighths of an inch.

T, ST, TT—T—Straight sided bulb, ST—dome topped tapered bulb, TT—large straight sided bulb with top and bottom curved.

Metal—Octal base, T-8 metal envelope.

Lock-in—Lock-in base, T-9 glass bulb.

9-T9—Conventional 9 pin miniature base with T-9 bulb.

M-N—Metal Cased Nuvistor.

Comp.—Compactron, 12 pin base with T-9 or T-12 bulb, exhaust tip located at bottom.


NOVAR—9 pin base (large pin circle .687" dia. and large dia. pins .04") with T-9 or T-12 bulb.

MAGNOVAL—9 pin base (large pin circle .687" dia. and large dia. pins .05") bonded to T-9 bulb, exhaust tip located at bottom.

CERAMIC and METAL—Planar Construction, ceramic and metal envelope, thimble sized, baseless.


EMITTER COLUMN. When replacing tubes in series string television receivers, attention should be given to the complete type number including the suffix. Prototypes should not be substituted for series string types.

Heater voltage, heater current and heater-cathode voltage ratings of series string tubes may differ widely from those of their prototypes. All series string types have controlled heater warm-up time. In addition, heater current production tolerances for series string tubes are tighter to assure proper steady state voltage distribution. Failure to recognize these differences may result in poor set performance and premature tube failure.



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts?	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milliwatts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
OA2 GB-OA2WA (3)	T-5½	Diode	5B0	Voltage Regulator with Starting Voltage at 155, Operating Voltage 150, Operating Current 5 to 30 Ma.											
OA3 OA3A	ST-12 T-9	Diode	4AJ	Voltage Regulator with Starting Voltage at 165, Operating Voltage 75, Operating Current 5 to 40 Ma.											
OA4G	ST-12	Gas Triode	4V	Relay Tube Peak Cathode Ma. = 100 D.C. Cathode Ma. = 25 Max. Starter Anode Drop = 60 V. Approx.											
OA5	T-5½	Gas Pentode	OA5	Switching	750										
OB2 GB-OB2WA (3)	T-5½	Diode	5B0	Voltage Regulator with Starting Voltage at 115, Operating Voltage 105, Operating Current 5 to 30 Ma.											
OB3 OB3A	ST-12 T-9	Diode	4AJ	Voltage Regulator with Starting Voltage at 125, Operating Volts 90, Operating Current 5 Ma. Min., 30 Ma. Max.											
OC2	T-5½	Diode	5B0	Voltage Regulator with Starting Voltage at 105, Operating Voltage 75, Operating Current 5 Ma. Min., 30 Ma. Max.											
OC3 OC3A	ST-12 T-9	Diode	4AJ	Voltage Regulator with Starting Voltage at 135, Operating Volts 105, Operating Current 5 Ma. Min., 40 Ma. Max.											
OD3 OD3A	ST-12 T-9	Diode	4AJ	Voltage Regulator with Starting Voltage at 180, Operating 150 Volts, Operating Current 5 Ma. Min., 40 Ma. Max.											
OY4 OY4G	Metal T-7	Gas Diode	4BU 4BU	Ionic	H-W Rect.	117 A.C. Volts Per Plate, RMS, 75 Ma. Max., 40 Ma. Min. Output Current.									
OZ4	Metal	Gas Duodi.	4R	Ionic	F-W Rect.	300 A.C. Volts Per Plate, RMS, 90 Ma. Max., 30 Ma. Min. Output Current.									
OZ4A	Metal	Gas Duodi.	4R	Ionic	F-W Rect.	300 A.C. Volts Per Plate, RMS, 110 Ma. Max., 30 Ma. Min. Output Current.									
OZ4G	T-7	Gas Duodi.	4R	Ionic	F-W Rect.	300 A.C. Volts Per Plate, RMS, 90 Ma. Max., 30 Ma. Min. Output Current.									
1A3	T-5½	Diode	5AP	1.4	0.150	Detector	Half Wave Cathode Type Rectifier for H. F. Use.									
1A5GT	T-9	Power Pent.	6X	1.4	0.050	Power Amp.	85 4.5 85 3.5 0.7 300000 800 25000 100 90 4.5 90 4.0 0.8 300000 850 25000 115									
1A7GT	T-9	Heptode	7Z	1.4	0.050	Converter	90 0.0 90 0.6 1.2 600000 250* (Ga = 90 V. Max. 1.2 Ma.)									
1AC5	T-3	Pentode	8CP	1.25	0.040	Power Amp.	30 2.0 30 0.5 0.1 200000 450 50000 5 45 3.0 45 1.0 0.2 170000 600 40000 15 67.5 4.5 67.5 2.0 0.4 150000 750 25000 50									
1AD2	T-9	Diode	12DQ	1.25	0.200	Flyback H-W Rectifier	Maximum Peak Inverse Plate Voltage = 26,000 Volts, Maximum Peak Plate Current = 50 Ma., Maximum Average Output Current = 0.5 Ma.									
1AD5	T-3	Pentode	8CP	1.25	0.040	R-F Amp.	30 0 30 0.45 0.16 700000 430 50000 5 45 0 45 0.9 0.35 700000 580 50000 10 67.5 0 67.5 1.85 0.75 700000 735 50000 15									
1AE4	T-5½	Pentode	6AR	1.25	0.100	R-F Amp.	90 0 90 3.5 1.2 500000 1550 50000 15									
1AF4	T-5½	Pentode	6AR	1.4	0.025	R-F Amp.	67.5 0 67.5 1.2 0.32 2.2 Meg. 925 50000 10 90 0 90 1.8 0.35 1.8 Meg. 1050 50000 15									
1AF5	T-5½	Diode Pent.	6AU	1.4	0.025	Det. Amp.	67.5 0 67.5 0.7 0.25 2.8 Meg. 550 50000 10 90 0 90 1.1 0.4 2.0 Meg. 600 50000 15									
1AG4	T-2X3	Pentode	1AG4	1.25	0.040	Power Amp.	41.4 3.6 41.4 2.4 0.6 180000 1030 50000 10									
1AG5	T-2X3	Diode Pent.	1AG5	1.25	0.030	Det. Amp.	45 2.0 45 0.28 0.12 2.5 Meg. 250 50000 10									
1AH4	T-2X3	Pentode	1AH4	1.25	0.040	R-F Amp.	45 5 Meg. ⁴ 45 0.75 0.2 1.5 Meg. 750 50000 10 67.5 5 Meg. ⁴ 67.5 0.75 0.2 2.0 Meg. 750 50000 15									
1AJ5	T-2X3	Diode Pent.	1AJ5	1.25	0.040	Det. Amp.	45 0 45 1.0 0.3 300000 425 50000 10									
1AK4	T-2X3	Pentode	1AK4	1.25	0.020	Class A1 Amp.	45 0 45 0.75 0.2 1500000 750 (Screen Supply = 67.5 Volts Thru .11 Meg. Res.) 67.5 0 67.5 0.75 0.2 2000000 750									
1AK5	T-2X3	Diode Pent.	1AK5	1.25	0.020	Det. Amp.	45 0 45 0.5 0.2 400000 280 50000 10									
1AN5	T-5½	Pentode	7ES	1.4	0.025	I-F Amp.	90 0 62 1.7 0.7 450000 940 G1 to G2 = 20									
1AU3	T-12	Diode	3C	1.25	0.200	Flyback H-W Rect.	Maximum Peak Inverse Plate Voltage = 30,000 Volts. Maximum Peak Plate Current = 50 Ma. Maximum Average Plate Current = 0.5 Ma.									
1AX2	T-6½	Diode	9Y	1.4	0.650	Flyback H-W Rect.	Maximum Peak Inverse Plate Voltage = 25,000 Volts. Maximum Peak Plate Current = 45 Ma. Maximum Average Current = 0.5 Ma.									



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
1B3GT	T-9	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1DN5	T-5½	Diode Pent.	6BW	1.4†	0.050	Det. Amp.	67.5	0	67.5	2.1	0.55	.6 Meg.	630
1G3	T-9	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1H2	T-6½	Diode	9LX	1.4	0.550	Flyback H-W Rect.
1H5GT	T-9	Diode Triode	5Z	1.4†	0.050	Det. Amp.	90	0.0	0.15	240000	275	65
1J3	T-9	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1J3A	T-9	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1K3	T-9	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1L4	T-5½	Pentode	6AR	1.4†	0.050	R-F Amp.	90	0	67.5	2.9	1.2	600000	925
1L6	T-5½	Heptode	7DC	1.4†	0.050	Converter	90	0	45	0.5	0.6	650000	300 [▲]	(Ga = 90 V., 1.2 Ma.)
1LA4	Lock-in	Power Pent.	5AD	1.4†	0.050	Power Amp.	85	4.5	85	3.5	0.7	300000	800	25000	100
1LA6	Lock-in	Heptode	7AK	1.4†	0.050	Converter	90	4.5	90	4.0	0.8	300000	850	25000	115
1LB4	Lock-in	Power Pent.	5AD	1.4†	0.050	Power Amp.	90	0.0	45	0.55	0.6	750000	250 [▲]	(Ga = 90 V. Max., 1.2 Ma.)
1LC5	Lock-in	Pentode	7AO	1.4†	0.050	R-F Amp.	45	0.0	45	1.1	0.35	700000	750
1LC6	Lock-in	Heptode	7AK	1.4†	0.050	Converter	90	0.0	45	1.15	0.30	1.5 Meg.	775
1LD5	Lock-in	Diode Pent.	6AX	1.4†	0.050	Amplifier	45	0.0	45	0.75	0.75	300000	250 [▲]	(Ga = 45 V. Max., 1.4 Ma.)
1LE3	Lock-in	Triode	4AA	1.4†	0.050	Amplifier	90	0.0	4.5	11200	1300	14.5
1LG5	Lock-in	Pentode	7AO	1.4†	0.050	R-F Amp.	90	0	45	1.5	0.45	350000	800
1LH4	Lock-in	Diode Triode	5AG	1.4†	0.050	Det. Amp.	90	1.5	45	1.7	0.4	1000000	800
1LN5	Lock-in	Pentode	7AO	1.4†	0.050	R-F Amp.	90	0.0	90	3.7	0.9	500000	1050
1N2A	T-12	Diode	3C	1.25†	0.200	Flyback H-W Rect.
1N5GT	T-9	Pentode	5Y	1.4†	0.050	R-F Amp.	90	0.0	90	1.2	0.3	1.5 Meg.	750
1R4	Lock-in	H. F. Diode	4AH	1.4†	0.150	Detector
1R5	T-5½	Heptode	7AT	1.4†	0.050	Converter	45	0.0	45	0.7	2.1	500000	210 [▲]
1S4	T-5½	Power Pent.	7AV	1.4†	0.100	Power Amp.	90	0.0	67.5	1.5	3.5	400000	280 [▲]
1S5	T-5½	Diode Pent.	6AU	1.4†	0.050	Det. Amp.	67.5	0.0	67.5	1.6	0.4	600000	625
1S6	T-3	Diode Pent.	8DA	1.25†	0.040	Det. Amp.	30	0	30	0.33	0.1	500000	330
1T4	T-5½	Pentode	6AR	1.4†	0.050	R-F Amp.	45	0.0	45	1.7	0.7	350000	700

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. †† Filamentary Type. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ††† Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Amplifi-cation Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
1U4	T-5½	Pentode	6AR	1.4♣	0.050	R-F Amp.	90	0	90	1.6	0.45	1.6 Meg.	900
1U5	T-5½	Diode Pent.	6BW	1.4♣	0.050	Det. Amp.	Characteristics Same as Type 1S5.									
1U6	T-5½	Heptode	7DC	1.4♣	0.025	Converter	67.5 90	0 0	45 45	0.5 0.6	0.7 0.6	500000 500000	260 ^A 275 ^A	(Ga = 67.5 V., 1.0 Ma.) (Ga = 90 V., 1.1 Ma.)		
1V2	T-6½	Diode	9U	0.625♣	0.300	H-W Rect.	Television Service. RF or Flyback Supply. Peak Inverse Volts = 8250, Output = 0.6 Ma.									
1V6	T-2x3	Tri. Pentode	1V6	1.25♣	0.040	R-F Osc. R-F Amp.	45 45	1 Meg. ⁴ 5 Meg. ⁴ 45	0.4 0.4	1G ¹ = 12 μa 0.15 200 ^A			
1X2B	T-6½	Diode	9Y	1.25♣	0.200	H-W Rect.	Television Service, RF or Flyback Supply. Peak Inverse Volts = 22 KV, Output = 0.5 Ma.									
2A3	ST-16	Triode	4D	2.5♣	2.500	S.T. A1 Amp. P.P.AB1 Amp.	16.5	250 300	45.0 62.0	60.0 80-147 ¹	800	5250	4.2	2500 3000 [†]	3500 15000
2AF4A 2AF4B	T-5½	Triode	7DK	2.35*	0.600	UHF Osc.	2.5	Characteristics Same as Type 6AF4A.									
2AH2	Comp. T-9	Diode	12DG	2.5♣	0.300	Flyback H-W Rect.	Type 2AF4B has Higher-Cathode Voltage Ratings than Otherwise Identical Type 2AF4A. Maximum Peak Inverse Plate Voltage = 30,000 Volts. Maximum Peak Plate Current = 80 Ma. Maximum Average Plate Current = 1.5 Ma.									
2B3	T-9	Diode	8HC	1.75♣	0.250	H-W Rect.	Television Service. Flyback Supplies. Peak Inverse Volts = 22 KV. Output = 0.5 Ma.									
2BN4A	T-5½	Triode	7EG	2.35*	0.600	VHF Amp.	2.42	Characteristics Same as Type 6BN4A. (2BN4A Designed for Series String Receivers.)									
2C21	ST-12	Duotriode	7BH	6.3	0.600	Amplifier Power Amp.	2.3	250 250	16.5 60.0	8.3 20.0	7600	1375	10.4	20000 3500
2C22	T-9	Triode	4AM	6.3	0.300	Amplifier	3.3	300	10.5	11.0	6600	3000	20.0
2C50	T-9	Duotriode	8BD	12.6	0.300	Amplifier	3.85	200	11	18	3450	2900	10
2C61	T-6½	Duotriode	8CJ	6.3	0.300	Amplifier	1.65	150	240 [■]	8.2	6500	5500	35
2C52	T-9	Duotriode	8BD	12.6	0.300	Amplifier	1.65	250	2.0	1.3	1900	100
2CW4	M-N	Triode	12AQ	2.1*	0.450	VHF Amp.	1.0	Characteristics Same as Type 6CW4. (2CW4 Designed for Series String Receivers.)									
2CY5	T-5½	Tetrode	7EW	2.4*	0.600	VHF Amp.	2.0	Characteristics Same as Type 6CY5. (2CY5 Designed for Series String TV Receivers.)									
2D21	T-5½	Gas Tetrode	7BN	6.3	0.600	Relay Tube	400	5	Average Cathode Current = 100 Max. Ma., Averaged over any 30 Sec. Interval.						
2E26	T-9	Beam Pent.	7CK	6.3	0.800	Class C Amp.	10	500	40.0	185	60.0	11.0	Driving Power = 0.12 Watts. D.C. Grid No. 1 Current = 3.0 Ma. 2000				
2EA5	T-5½	Tetrode	7EW	2.4*	0.600	VHF Amp.	3.25	Characteristics Same as Type 6EA5. (2EA5 Designed for Series String Receivers.)									
2EN5	T-5½	Duodiode	7FL	2.1*	0.450	Phase-Comparator	Diode Current for Continuous Operation (Each Plate) = 20 Ma. Diode Characteristics with 5.0 Volts Applied. Ib = 20 Ma. (Each Plate—Test Condition Only.)									
2ER5	T-5½	Triode	7FP	2.3*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6ER5. (2ER5 Designed for Series String Receivers.)									
2ES5	T-5½	Triode	7FP	2.35*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6ES5. (2ES5 Designed for Series String Receivers.)									
2EV5	T-5½	Tetrode	7EW	2.4*	0.600	VHF Amp.	3.25	Characteristics Same as Type 6EV5. (2EV5 Designed for Series String Receivers.)									
2FH5	T-5½	Triode	7FP	2.35*	0.600	R-F Amp.	2.2	Characteristics Same as Type 6FH5. (2FH5 Designed for Series String Receivers.)									
2FQ5	T-5½	Triode	7FP	2.3*	0.600	VHF Amp.	2.5	Characteristics Same as Type 6FQ5. (2FQ5 Designed for Series String Receivers.)									
2FQ5A	T-5½	Triode	7FP	2.3*	0.600	VHF Amp.	2.5	Characteristics Same as Type 6FQ5A. (2FQ5A Designed for Series String Receivers.)									
2FS5	T-5½	Shadow Grid Beam Pent.	7GA	2.4*	0.600	VHF Amp.	3.2	Characteristics Same as 6FS5. (2FS5 Designed for Series String Receivers.)									
2FY5	T-5½	Triode	7FP	2.4*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6FY5. (2FY5 Designed for Series String Receivers.)									
2FV6	T-5½	Tetrode	7FQ	2.4*	0.600	VHF Amp.	2.0	Characteristics Same as Type 6FV6. (2FV6 Designed for Series String Receivers.)									
2GK5	T-5½	Triode	7FP	2.3*	0.600	VHF Amp.	2.5	Characteristics Same as Type 6GK5. (6GK5 Designed for Series String Receivers.)									
2T4	T-5½	Triode	7DK	2.35*	0.600	UHF Osc.	3.85	Characteristics Same as Type 6T4. (2T4 Designed for Series String TV Receivers.)									
2X2	ST-12	Diode	4AB	2.5♣	1.750	Maximum Inverse Plate Voltage = 12,500 Volts, Maximum Peak Current = 60 Ma. Maximum Average Current = 7.5 Ma., Maximum RMS Supply Voltage = 5500 Volts. Characteristics Same as 2X2.									
2X2A(3)	T-6½	Diode	9DT	3.15	0.220	H-W Rect.	TV Service. Peak Inverse Volts = 18 KV. Peak Current = 80 Ma. Average Current = 1.5 Ma.									
3A2	T-9	Diode	4AC	3.15	0.220	H-W Rect.	TV Service. Peak Inverse Volts = 30 KV. Peak Current = 80 Ma. Average Current = 1.5 Ma.									
3A4	T-5½	Pentode	7BB	1.4♣	0.200	Power Amp.	2.5	135 150	7.5 8.4	90 90	14.8 13.3	2.6 2.2	90000 100000	1900 1900	8000 8000	600 700




AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
3A5	T-5½	Duotriode	7BC	1.4† 2.8	0.220 0.110	Amplifier	0.55	90	2.5	3.7	8300	1800	15	2000
3AF4A	T-5½	Triode	7DK	3.2*	0.450	UHF Osc.	2.5	Characteristics Same as Type 6AF4A.									
3AF4B	T-5½	Triode	7DK	3.2*	0.450	VHF Osc.	2.7	Characteristics Same as Type 6AF4A. (3AF4B has Peak Positive and Negative Heater Cathode Voltages of 180 Volt.)									
3AL5	T-5½	Duodiode	6BT	3.15*	0.600	Detector	Characteristics Same as Type 6AL5. (3AL5 Designed for Series String TV Receivers.)									
3AU6	T-5½	Pentode	7BK	3.15*	0.600	R-F Amp.	3.3	Characteristics Same as Type 6AU6. (3AU6 Designed for Series String TV Receivers.)									
3AV6	T-5½	Duodiode Tri.	7BT	3.15*	0.600	Det. Amp.	0.55	Characteristics Same as Type 6AV6. (3AV6 Designed for Series String TV Receivers.)									
3AW3	T-9	Diode	8EZ	3.15†	0.220	Flyback H-W Rect.	Maximum Peak Inverse Volts = 30,000 Volts. Maximum Peak Plate Current = 88 Ma. Maximum Average Plate Current = 1.7 Ma.									
3B2	T-12	Diode	8GH	3.15	0.220	H-W Rect.	TV Service. Pulsed Rectifier Service. Max. Peak Inverse Volts = 35 Kv, Output = 1.1 Ma.									
3B7	Lock-in	Duotriode	7BE	2.8† 1.4	0.110 0.220	Power Amp. Oscillator	2.97	135 180	0 0	22.0 25.0	1900 (Class C)	20 R.F. Pwr. Amp.	16000 2800 mw at 25 mc, 1400 mw at 125mc.
3BA6	T-5½	Pentode	7BK	3.15*	0.600	I-F or R-F Amplifier	3.3	Characteristics Same as Type 6BA6. (3BA6 Designed for Series String TV Receivers.)									
3BC5	T-5½	Pentode	7BD	3.15*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6BC5. (3BC5 Designed for Series String TV Receivers.)									
3BE6	T-5½	Heptode	7CH	3.15*	0.600	Converter	1.1	Characteristics Same as Type 6BE6. (3BE6 Designed for Series String TV Receivers.)									
3BN4A	T-5½	Triode	7EG	3.0*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6BN4A. (3BN4A Designed for Series String Receivers.)									
3BN6	T-5½	Gated Beam	7DF	3.15*	0.600	Quad. Det.	Characteristics Same as Type 6BN6. (3BN6 Designed for Series String TV Receivers.)									
3BU8	T-6½	Duo Pentode	9FG	3.15*	0.600	Sync. Sep.	1.1	Characteristics Same as Type 6BU8. (3BU8 Designed for Series String TV Receivers.)									
3BX6	T-6½	Pentode	9AQ	3.4*	0.600	VHF Amp.	2.5	Characteristics Same as Type 6BX6. (3BX6 Designed for Series String Receivers.)									
3BY6	T-5½	Heptode	7CH	3.15*	0.600	Sync. Sep.	2.2	Characteristics Same as Type 6BY6. (3BY6 Designed for Series String TV Receivers.)									
3BY7	T-6½	Pentode	9AQ	3.4*	0.600	VHF Amp.	2.7	100 250	1.1 2.0	57 100	5.5 10	1.6 2.5	250000 600000	5000 6000
3BZ6	T-5½	Pentode	7CM	3.15*	0.600	VHF Amp.	2.3	Characteristics Same as Type 6BZ6. (3BZ6 Designed for Series String TV Receivers.)									
3CB6	T-5½	Pentode	7CM	3.15*	0.600	Amplifier	2.3	Characteristics Same as Type 6CB6. (3CB6 Designed for Series String TV Receivers.)									
3CE5	T-5½	Pentode	7BD	3.15*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6CE5. (3CE5 Designed for Series String TV Receivers.)									
3CF6	T-5½	Pentode	7CM	3.15*	0.600	VHF Amp.	2.3	Characteristics Same as Type 6CF6. (3CF6 Designed for Series String TV Receivers.)									
3CS6	T-5½	Heptode	7CH	3.15*	0.600	Sync. Sep.	1.0	Characteristics Same as Type 6CS6. (3CS6 Designed for Series String TV Receivers.)									
3CY5	T-5½	Tetrode	7EW	2.9*	0.450	VHF Amp.	2.0	Characteristics Same as Type 6CY5. (3CY5 Designed for Series String TV Receivers.)									
3D6	Lock-in	Beam Pent.	6BA	2.8† 1.4	0.110 0.220	Power Amp.	4.95	150 150	4.5 20.0	90 135	10.2 23.0	1.8 6.0	(Class A) (Class C)	2400 R.F. Power Amp.	14000 at 50 mc.	600 1400	
3DG4	T-12	Duodiode	5DE Directly Heated Cathode	3.3	3.800	F-W Rect.	275 A.C. Volts Per Plate, RMS, 350 Ma. Output Current. Condensor Input to Filter. 300 Volts D.C. Output.									
3DK6	T-5½	Pentode	7CM	3.15*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6DK6. (3DK6 Designed for Series String TV Receivers.)									
3DT6	T-5½	Gated Beam	7EN	3.15*	0.600	Quad. F. M. Det.	1.65	Characteristics Same as Type 6DT6. (3DT6 Designed for Series String TV Receivers.)									
3DT6A	T-5½	Gated Beam	7EN	3.15*	0.600	Quad. F. M. Det.	1.7	Characteristics Same as Type 6DT6A. (3DT6A Designed for Series String Receivers.)									
3EA5	T-5½	Tetrode	7EW	2.9*	0.450	VHF Amp.	3.25	Characteristics Same as Type 6EA5. (3EA5 Designed for Series String Receivers.)									
3EH7	T-6½	Pentode	9AQ	3.4*	0.600	VHF Amp.	2.7	Characteristics Same as Type 6EH7. (3EH7 Designed for Series String Receivers.)									
3EJ7	T-6½	Pentode	9AQ	3.4*	0.600	VHF Amp.	2.7	Characteristics Same as Type 6EJ7. (3EJ7 Designed for Series String Receivers.)									
3ER5	T-5½	Triode	7FP	2.8*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6ER5. (3ER5 Designed for Series String Receivers.)									
3ES5	T-5½	Triode	7FP	3.0*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6ES5. (3ES5 Designed for Series String Receivers.)									
3EV5	T-5½	Tetrode	7EW	2.9*	0.450	VHF Amp.	3.25	Characteristics Same as Type 6EV5. (3EV5 Designed for Series String Receivers.)									
3FH5	T-5½	Triode	7FP	3.0*	0.450	R-F Amp.	2.2	Characteristics Same as Type 6FH5. (3FH5 Designed for Series String Receivers.)									
3FQ5	T-5½	Triode	7FP	2.8*	0.450	VHF Amp.	2.5	Characteristics Same as Type 6FQ5. (3FQ5 Designed for Series String Receivers.)									

(1) See Frontal Section.
 (2) Design Maximum Values.
 † Maximum Signal.


(3) Has Special Mechanical and/or Life Characteristics.
 (4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
 † Filamentary Type.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
 † Plate to Plate.
 ■ Cathode Resistor (ohms).




SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
3FQ5A	T-5½	Triode	7FP	2.8*	0.450	VHF Amp.	2.5	Characteristics Same as Type 6FQ5A. (3FQ5A Designed for Series String Receivers.)									
3SF5	T-5½	Shadow Grid Beam Pentode	7GA	2.9*	0.450	VHF Amp.	3.2	Characteristics Same as Type 6SF5. (3SF5 Designed for Series String Operation.)									
3FY5	T-5½	Triode	7FP	3.1*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6FY5. (3FY5 Designed for Series String Receivers.)									
3GK5	T-5½	Triode	7FP	2.8*	0.450	VHF Amp.	2.5	Characteristics Same as Type 6GK5. (3GK5 Designed for Series String Receivers.)									
3GS8	T-6½	Duo Pent.	9LW	3.15*	0.600	Sync. Sep.	1.1	Characteristics Same as Type 6GS8. (3GS8 Designed for Series String Receivers.)									
3HS8	T-6½	Twin Pent.	9FG	3.15*	0.600	AGC/Sync. Amplifier	1.1	Characteristics Same as Type 6HS8. (3HS8 Designed for Series String Receivers.)									
3Q4	T-5½	Power Pent.	7BA	1.44 2.84	0.100 0.050	Power Amp.	85 90 90	5.0 4.5 4.5	85 90 90	6.9 9.5 7.7	1.5 2.1 1.7	120000 100000 120000	1975 2150 2000	10000 10000 10000	250 270 240
3Q5GT	T-9	Beam Pent.	7AP	1.44 2.84	0.100 0.050	Power Amp.	90 90	4.5 4.5	90 90	9.5 8.0	1.3 1.0	90000 80000	2200 2000	8000 8000	270 230
3S4	T-5½	Power Pent.	7BA	1.44 2.84	0.100 0.050	Power Amp.	90 90	7.0 7.0	67.5 67.5	7.4 6.1	1.4 1.1	100000 100000	1575 1425	8000 8000	270 235
3V4	T-5½	Power Pent.	6BX	1.4 2.84	0.100 0.050	Power Amp.	Characteristics Same as Type 3Q4.									
3Z4	T-5½	Power Pent.	7BA	1.44 2.84	0.050 0.025	Power Amp.	67.5	7.0	67.5	6.5	1.3	100000	1450	8000	210
4A6U	T-5½	Pentode	7BK	4.2*	0.450	R-F Amp.	3.3	Characteristics Same as Type 6A6U. (4A6U Designed for Series String TV Receivers.)									
4AV6	T-5½	Duodiode Tri.	7BT	4.2*	0.450	Det. Amp.	.55	Characteristics Same as Type 6AV6. (4AV6 Designed for Series String Receivers.)									
4BA6	T-5½	Pentode	7BK	4.2*	0.450	R-F Amp.	3.3	Characteristics Same as Type 6BA6. (4BA6 Designed for Series String TV Receivers.)									
4BC5	T-5½	Pentode	7BD	4.2*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6BC5. (4BC5 Designed for Series String TV Receivers.)									
4BC8	T-6½	Duotriode	9AJ	4.2*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6BC8. (4BC8 Designed for Series String TV Receivers.)									
4BE6	T-5½	Heptode	7CH	4.2*	0.450	Converter	1.1	Characteristics Same as Type 6BE6. (4BE6 Designed for Series String TV Receivers.)									
4BL8	T-6½	Tri. Pentode	9DC	4.6*	0.600	VHF Osc. VHF Amp.	1.6 1.8	Characteristics Same as Type 6BL8. (4BL8 Designed for Series String Receivers.)									
4BN4	T-5½	Triode	7EG	4.2	0.300	VHF Amp.	2.42	Characteristics Same as Type 6BN4.									
4BN6	T-5½	Gated Beam	7DF	4.2*	0.450	Quad. F. M. Det.	Characteristics Same as Type 6BN6. (4BN6 Designed for Series String TV Receivers.)									
4BQ7A	T-6½	Duotriode	9AJ	4.2*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6BQ7A. (4BQ7A Designed for Series String TV Receivers.)									
4BS8	T-6½	Duotriode	9AJ	4.5*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6BS8. (4BS8 Designed for Series String TV Receivers.)									
4BX8	T-6½	Duotriode	9AJ	4.5*	0.600	VHF Amp.	2.0	Characteristics Same as Type 6BX8. (4BX8 Designed for Series String TV Receivers.)									
4BZ6	T-5½	Pentode	7CM	4.2*	0.450	R-F Amp.	2.3	Characteristics Same as Type 6BZ6. (4BZ6 Designed for Series String TV Receivers.)									
4BZ7	T-6½	Duotriode	9AJ	4.2*	0.600	VHF Amp.	2.2	Characteristics Same as Type 6BZ7. (4BZ7 Designed for Series String TV Receivers.)									
4BZ8	T-6½	Duotriode	9AJ	4.2*	0.600	VHF Amp.	2.4	Characteristics Same as Type 6BZ8. (4BZ8 Designed for Series String TV Receivers.)									
4CB6	T-5½	Pentode	7CM	4.2*	0.450	VHF Amp.	2.3	Characteristics Same as Type 6CB6. (4CB6 Designed for Series String TV Receivers.)									
4CE5	T-5½	Pentode	7BD	4.2*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6CE5. (4CE5 Designed for Series String TV Receivers.)									
4CM4	T-6½	Triode	9KG	3.8	0.300	VHF Amp.	1.1	Characteristics Same as Type 6CM4. (4CM4 Designed for Series String TV Receivers.)									
4CS6	T-5½	Dual Control Heptode	7CH	4.2	0.450	Sync. Sep.	1.1	Characteristics Same as Type 6CS6. (4CS6 Designed for Series String TV Receivers.)									
4CX7	T-6½	Duotriode	9FC	4.2*	0.600	Amplifier	2.2	Characteristics Same as Type 6CX7. (4CX7 Designed for Series String TV Receivers.)									
4CY5	T-5½	Tetrode	7EW	4.5*	0.300	VHF Amp.	2.2	Characteristics Same as Type 6CY5. (4CY5 Designed for Series String TV Receivers.)									
4DE6	T-5½	Pentode	7CM	4.2*	0.450	VHF Amp.	2.3	Characteristics Same as Type 6DE6. (4DE6 Designed for Series String Receivers.)									
4DK6	T-5½	Pentode	7CM	4.2*	0.450	VHF Amp.	2.2	Characteristics Same as Type 6DK6. (4DK6 Designed for Series String TV Receivers.)									
4DT6	T-5½	Gated Beam	7EN	4.2*	0.450	Quad. F. M. Det.	1.65	Characteristics Same as Type 6DT6. (4DT6 Designed for Series String TV Receivers.)									
4DT6A	T-5½	Gated Beam	7EN	4.2*	0.450	Quad. F. M. Det.	1.7	Characteristics Same as Type 6DT6A. (4DT6A Designed for Series String Receivers.)									
4EH7	T-6½	Pentode	9AQ	4.4*	0.450	VHF Amp.	2.7	Characteristics Same as Type 6EH7. (4EH7 Designed for Series String Receivers.)									
4EJ7	T-6½	Pentode	9AQ	4.4*	0.450	VHF Amp.	2.7	Characteristics Same as Type 6EJ7. (4EJ7 Designed for Series String Receivers.)									



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Amplifi-cation Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
5CL8A	T-6½	Tri. Tetrode	9FX	4.7*	0.600	VHF Osc. VHF Amp.	2.97 3.0	Characteristics Same as Type 6CL8A. (5CL8A Designed for Series String Receivers.)									
5CM6	T-6½	Beam Pent.	9CK	4.7*	0.600	Power Amp	13.2	Characteristics Same as Type 6CM6. (5CM6 Designed for Series String TV Receivers.)									
5CM8	T-6½	Tri. Pentode	9FZ	4.7*	0.600	Class A1 Amp	1.1 2.2	Characteristics Same as Type 6CM8. (5CM8 Designed for Series String TV Receivers.)									
5CQ8	T-6½	Tri. Tetrode	9GE	4.7*	0.600	VHF Tri. Osc. VHF Pent. A.	2.79 3.0	Characteristics Same as Type 6CQ8. (5CQ8 Designed for Series String TV Receivers.)									
5CR8	T-6½	Tri. Pentode	9GJ	4.7*	0.600	Tri. Amp. Pent. Amp.	2.75 2.3	Characteristics Same as Type 6CR8. (5CR8 Designed for Series String Receivers.)									
5CU4	T-12	Duodiode	8KD	5.0♠	3.300	H-W Rect.	260 Volts A.C. Per Plate, RMS, 385 Ma. Output Current. Condenser Input to Filter.									
5CZ5	T-6½	Beam Pent.	9HN	4.7*	0.600	Vert. Defl. Amplifier	13.2	Characteristics Same as Type 6CZ5. (5CZ5 Designed for Series String TV Receivers.)									
5DH8	T-6½	Tri. Pentode	9EG	5.2*	0.600	Vert. Osc. Video Amp.	2.0 2.2	250 125	390 ^m 56 ^m 125	7.3 13.5 3.8	12000 150000	4400 8600	53
5DJ4	T-12	Duodiode	8KS	5.0♠	3.000	F-W Rect.	450 A.C. Volts Per Plate, RMS, 275 Ma. Output Current. Capacitor Input to Filter.									
5EA8	T-6½	Tri. Pentode	9AE	4.7*	0.600	Tri. VHF Amp. Pent VHF Amp.	3.0 3.1	Characteristics Same as Type 6EA8. (5EA8 Designed for Series String Receivers.)									
5EH8	T-6½	Tri. Pentode	9JG	4.7*	0.600	VHF Osc. VHF Amp.	2.75 3.0	Characteristics Same as Type 6EH8. (5EH8 Designed for Series String Receivers.)									
5ES8	T-6½	Duotriode	9AJ	5.6*	0.450	VHF Amp.	1.8	90	1.4	15	2500	12500
5EU8	T-6½	Tri. Pentode	9JF	4.7*	0.600	VHF Osc. VHF Amp.	3.1	Characteristics Same as Type 6EU8. (5EU8 Designed for Series String Receivers.)									
5EW6	T-5½	Pentode	7CM	5.6*	0.450	VHF Amp.	3.1	Characteristics Same as Type 6EW6. (5EW6 Designed for Series String Receivers.)									
5FG7	T-6½	Tri. Pentode	9GF	4.7*	0.600	VHF Osc./ Mixer	2.5 3.0	125 125	1.0 1.0 125	13 11 4	5700 180000	7500 6000	43
5FV8	T-6½	Tri. Pentode	9FA	4.7*	0.600	Vert. Osc. VHF Amp.	2.0 2.3	Characteristics Same as Type 6FV8. (5FV8 Designed for Series String Receivers.)									
5GH8	T-6½	Tri. Pentode	9AE	4.7*	0.600	Tri. Gen. Pur. Pentode Horiz. Osc.	2.5 2.5	Characteristics Same as Type 6GH8. (5GH8 Designed for Series String Receivers.)									
5GM6	T-5½	Pentode	7CM	5.6*	0.450	VHF Amp.	3.1	Characteristics Same as Type 6GM6. (5GM6 Designed for Series String Receivers.)									
5GX6	T-5½	Pentode	7EN	4.7*	0.600	Dual Control	1.7	Characteristics Same as Type 6GX6. (5GX6 Designed for Series String Receivers.)									
5J6	T-5½	Duotriode	7BF	4.7*	0.600	R-F Amp. Osc. Amp.	1.65	Characteristics Same as Type 6J6. (5J6 Designed for Series String TV Receivers.)									
5R4GY 5R4GYA 5R4GYB	ST-16 T-12	Duodiode	5T	5.0♠	2.000	F-W Rect.	900 Volts, RMS Per Plate, 150 Ma. D.C. Output. Condenser Input to Filter. 950 Volts, RMS Per Plate, 175 Ma. D.C. Output. Choke Input to Filter.									
5T4	Metal	Duodiode	5T	5.0♠	2.000	Rectifier	450 A.C. Volts Per Plate, RMS, 225 Ma. Output Current. Condenser Input to Filter. 550 A.C. Volts Per Plate, RMS, 225 Ma. Output Current. Choke Input to Filter.									
5T8	T-6½	Triple Dio. Tri.	9E	4.7*	0.600	Det. Amp.	1.1	Characteristics Same as Type 6T8 (5T8 Designed for Series String TV Receivers.)									
5U4G	ST-16	Duodiode	5T	5.0♠	3.000	F-W Rect.	450 A.C. Volts Per Plate, RMS, 225 Ma. Output Current. Condenser Input to Filter.									
5U4GA	T-11	Duodiode	5T	5.0♠	3.000	F-W Rect.	450 A.C. Volts Per Plate, RMS, 250 Ma. Output Current with Cap. Input to Filter. Peak Current = 900 Ma. Per Plate.									
5U4GB	T-12	Duodiode	5T	5.0♠	3.000	F-W Rect.	450 A.C. Volts Per Plate, RMS, 275 Ma. Output Current with Cap. Input to Filter. Peak Current = 1 Amp. Per Plate.									
5U4WG(3)	T-12	Duodiode	5T	5.0♠	3.000	F-W Rect.	Characteristics Same as Type 5U4G.									
5U8	T-6½	Tri. Pentode	9AE	4.7*	0.600	VHF Osc. VHF Mixer	2.5 3.0	Characteristics Same as Type 6U8. (5U8 Designed for Series String TV Receivers.)									
5V3	T-12	Duodiode	5T	5.0♠	3.800	F-W Rect.	425 A.C. Volts Per Plate, RMS, 350 Ma. Output Current. Capacitor Input to Filter. 500 A.C. Volts Per Plate, RMS, 350 Ma. Output Current. Choke Input to Filter.									
5V3A	T-12	Duodiode	5T	5.0♠	3.000	F-W Rect.	425 A.C. Volts Per Plate, RMS, 350 Ma. Output Current. Capacitor Input to Filter. 500 A.C. Volts Per Plate, RMS, 350 Ma. Output Current. Choke Input to Filter.									
5V4G	ST-14	Duodiode	5L	5.0	2.000	F-W Rect.	375 A.C. Volts Per Plate, RMS, 175 Ma. Output Current. Condenser Input to Filter.									



AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
5V4GA	T-12	Duodiode	5L	5.0	2.000	F-W Rect.	375 A.C. Volts Per Plate, RMS, 175 Ma. Output Current with Cap. Input to Filter. Peak Current = 525 Ma. per Plate.									
5V6GT	T-9	Beam Pent.	7S	4.7*	0.600	Power Amp.	13.2	Characteristics Same as Type 6V6GT. (5V6GT Designed for Series String TV Receivers.)									
5X8	T-6½	Tri. Pentode	9AK	4.7*	0.600	Oscillator Mixer	1.7 2.3	Characteristics Same as Type 6X8. (5X8 Designed for Series String TV Receivers.)									
5Y3GT 5Y3GA GB-5Y3WGTA(3)	T-9 T-12	Duodiode	5T	5.0†	2.000	F-W Rect.	350 A.C. Volts Per Plate, RMS, 125 Ma. Output Current. Condenser Input to Filter. 500 A.C. Volts Per Plate, RMS, 125 Ma. Output Current. Choke Input to Filter.									
5Y4GT 5Y4GA	T-9 T-12	Duodiode	5Q	5.0†	2.000	F-W Rect.	Characteristics Same as Type 5Y3GT.									
5Z3	ST-16	Duodiode	4C	5.0†	3.000	F-W Rect.	450 A.C. Volts Per Plate, RMS, 225 Ma. Output Current. Condenser Input to Filter.									
5Z4 5Z4GT	Metal T-9	Duodiode	5L 5L	5.0	2.000	F-W Rect.	350 A.C. Volts Per Plate, RMS, 125 Ma. Output Current. Condenser Input to Filter.									
6A3	ST-16	Power Triode	4D	6.3†	1.000	S.T. A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	16.5	250 325 325	45.0 68.0	60.0 80-147†	800 700000 360000	5250 5000 550*	4.2	2500 3000† 5000†	3200 15000 10000
6A7	ST-12	Heptode	7C	6.3	0.300	Converter	1.1	Characteristics Same as Type 6A8G, Except Capacitances.									
6A8 6A8G 6A8GT	Metal ST-12 T-9	Heptode	8A	6.3	0.300	Converter	1.1	100 250	1.5 3.0	50 100	1.1 3.5	1.3 2.7	600000 360000	360* 550*	(Ga = 100V.) (Ga = 250 V. thru 20 K. Ohm)		
6AB4	T-5½	Triode	5CE	6.3	0.150	R-F Amp.	2.75	250	200	10	10900	5500	60
6AB7	Metal	Pentode	8N	6.3	0.450	Amplifier	4.12	300	3.0	200	12.5	3.2	700000	5000	3500
6AB8	T-6½	Tri. Pentode	6AB8	6.3	0.300	A-F Amp. S.T.A1 Amp.	1.0	100 170	2.3 6.3 170	4 15 2.8	12500 150000	1400 3300	17	11000	1000
6AC7	Metal	Pentode	8N	6.3	0.450	Video Amp.	3.3	300	160	150	10.0	2.5	1.0 Meg.	9000	6750
6AD4	T-3	Triode	8DK	6.3	0.150	Osc. Amp.	0.33	100	820	1.4	35000	2000	70
6AD6G	T-9	Electron Ray	7AG	6.3	0.150	Indicator	100 (Ray Control Volts = 45 Approx. For 0° Shadow, Approx. = 23 Volts for 135° Shadow.) 150 (Ray Control Volts = 75 Approx. For 0° Shadow, Approx. = 50 Volts for 135° Shadow.)									
6AF3	T-6½	Diode	9CB	6.3	1.200	T.V. Dampener	6.0	Maximum Peak Inverse Plate Voltage = 4500 Volts. Maximum D.C. Plate Current = 185 Ma.									
6AF4A 6AF4	T-5½	Triode	7DK	6.3	0.225	UHF Osc.	2.5	100	Grid Resistor = 10,000 Ohms.		Plate Resistor = 220 Ohms. Grid Current = 750 μA.						
6AF6G	T-9	Twin Elec. Ray	7AG	6.3	0.150	Indicator	100 (Ray Control Volts = Approx. 60 for 0° Shadow, Approx. Zero Volts for 100° Shadow.) 135 (Ray Control Volts = Approx. 81 for 0° Shadow, Approx. Zero Volts for 100° Shadow.)									
6AF11	Comp. T-9	Pentode Duotriode	12DP	6.3	1.050	Video Amp. AGC Keyer Sync. Sep.	5.0 1.1 2.0	250 200 200	100 2.0 220	150	24 7.0 9.2	4.8	68000 12400 9400	11000 5500 4400 68 41
6AG5	T-5½	Pentode	7BD	6.3	0.300	R-F Amp.	2.2 2.75	100 125 250	180 100 180	100 125 150	4.5 7.2 6.5	1.4 2.1 2.0	600000 500000 800000	4500 5100 5000
6AG7	Metal	Pentode	8Y	6.3	0.650	Video Amp.	9.9	300	3	150	30.0	7.0	130000	11000	10000	3000
6AG11	Comp. T-9	Duodiode Duotriode	12DA	6.3	0.750	FM Multiplex Service	2.0	125	1.0	7.5	8500	7800	66
6AH4GT	T-9	Triode	8EL	6.3	0.750	Defl. Amp.	8.25	250	23	30	1780	4500	8
6AH6	T-5½	Pentode	7BK	6.3	0.450	Pent. Amp. Tri. Amp.	3.52	300 150	160 160	150	10 12.5	2.5	500000 3600	9000 11000 40
6AJ4	T-6½	Triode	9BX	6.3	0.225	UHF Amp.	2.2	125	68	16	4200	10000	42
6AJ5	T-5½	Pentode	7BD	6.3	0.175	R-F Amp.	1.87	28	1.0	28	2.7	1.0	100000	2500
6AK4	T-3	Triode	8DK	6.3	0.125	UHF Amp.	3.3	200	680	9.5	5300	3800	20
6AK5	T-5½	Pentode	7BD	6.3	0.175	VHF Amp.	1.87	120 180	180 180	120 120	7.5 7.7	2.5 2.4	300000 500000	5000 5100	1700 3500


(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. †† Filamentary Type. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ††† Plate to Plate. †††† Cathode Resistor (ohms).



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6AW8	T-6½	Tri. Pentode	9DX	6.3*	0.600	Tri. Amp.	1.1	200	2.0	4.0	...	17500	4000	70
6AW8A						Pent. Video Amp.	3.57	150	150 [■]	150	15	3.5	200000	9500
6AW8 and 6AW8A are Similar Except for Plate Knee Characteristics of 6AW8A.																	
6AX3	Comp. T-9	Diode	12BL	6.3	1.200	T.V. Damper	5.3	Maximum Peak Inverse Plate Voltage = 5000 Volts, Maximum D.C. Output Current = 165 Ma.									
6AX4GT	T-9	Diode	4CG	6.3	1.200	T.V. Damper	5.28	P.I.V. = 4400 Volts Max., D.C. Plate Current = 125 Ma. Max.									
6AX4GTA	T-9	Diode	4CG	6.3	1.200	T.V. Damper	5.28	P.I.V. = 4400 Volts Max., D.C. Plate Current = 165 Ma.									
6AX5GT	T-9	Duodiode	6S	6.3	1.200	F-W Rect.	350 A.C. Volts Per Plate, R.M.S., 125 Ma. D.C. Output. Condenser Input to Filter. 450 A.C. Volts Per Plate, R.M.S., 125 Ma. D.C. Output. Choke Input to Filter.									
6AX7	T-6½	Duotriode	9A	6.3/ 3.15*	0.300/ 0.600	A-F Amp.	1.1	Characteristics Same as Type 12AX7. (6AX7 Designed for Series String TV Receivers.)									
6AX8	T-6½	Tri. Pentode	9AE	6.3	0.450	Sync. Sep. Video Amp.	2.97 3.0	150 250	56 [■] 120 [■] 110	18 10 3.5	5000 400000	8500 4800	40
6AY3	Novar	Diode	9HP	6.3	1.200	T.V. Damper	6.5	Maximum Peak Inverse Plate Voltage = 5000 Volts, Maximum D.C. Plate Current = 175 Ma.									
6AY3A	T-9																
6AZ5	T-3	Duodiode	8DF	6.3	0.150	Rectifier	Plate Supply Voltage = 50 Volts, RMS, Each Plate. D.C. Output Current = 4 Ma. Each Plate. Capacitor Input to Filter.									
6AZ8	T-6½	Tri. Pentode	9ED	6.3	0.450	Sync. Sep. Video Amp.	2.86 2.2	200 200	6 180 [■] 150	13.0 9.5 3.0	5750 300000	3300 6000	19
6B3	T-6½	Diode	9BD	6.3	1.200	T.V. Damper	Maximum Peak Inverse Plate Voltage = 4400 Volts. Maximum D.C. Plate Current = 150 Ma.									
6B4G	ST-16	Triode	5S	6.3 [†]	1.000	Power Amp.	16.5	Characteristics Same as Type 6A3.									
6B8	Metal	Duodi. Pent.	8E	6.3	0.300	Det. Amp.	3.3	Characteristics Same as Type 6B7, Except Capacitances.									
6B10	Comp. T-9	Duodiode	12BF	6.3*	0.600	Horiz. Phase Det./Osc.	3.0	250	8.0	10	7200	2500	18
6BA3	T-9	Diode	9HP	6.3	1.200	T.V. Damper	5.3	Maximum Peak Inverse Plate Voltage = 5000 Volts. Maximum D.C. Output Current = 165 Ma.									
6BA5	T-3	Pentode	8DY	6.3	0.150	A-F Amp.	0.77	100	270 [■]	100	5.5	2.0	175000	2150
6BA6	T-5½	Pentode	7BK	6.3	0.300	R-F Amp.	3.3	100 250	68 [■] 68 [■]	100 100	10.8 11.0	4.4 4.2	250000 1.0 Meg.	4300 4400
6BA7	T-6½	Heptode	8CT	6.3	0.300	Converter	2.2	100 250	1.0 1.0	100 100	3.6 3.8	10.2 10.0	500000 1 Meg.	900 [▲] 950 [▲]
6BA8	T-6½	Tri. Pentode	9DX	6.3*	0.600	Tri. Amp.	2.2	200	8.0	8.0	6700	2700	18
6BA8A	T-6½					Pent. Video Amp.	3.57	200	180 [■]	150	13.0	3.5	400000	9000
6BA8 and 6BA8A are Similar Except for Plate Knee Characteristics of 6BA8A.																	
6BC5	T-5½	Pentode	7BD	6.3	0.300	Tri. Amp.	2.75	250	820 [■]	6.0	9000	4400	40
						Pent. Amp.	2.2	180 100 125 250	330 [■] 180 [■] 100 [■] 180 [■] 100 125 150	8.0 4.7 8.0 7.5 1.4 2.4 2.1	6000 600000 500000 800000	6000 4900 6100 5700	42
6BC7	T-6½	Triple Diode	9AX	6.3	0.450	F. M. Det.	High Perveance Diode.									
6BC8	T-6½	Duotriode	9AJ	6.3	0.400	Det. Amp.	2.2	150	220 [■]	10.0	5300	6200	35
6BD4	T-12	Beam Triode	8FU	6.3	0.600	Hi-Volt. Reg.	22	20000 Max. D.C. Plate Volts. 125 Max. D.C. Grid Volts. 1.5 Ma. Max. D.C. Plate Current.									
6BD4A	T-12	Beam Triode	8FU	6.3	0.600	Hi-Volt. Reg.	27.5	27000 Max. D.C. Plate Volts. 125 Max. D.C. Grid Volts. 1.5 Ma. Max. D.C. Plate Current.									
6BD5GT	T-9	Beam Pent.	6CK	6.3	0.900	Horiz. Defl. Amp.	11	Max. Peak Positive Pulse Plate Voltage = 4000 Volts. Max. D.C. Cathode Current = 100 Ma.									
6BD6	T-5½	Pentode	7BK	6.3	0.300	R-F Amp.	3.3	250 100	3.0 1.0	100 100	9.0 13	3.5 5.0	700000 120000	2000 2350
6BE6	T-5½	Heptode	7CH	6.3	0.300	Converter	1.1	100 250	1.5 1.5	100 100	2.6 2.9	7.0 6.8	400000 1.0 Meg.	455 [▲] 475 [▲]	(Osc. Grid Res. = 20000 Ohms) (Osc. Grid Current 0.5 Ma.)		
6BE8	T-6½	Tri. Pentode	9EG	6.3	0.450	VHF Osc.	2.75	150	56 [■]	18.0	5000	8500	40
6BE8A	T-6½			6.3*	0.450	VHF Amp.	3.0	250	68 [■]	110	10.0	3.5	400000	5200
6BF5	T-5½	Pentode	7BZ	6.3	1.200	S.T.A1 Amp.	6.0	110	7.5	110	36	4	12000	7500	2500	1900
6BF6	T-5½	Duodiode Tri.	7BT	6.3	0.300	Det. Amp.	2.75	250	9.0	9.5	8500	1900	16	10000	300

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ‡ Filamentary Type. ▲ Conversion Transconductance. ¶ Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6BF7W (3)	T-3	Duotriode	8DG	6.3	0.300	R-F Amp.	1.1	100	100 [■]	8.0	7000	4800	35
6BF8	T-6½	Sextuple Diode	9NX	6.3	0.450	Shunt Detector	Maximum Peak Inverse Plate Voltage = 165 Volts. Maximum Peak Plate Current, Per Plate = 11 Ma., Maximum D.C. Output Current = 2.2 Ma.									
6BG6GA	T-12	Beam Pent.	5BT	6.3	0.900	Horiz. Defl. Amp.	22	Maximum Peak Positive Plate Voltage = 6600 Volts. Maximum D.C. Cathode Current = 110 Ma.									
6BH3	Novar T-9	Diode	9HP	6.3	1.600	T.V. Damper	6.5	Maximum Peak Inverse Plate Voltage = 5500 Volts. Maximum D.C. Plate Current = 180 Ma.									
6BH6	T-5½	Pentode	7CM	6.3	0.150	R-F Amp.	3.3	100	1.0	100	3.6	1.4	0.7 Meg.	3400
6BH8	T-6½	Tri. Pentode	9DX	6.3*	0.600	Tri. Amp. Pent. Amp.	2.75	150	5	9.5	5150	3300	17
6BJ5	T-5½	Pentode	6CH	6.3	0.640	Power Amp.	9.9	250	5.0	250	3.5	5.5	40000	10500	450	7000	4000
6BJ6	T-5½	Pentode	7CM	6.3	0.150	R-F Amp.	3.3	250	1.0	100	9.2	3.3	1.3 Meg.	3600
6BJ7	T-6½	Triple Diode	9AX	6.3	0.450	TV DC Rest'r	Each Section Similar to Each Section of a 6AL5.									
6BJ8	T-6½	Duodiode Tri.	9ER	6.3*	0.600	Det. Amp.	3.85	90	0	13.5	4700	4700	22
6BK4	T-12	Beam Triode	8GC	6.3	0.200	Hi-Volt. Reg.	27.5	25000 Maximum D.C. Plate Volts. 125 D.C. Grid Volts. 1.5 Ma. Maximum D.C. Plate Current.									
6BK5	T-6½	Beam Pent.	9BQ	6.3	1.200	Power Amp.	9.9	250	5.0	250	3.5	3.5	0.1 Meg.	8500	6500	3500
6BK7A	T-6½	Duotriode	9AJ	6.3	0.450	VHF Amp.	2.97	150	56 [■]	18.0	4600	9300	43
6BK7B	T-6½	Duotriode	9AJ	6.3*	0.450	VHF Amp.	2.97	150	56 [■]	18.0	4600	9300	43
6BL4	T-12	Diode	8GB	6.3	3.000	T.V. Damper	8.8	P.I.V. = 4500 Volts Abs. Max. D.C. Plate Current = 200 Ma. Max.									
6BL7GT	T-9	Duotriode	8BD	6.3	1.500	Vert. Osc. Vert. Defl. Amp.	11	250	9	40	2150	7000	15
6BL7GTA	T-9	Duotriode	8BD	6.3	1.500	Vert. Osc. Vert. Defl. Amp.	13.2	250	9	40	2150	7000	15
6BL8	T-6½	Tri. Pentode	9DC	6.3	0.450	VHF Osc. VHF Amp.	1.65	100	2.0	14.0	5000	6200	20
6BM8	T-6½	Tri. Pentode	9EX	6.3	0.780	Pent. Vert. Defl. Amp. Tri. Vert. Osc.	5.5	200	16.0	200	35.0	7.0	20000	6400	9.5
6BN4A	T-5½	Triode	7EG	6.3	0.200	VHF Amp.	2.42	150	220 [■]	9	8000	5400	43
6BN6	T-5½	Gated Beam	7DF	6.3	0.300	Quad. F. M. Det.	65	1.3	60	0.23	5.0	Grid No. 1 Signal Voltage (RMS) = 30 Volts. Grid No. 3 Signal Voltage (RMS) = 4 Volts.				
6BN8	T-6½	Duodiode Tri.	9ER	6.3*	0.600	Det. Amp.	1.65	100	1	1.5	21000	3500	75
6BQ5	T-6½	Beam Pent.	9CV	6.3	0.760	S.T. A1 Amp. P.P. AB1 Amp. P.P. AB1 Amp.	13.2	250	135 [■]	250	48	5.5	38000	11300	5200	5700
6BQ6GTA	T-9	Beam Pent.	6AM	6.3	1.200	Horiz. Defl. Amp.	12.1	6000	22.5	150	57	2.1	14500	5900
6BQ7A	T-6½	Duotriode	9AJ	6.3	0.400	VHF Amp.	2.2	150	220 [■]	9	5800	6000	38
6BR8A	T-6½	Triode Pentode	9FA	6.3*	0.450	Oscillator Mixer	2.97	150	56 [■]	18	5000	8500	40
6BS8	T-6½	Duotriode	9AJ	6.3	0.400	VHF Amp.	2.2	150	220 [■]	10	5000	7200	36
6BT8	T-6½	Duodi. Pent.	9FE	6.3	0.450	Amp. Det.	2.2	200	180 [■]	150	9.5	2.8	30000	6200
6BU4	T-12	Triode	8GC	6.3	0.450	H.V. Reg.	27.5	25000	8.4	1.0	8.2 Meg.	185	1515
6BU5	T-11	Beam Power Pentode	8FP	6.3	0.150	H.V. Reg.	20	20K	3.4	70	0.6
6BU8	T-6½	Duo Pentode	9FG	6.3	0.300	Sync. Sep.	1.1	100	0 Grid 1	67.5	180 Gr. 3	Grid No. 3 Volts = -4.5
6BU8A	T-6½	Duo Pentode	9FG	6.3	0.300	Sync. Sep.	1.1	100	67.5	2.2	1500 Gr. 1	Grid No. 1 Volts = -2.3
6BV8	T-6½	Duodiode Tri.	9FJ	6.3*	0.600	Det. Amp.	2.7	200	330 [■]	11.0	5900	5600	33
6BW4	T-6½	Duodiode	9DJ	6.3	0.900	F-W Rect.	325 A.C. Volts Per Plate, RMS, 100 Ma. Output Current. Capacitor Input to Filter. 450 A.C. Volts Per Plate, RMS, 100 Ma. Output Current. Choke Input to Filter.									



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Res. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6BW8	T-6½	Duodi. Pent.	9HK	6.3*	0.450	R-F or I-F Amplifier	3.0	250	68 [¶]	110	10.0	3.5	250000	5200
6BX7GT	T-9	Duotriode	8BD	6.3	1.500	Vert. Amp. Vert. Osc.	11 13.2	Max. Peak Positive Pulse Plate Volts = 2000 Volts.	42	1300	7600	10
6BX6	T-6½	Pentode	9AQ	6.3	0.300	R-F/I-F Amp.	2.75	170	2.0	170	10	2.5	400000	7200
6BX8	T-6½	Duotriode	9AJ	6.3	0.400	VHF Amp.	2.0	65	1.0	9	6700	25
6BY5G	ST-14	Duodiode	6CN	6.3	1.600	F-W Rect.	375 A.C. Volts Per Plate, R.M.S., 175 Ma. D.C. Output Current.
6BY5GA	T-12	Duodiode	6CN	6.3	1.600	T.V. Damp.	P.I.V. = 3000 Volts Abs. Max. D.C. Plate Current = 175 Ma. Max. Each Plate.
6BY6	T-5½	Heptode	7CH	6.3	0.300	Sync. Sep.	2.2	10	G1&2=0	25	1.4	3.5	Plate Current = 50µ Amps. When Grid 3 V. = 2.5
6BY8	T-6½	Diode Pent.	9FN	6.3*	0.600	Det. Amp.	3.3	100	150 [¶]	100	5.0	2.1	500000	3900
6BZ6	T-5½	Pentode	7CM	6.3	0.300	R-F Amp.	2.3	125	56 [¶]	125	14	3.6	260000	8000	Semi-Remote Cutoff.
6BZ7	T-6½	Duotriode	9AJ	6.3	0.400	VHF Amp.	2.2	150	220 [¶]	10	5300	6800	36
6BZ8	T-6½	Duotriode	9AJ	6.3	0.400	VHF Amp.	2.42	125	100 [¶]	10	5600	8000	45
6C4	T-5½	Triode	6BG	6.3	0.150	R-F Osc. R-F Amp.	5.5 3.85	300 250	27 8.5	25 10.5	7700 6250	2200 3100	17 19.5	Class C 5500
6C5	Metal T-9	Triode	6Q	6.3	0.300	Amplifier	2.75	250	8.0	8.0	10000	2000	20
6C5GT
6C6	ST-12	Pentode	6F	6.3	0.300	Amplifier	.825	100	3.0	100	2.0	0.5	1 Meg.	1185
6C6	1 Meg.>	1225
6C8G	ST-12	Duotriode	8G	6.3	0.300	Amplifier Inverter	1.1	250	4.5	3.2	22500	1600	36	(One Section)
6C9	T-6½	Duotetrode	10F	6.3	0.400	VHF Amp.	2.5	125	1.0	80	10	1.5	100000	8000
6C10	Comp. T-9	Triple Triode	12BQ	6.3*	0.600	A-F Amp.	1.0	Characteristics Same as Type 12AX7.									
6CA4	T-6½	Duodiode	9M	6.3	1.000	F-W Rect.	350 A.C. Volts Per Plate, RMS, 150 Ma. Output Current.									
6CA5	T-5½	Beam Pent.	7CV	6.3	1.200	Power Amp.	5.5	110	4.0	110	32	3.5	16000	8100	3500	1100
6CA5	125	4.5	125	37	4.0	15000	9200	4500	1500
6CA7	T-10 (SP)	Beam Pent.	8ET	6.3	1.500	Power Amp.	27.5	Characteristics Same as Type EL34.									
6CB5A	T-12	Beam Pent.	8GD	6.3	2.500	Horiz. Defl. Amp.	25	6800 Maximum Peak Positive Pulse Plate Volts.									
6CB5A	175	30	175	90	6.0	5000	8800
6CB6A	T-5½	Pentode	7CM	6.3*	0.300	VHF Amp.	2.3	125	56 [¶]	125	13	3.7	280000	8000
6CD6G	ST-16	Beam Pent.	5BT	6.3	2.500	Horiz. Defl. Amp.	16.5	Maximum Peak Positive Pulse Plate Voltage = 6600 Volts. Maximum D.C. Plate Current = 200 Ma.									
6CD6GA	T-12	Beam Pent.	5BT	6.3	2.500	Horiz. Defl. Amp.	22	7000 Maximum Peak Positive Pulse Plate Volts. 200 Ma. Max. Cathode Current.									
6CE5	T-5½	Pentode	7BD	6.3	0.300	VHF Amp.	2.2	125	1.0	125	111	3.7	1.0 Meg.	7600
6CF6	T-5½	Pentode	7CM	6.3	0.300	VHF Amp.	2.3	125	56 [¶]	125	12.5	3.7	0.3 Meg.	7800
6CG7	T-6½	Duotriode	9AJ	6.3*	0.600	Amplifier	3.85	Characteristics Same as Type 6SN7GT. (6CG7 Designed for Series String TV Receivers.)									
6CG8	T-6½	Tri. Pentode	9GF	6.3	0.450	Osc. Mixer	1.7	125	1.0	12	6000	6500	40
6CG8A	T-6½	Tri. Pentode	9GF	6.3*	0.450	Osc. Mixer	2.3	125	1.0	125	9.	2.2	.3 Meg.	5500
6CH7	T-6½	Duotriode	9FC	6.3	0.400	Amplifier	2.2	150	220 [¶]	10	5300	6800	36
6CH8	T-6½	Tri. Pentode	9FT	6.3	0.450	Tri. Amp. Pent. Amp.	2.82 2.2	200 200 180 [¶] 150	13.0 9.5 2.8	5750 300000	3300 6200	19
6CK4	T-9	Power Triode	8JB	6.3	1.250	Vert. Defl. Amp.	12	Max. Peak Positive Pulse Plate Voltage = 2000 Volts. Max. D.C. Cathode Current = 100 Ma.									
6CK4	250	28	40	1200	5500	6.6
6CL5	T-12	Beam Pent.	8GD	6.3	2.500	Horiz. Defl.	27.5	7000 Maximum Peak Positive Pulse Plate Volts. 25 Watts Maximum Plate Dissipation. 4.0 Watts Maximum Screen Dissipation.									
6CL6	T-6½	Power Pent.	9BV	6.3	0.650	Video Amp.	8.25	250	3	150	30	7	0.15 Meg.	11000

- (1) See Frontal Section. (2) Design Maximum Values. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
- † Maximum Signal. ‡ Filamentary Type. ¶ Conversion Transconductance. †† Plate to Plate. ††† Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Res. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6CL8A	T-6½	Tri. Tetrode	9FX	6.3*	0.450	VHF Osc. VHF Amp.	2.97 3.0	125 125	1.0 1.0	125 125	14 12	4 4	5000 200000	8000 6500	40 68
6CM4	T-6½	Triode	9KG	6.3	0.170	VHF Amp.	2.2	175	1.5	12	14000	68
6CM5	T-9	Beam Pent.	8GT	6.3	1.250	Horiz. Defl. Amp.	11	100	7.7	100	100	7.0	5000 3300	8000 14000	40 68
6CM6	T-6½	Beam Pent.	9CK	6.3	0.450	Vert. Defl. Amp. Power Amp.	8.8 13.2	250 180 250 315	12.5 8.5 12.5 13.0	250 180 250 225	45 29.0 45.0 34.0	4.5 3.0 4.5 2.2	50000 50000 50000 80000	4100 3700 4100 3750	5500 5000 5000 8500	2000 4500
6CM7	T-6½	Duotriode	9ES	6.3*	0.600	Sept. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	6.0 1.37	250 200	8.0 7.0	20.0 5.0	4100 11000	4400 2000	18 20
6CM8	T-6½	Tri. Pentode	9FZ	6.3*	0.450	Class A1 Amp.	1.1 2.2	250 200	2 180	150	1.8 9.5	2.8	50000 600000	2000 6200	100
6CN7	T-6½	Duodiode Tri.	9EN	6.3	0.300	Det. Amp.	1.1	100 250	1.0 3.0	0.8 1.0	54000 58000	1300 1200	70 70
6CQ4	T-9	Diode	4CG	6.3	1.600	T.V. Damper	6.5
6CQ8	T-6½	Tri. Tetrode	9GE	6.3*	0.450	VHF Tri. Osc. VHF Tet. Amp	2.97 3.0	125 125	56 ^m 1.0	125 125	15 12	5000 140000	8000 5800	40
6CR4	T-6½	Triode	9BX	6.3	0.370	UHF Amp.	130	1.0	16	15000	60
6CR6	T-5½	Diode Pent.	7EA	6.3	0.300	Det.-Audio Amplifier	2.75	250	2.0	100	9.5	3.0	200000	1950
6CR8	T-6½	Tri. Pentode	9GJ	6.3*	0.450	Tri. Amp. Pent. Amp.	2.75 2.3	125 125	2.0 56 ^m 125	12.0 13.0	3.0	5000 300000	4000 7700	22
6CS6	T-5½	Dual Control Heptode	7CH	6.3	0.300	Sync. Sep.	1.1	100 100	0 Grid 1 -1 Grid 1	30 30	0.8 1.0	5.5 1.3	0.7 Meg. 1.0 Meg.	1500 Gr. 3 1100 Gr. 1	Grid No. 3 Volts = -1.0 Grid No. 3 Volts = 0.
6CS7	T-6½	Duotriode	9EF	6.3*	0.600	Sept. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	1.37	250 250	10.5 8.5	19.0 10.5	3450 7700	4500 2200	15.5 17
6CS8	T-6½	Tri. Pentode	9FZ	6.3*	0.450	Tri. Amp. Pent. Amp.	2.75 2.3	125 125	2.0 56 ^m	125	12.0 13.0	3.0	5000 300000	4000 7700	22
6CU5	T-5½	Pentode	7CV	6.3	1.200	Power Amp.	6.6	120	8	110	49	4	10000	7500	2500	2300
6CU6	T-12	Beam Pent.	6AM	6.3	1.200	Horiz. Amp.	12.1
6CU8	T-6½	Tri. Pentode	9GM	6.3*	0.450	Tri. Amp. Pent. Amp.	2.82 2.2	125 125	1.0 56 ^m	125	17 12	3.8	4100 170000	5800 7800	17
6CW4	M-N	Triode	12AQ	6.3	0.135	VHF Amp.	1.0	70	47K ⁴	8	12500	5440	68
6CW5	T-6½	Beam Pent.	9CV	6.3	0.760	S.T. A1 Amp. S.T. A1 Amp. P.P.AB1 Amp.	13	100 170 170	6.7 12.5 120 ^m	100 170 170	43 70	3 5	23000	9000	2400 2400 3500 [†]	1900 5600 13000
6CX7	T-6½	Duotriode	9FC	6.3	0.400	Amplifier	2.2	150	220 ^m	9.0	6400	39
6CX8	T-6½	Tri. Pentode	9DX	6.3	0.750	Tri. Amp. Video Amp.	2.0 5.0	150 200	150 ^m 68 ^m	125	9.2 24	5.2	8700 70000	4600 10000	40
6CY5	T-5½	Tetrode	7EW	6.3	0.200	VHF Amp.	2.0	125	1.0	80	10.0	1.5	100000	8000
6CY7	T-6½	Duotriode	9LG	6.3	0.750	Vert. Osc. Vert. Defl. A.	1.0 5.5	250 150	3 620 ^m	1.2 30	52000 920	1300 5400	68 5
6CZ5	T-6½	Beam Pent.	9HN	6.3*	0.450	Vert. Defl. Amp.	11	250	14	250	46.0	4.6	73000	4800
6D4	T-5½	Gas Triode	5AY	6.3	0.250	Relay Tube	350	50
6D6	ST-12	Pentode	6F	6.3	0.300	Amplifier	2.47	100 250	3.0 3.0	100 100	8.0 8.2	2.2 2.0	250000 800000	1500 1600



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6D10	Comp. T-9	Triple Triode	12BQ	6.3	0.450	VHF R-F/Osc./Mixer	2.0	Characteristics Same as Type 6E28.									
6DA4	T-9	Diode	4CG	6.3	1.200	T.V. Damper	5.5	Max. Peak Inverse Plate Voltage = 4400 Volts. Max. D.C. Plate Current = 155 Ma.									
6DA4A	T-9	Diode	4CG	6.3	1.200	T.V. Damper	8.0	Max. Peak Inverse Plate Voltage = 5000 Volts. Max. D.C. Plate Current = 185 Ma.									
6DA7	T-6½	Duotriode	9EF	6.3	1.000	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	2.2	Max. Peak Positive Pulse Plate Voltage = 1800 Volts. Max. D.C. Cathode Current = 40 Ma.									
							6.6	150	17.5	40.0	1100	5700	6.3
								250	8.0	9.0	7700	2600	20
6DB5	T-6½	Beam Pent.	9GR	6.3	1.200	Vert. Defl. Amp.	11	Max. Peak Positive Pulse Plate Voltage = 2000 Volts. Max. D.C. Cathode Current = 55 Ma.									
								200	180	125	46.0	2.2	28000	8000
6DB6	T-5½	Pentode	7CM	6.3	0.300	Color Demod.	3.3	150	1.0	150	5.8	6.6	50000	2050	μmhos when Eg3 = -3 Volts.		
6DC6	T-5½	Pentode	7CM	6.3	0.300	Amplifier	2.2	200	180	150	9.0	3.0	500000	5500	Semi-Remote Cutoff.		
6DC8	T-6½	Duodi. Pent.	9HE	6.3	0.300	R-F Amp.	2.47	200	1.5	100	11	3.3	.6 Meg.	4500		
6DE4	T-9	Diode	4CG	6.3	1.600	T.V. Damper	6.5	P.I.V. = 5500 Volts Max., D.C. Plate Current = 180 Ma. Max.									
6DE6	T-5½	Pentode	7CM	6.3	0.300	VHF Amp.	2.3	125	56	125	15.5	4.2	250000	8000		
6DE7	T-6½	Duotriode	9HF	6.3	0.900	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	7.0	Max. Peak Positive Plate Voltage = 1500 Volts. Max. Cathode Current = 50 Ma.									
							1.5	150	17.5	35.0	925	6500	6
								250	11.0	5.5	8750	2000	17.5
6DG6GT	T-9	Beam Pent.	7S	6.3	1.200	Power Amp.	11	110	7.5	110	49	4.0	13000	8000	2000	2100
								200	180	125	46	2.2	28000	8000	4000	3800
6DG7	T-6½	Pentode	9BA	6.3	0.300	R-F or I-F Amplifier	3.3	100	68	100	10.8	4.4	250000	4300		
								250	68	100	11.0	4.2	1 Meg.	4400		
6DJ8	T-6½	Duotriode	9AJ	6.3	0.365	VHF Amp.	1.98	90	1.3	15	2700	12500	33	
6DK6	T-5½	Pentode	7CM	6.3	0.300	VHF Amp.	2.2	125	56	125	12.0	3.8	9800		
6DM4	T-9	Diode	4CG	6.3	1.200	T.V. Damper	6.5	Max. Peak Inverse Plate Voltage = 5000 Volts. Max. D.C. Plate Current = 175 Ma.									
6DN6	T-12	Beam Pent.	5BT	6.3	2.500	Horiz. Defl. Amp.	16.5	Max. Peak Positive Pulse Plate Voltage = 6600 Volts. Max. D.C. Cathode Current = 200 Ma.									
								125	18	125	70	6.3	4000	9000		
6DN7	T-9	Duotriode	8BD	6.3	0.900	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	10	Max. Peak Positive Pulse Plate Voltage = 2500 Volts. Max. D.C. Cathode Current = 50 Ma.									
							1.0	250	9.5	41	2000	7700	15.4
								250	8	8.0	9000	2500	22.5
6DQ4	T-9	Diode	4CG	6.3	1.200	T.V. Damper	6.0	Max. Peak Inverse Plate Voltage = 5500 Volts. Max. Peak Plate Current = 1000 Ma.									
								Max. D.C. Output Current = 175 Ma.									
6DQ5	T-12	Beam Pent.	8JC	6.3	2.500	Horiz. Defl. Amplifier	26.4	Max. Peak Positive Pulse Plate Voltage = 7000 Volts. Max. D.C. Cathode Current = 285 Ma.									
								175	25	125	110	5	5500	10500		
6DQ6A	T-12	Beam Pent.	6AM	6.3	1.200	Horiz. Defl. Amplifier	18	6000 Max. Peak Positive Plate Volts. 155 Ma. Max. Cathode Current.									
								250	22.5	150	55	1.5	20000	6600		
6DQ6B	T-12	Beam Pent.	6AM	6.3	1.200	Horiz. Defl. Amplifier	18	Max. Peak Positive Pulse Plate Voltage = 6500 Volts. Max. D.C. Cathode Current = 175 Ma.									
								250	22.5	150	65	1.8	18000	7300	4.4	G1 to G2	
6DR4	T-5½	Triode	6BG	6.3	0.150	A-F Amp.	1.2	100	1.0	0.5	80000	1250	100	
								250	2.0	1.2	62500	1600	100	
6DR7	T-6½	Duotriode	9HF	6.3	0.900	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc.	7.0	Max. Peak Positive Pulse Plate Voltage = 1500 Volts. Max. Cathode Current = 50 Ma.									
							1.0	150	17.5	35	925	6500	6
								250	3	1.4	40000	1600	68
6DS4	M-N	Triode	12AQ	6.3	0.135	VHF Amp.	1.0	110	130	6.5	6900	9000	62	
6DS5	T-5½	Beam Pent.	7BZ	6.3	0.800	Power Amp.	8.8	200	180	200	34.5	3.5	28000	6000	6000	2800
								250	270	200	27	3	28000	5800	8000	3600
6DT5	T-6½	Beam Pent.	9HN	6.3	1.200	Vert. Defl. Amp.	9.0	Max. Peak Positive Plate Voltage = 2200 Volts. Max. D.C. Cathode Current = 55 Ma.									
							9.0	250	16.5	250	44	1.5	6200		

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. †† Filamentary Type. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ††† Plate to Plate. †††† Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6DT6	T-5½	Gated Beam	7EN	6.3	0.300	Quad. F. M. Det. FM Det.	1.65	150	560 ^m	100	1.1	2.1	150000	615 Gr. #1 515 Gr. #3	4.5 Gr. #1 for 10 μA IB 3.5 Gr. #3 for 10 μA IB		
6DT6A	T-5½	Pentode	7EN	6.3	0.300		1.7	150	560 ^m	100	1.55	1.8	150000	1350			
6DT8	T-6½	Duotriode	9AJ	6.3	0.300	Amplifier	2.75	100 250	270 ^m 200 ^m	...	3.7 10	...	15000 10900	4000 5500	60 60		
6DW4	Novar T-9	Diode	9HP	6.3	1.200	T.V. Damper	6.5	Max. Peak Inverse Plate Voltage = 4500 Volts.				Max. D.C. Output Current = 210 Ma.					
6DW5	T-6½	Beam Pent.	9CK	6.3	1.200	Vert. Defl. Amp.	11	Max. Peak Positive Pulse Plate Voltage = 2200 Volts.				Max. D.C. Cathode Current = 65 Ma.					
6DY5	T-6½	Beam Pent.	9CV	6.3	0.800	S.T. A1 Amp. P.P. A1 Amp.	10	200 200	13.9 135 ^m	190 200	45 90-104†	8.5 17-38†	24000	7600	...	4000 4000†	4200 12000
6DZ7	T-12	Double Beam Pent.	8JP	6.3	1.520	P.P. AB1 Amp. P.P. AB1 Amp.	13.2	400 300	11 120 ^m	250 250	40-100† 66-80†	4-13† 7-15†	9000 9000	18000 12000
6DZ8	T-6½	Tri. Beam Pent.	9EX	6.3	0.900	A-F Triode Volt. Amp. and Pent. Power Amp.	.825 7.15	120 145	1500 ^m 180 ^m	...	0.8 45	...	71000 2500	1400 7500	100 ...	2500	2000
6E5	T-9	Electron Ray	6R	6.3	0.300	Indicator	...	100 250	(Series Plate Resistor 0.5 Meg. Target Current 1.0 Ma. Grid Bias = 3.3 for 90° Shadow.) (Series Plate Resistor 1.0 Meg. Target Current 4.0 Ma. Grid Bias = 8.0 for 90° Shadow.)								
6EA5	T-5½	Tetrode	7EW	6.3	0.200	VHF Amp.	3.25	250	1.0	140	1.0	0.95	150000	8000	...		
6EA7	T-9	Duotriode	8BD	6.3	1.050	Sect. 2 Vert. Amp. Sect. 1 Vert. Osc.	10	Max. Peak Positive Pulse Plate Voltage = 1500 Volts.				Max. D.C. Cathode Current = 50 Ma.					
6EA8	T-6½	Tri. Pentode	9AE	6.3*	0.450	Tri. VHF Amp. Pent. Amp.	3.0 3.1	150 125	56 ^m 1.0	...	18 12	...	5000 20000	8500 6400	40 ...		
6EB5	T-5½	Duodiode	6BT	6.3	0.300	Low Current Volt./Doublers	...	Max. Peak Inverse Plate Voltage = 550 Volts. Plate Current = 5.5 Ma.									
6EB8	T-6½	Tri. Pentode	9DX	6.3	0.750	A-F Amp. Video Amp.	1.0 5.0	250 200	2.0 68 ^m	125	2 25	...	37000 75000	2700 12500	...		
6EH5	T-5½	Beam Pent.	7CV	6.3	1.200	S.T. A1 Amp.	5.5	110	62 ^m	115	42	11.5	11000	14600	...	3000	1400
6EH7	T-6½	Pentode	9AQ	6.3	0.300	VHF Amp.	2.7	200	2.0	90	12	4.5	500000	12500	...		
6EH8	T-6½	Tri. Pentode	9JG	6.3*	0.450	VHF Osc. VHF Amp.	2.5 2.8	125 125	1.0 1.0	125	13.5 12	...	170000	7500 6000	40		
6EJ7	T-6½	Pentode	9AQ	6.3	0.300	VHF Amp.	2.7	200	2.5	200	10	4.1	350000	15000	...		
6EL7	T-6½	Pentode	9AQ	6.3	0.300	VHF Amp.	3.0	170	150 ^m	170	10	2.6	...	9200	...		
6EM5	T-6½	Beam Pent.	9HN	6.3	0.800	Vert. Defl. Amplifier	11	Maximum Peak Positive Plate Voltage = 2200 Volts.				Maximum D.C. Cathode Current = 60 Ma.					
6EM7	T-9	Duotriode	8BD	6.3	0.925	Vert. Osc. Vert. Defl. A.	1.5 10	250 150	3.0 20	...	1.4 50	...	40000 750	1600 7200	64 5.4		
6EQ7	T-6½	Diode Pent.	9LQ	6.3	0.300	Det. R-F Amp.	3.0	100	2.2 Meg ⁴	100	9	3.5	250000	3800	...		
6ER5	T-5½	Triode	7FP	6.3	0.180	VHF Amp.	2.2	200	1.2	0	10	0	8000	10500	80		
6ES5	T-5½	Triode	7FP	6.3*	0.200	VHF Amp.	2.2	200	1.0	...	10	...	8000	9000	75		
6ES8	T-6½	Duotriode	9AJ	6.3	0.365	VHF Amp.	1.98	90	1.2	...	15	12500	...		
6ET7	T-6½	Duodi. Pent.	9LT	6.3	0.750	Video Amp.	5.0	200	100 ^m	150	25	5.5	60000	11500	...		
6EU7	T-6½	Duotriode	9LS	6.3	0.300	A-F Amp.	1.2	100 250	1.0 2.0	...	0.5 1.2	...	80000 62500	1250 1600	100 100		
6EU8	T-6½	Tri. Pentode	9JF	6.3	0.450	VHF Osc. VHF Amp.	3.1	150 125	56 ^m 1.0	...	18 12	...	5000 80000	8500 6400	40		
6EV5	T-5½	Tetrode	7EW	6.3	0.200	VHF Amp.	3.25	250	1.0	80	11.5	0.9	150000	8800	...		
6EV7	T-6½	Duotriode	9LP	6.3	0.600	Relay Control Tube	2.5	250	2.0	...	9.2	...	11500	5200	60		
6EW6	T-5½	Pentode	7CM	6.3	0.400	VHF Amp.	3.1	125	56 ^m	125	11	3.2	200000	14000	...		



AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts	
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.													
6EW7	9-T9	Duotriode	9HF	6.3	0.900	Vert. Defl. Amp. Vert. Osc.	10 1.5	Max. Peak Positive Plate Voltage = 1500 Volts. 150 250	17.5 11	45 5.5	800 8750	7500 2000	6 17.5
6EX6	T-12	Beam Pent.	5BT	6.3	2.250	Horiz. Defl. Amp.	22	Max. Peak Positive Pulse Plate Voltage = 7000 Volts. 175	30	67	8500	7700
6EY6	T-9	Beam Pent.	7S	6.3	0.680	Vert. Defl. Amp.	11	Max. Peak Positive Pulse Plate Voltage = 2500 Volts. 250	17.5	250	44	3	60000	4400
6EZ5	T-9	Beam Pent.	7S	6.3	0.800	Vert. Defl. Amp.	12	Max. Peak Positive Pulse Plate Voltage = 2500 Volts. 250	20	250	43	3.5	50000	4100
6EZ8	T-6½	Triode	9KA	6.3	0.450	VHF Amp.	2.0	125	1.0	...	4.2	...	13600	4200	57
6F5	Metal T-9	Triode	5M	6.3	0.300	A-F Amp.	...	250	2.0	...	0.9	...	66000	1500	100
6F5GT	T-9	Power Pent.	7S	6.3	0.700	Power Amp. S.T.A1 Amp. P.P.A1 Amp. P.P.AB2 Amp.	12.1	250 285 315 375	16.5 20.0 24.0 26.0	250 285 285 250	34.0 38.0 62-80† 34-82†	6.5 7.0 12-19.5† 5-19.5†	80000 78000	2500 2550	...	7000 7000	3200 4800	...
6F6	Metal T-9	Power Pent.	7S	6.3	0.700	Power Amp. S.T.A1 Amp. P.P.A1 Amp. P.P.AB2 Amp.	12.1	250 285 315 375	16.5 20.0 24.0 26.0	250 285 285 250	34.0 38.0 62-80† 34-82†	6.5 7.0 12-19.5† 5-19.5†	80000 78000	2500 2550	...	7000 7000	3200 4800	...
6F6G	Metal T-9	Power Pent.	7S	6.3	0.700	Power Amp. S.T.A1 Amp. P.P.A1 Amp. P.P.AB2 Amp.	12.1	250 285 315 375	16.5 20.0 24.0 26.0	250 285 285 250	34.0 38.0 62-80† 34-82†	6.5 7.0 12-19.5† 5-19.5†	80000 78000	2500 2550	...	7000 7000	3200 4800	...
6F6GT	Metal T-9	Power Pent.	7S	6.3	0.700	Power Amp. S.T.A1 Amp. P.P.A1 Amp. P.P.AB2 Amp.	12.1	250 285 315 375	16.5 20.0 24.0 26.0	250 285 285 250	34.0 38.0 62-80† 34-82†	6.5 7.0 12-19.5† 5-19.5†	80000 78000	2500 2550	...	7000 7000	3200 4800	...
6FA7	T-6½	Diode Duo Plate Tet.	9MR	6.3	0.300	Frequency Divider	1.5 1.5	100	2.2 Meg ⁴	100	3.8	1.7	90000	3200
6FC7	T-6½	Duotriode	9DD	6.3	0.340	VHF Amp.	1.9	90	1.2	...	15	12000
6FD6	T-5½	Pentode	7BK	6.3	0.330	R-F Amp.	...	12.6	2.2 Meg ⁴	12.6	1.4	0.5	500000	1450
6FD7	9-T9	Duotriode	9HF	6.3	0.925	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc. Amp.	10 1.5	Max. Peak Positive Plate Voltage = 1500 Volts. 150 250	17.5 3.0	40	1.4	...	800 40000	7500 1600	6 64
6FE5	T-6½	Beam Pent.	8KB	6.3	1.200	S.T.A1 Amp. P.P.AB1 Amp.	14.5	130 130	120 ³ 75 ³	130 130	82-94† 150-154†	4-15† 7.2-17†	1000 1600†	3500 7000	...
6FG5	T-5½	Shadow Grid Pent.	7GA	6.3	0.200	VHF Amp.	2.7	250	0.2	250	9	0.42	250000	9500
6FG7	T-6½	Tri. Pentode	9GF	6.3	0.450	VHF Osc./ Mixer	2.5 3.0	125 125	1.0 1.0	...	13 11	...	5700 180000	7500 6000	43
FH5	T-5½	Triode	7FP	6.3	0.200	R-F Amp.	2.2	135	1.0	...	11	...	5600	9000	50
6FH8	T-6½	Triode Triple Plate Tetrode	9KP	6.3	0.450	Tri. Amp. 3 Plate Tet. Plate No. 1 Plate No. 2 Plate No. 3	1.7 2.3 0.3 0.3	100 100 100 100	1.0 1.0	...	7.9 1.6 0.4 0.4	...	7400 ...	5400 2500 70 70	40
6FJ7	Comp. T-9	Duotriode	12BM	6.3	0.900	Sect. 2 Vert. Defl. Amp. Sect. 1 Vert. Osc. Amp.	10 1.0	Max. Peak Positive Plate Voltage = 2500 Volts. 250	9.5 8.0	41	2000 9000	7700 2500	15.4 22.5
6FM8	T-6½	Duodiode Tri.	9KR	6.3	0.450	Det. Amp.	1.1	250	3	...	1.0	...	58000	1200	70
6FQ5	T-5½	Triode	7FP	6.3	0.180	VHF Amp.	2.5	135	1.2	...	11.5	...	5500	11000	60
6FQ5A	T-5½	Triode	7FP	6.3	0.180	VHF Amp.	2.5	135	1.2	...	8.9	...	6300	12000	74
6FQ7	T-6½	Duotriode	9LP	6.3*	0.600	General Purpose	4.0	90 250	0 8.0	...	10 9	...	6700 7700	3000 2600	20 20
6FR7	9-T9	Duotriode	9HF	6.3	0.925	Vert. Defl. Amplifier Vert. Osc.	10 1.5	Max. Peak Positive Pulse Plate Voltage = 1500 Volts. 150 250	20 3.0	50 ...	1.4	...	40000	1600	68
6FS5	T-5½	Shadow Grid Beam Pent.	7GA	6.3	0.200	VHF Amp.	3.2	275	0.2	135	9	0.17	240000	10000
6FV6	T-5½	Tetrode	7FQ	6.3	0.200	VHF Amp.	2.0	125	1.0	80	10	1.5	100000	8000
6FV8	T-6½	Tri. Pentode	9FA	6.3*	0.450	Vert. Osc. VHF Amp.	2.0 2.3	125 125	1.0 1.0	...	14 12	...	5000 200000	8000 6500	40


(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. †† Plate to Plate. ‡ Cathode Resistor (ohms).



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6HB6	T-6½	Beam Pent.	9PU	6.3	0.760	Vert. Defl. Amplifier	10	Maximum Peak Positive Plate Voltage = 2500 Volts.									
6HC8	9-T9	Tri. Pentode	9EX	6.3	1.200	Vert. Defl. Amplifier Vert. Osc.	1.0 11	Max. Peak Positive Pulse Plate Voltage = 2200 Volts. Max. D.C. Cathode Current = 65 Ma.									
6HF8	T-6½	Tri. Pentode	9DX	6.3	0.750	Gen. Purpose Video Amp.	1.0 5.0	200 200	2.0 68 ^m	125	4 25	3 7	17500 7500	4000 12500	70		
6HG8	T-6½	Tri. Pentode	9MP	6.3	0.340	VHF Amp.	2.2	100 150	3.0 1.5	150	14 10	3.3	350000	6000 12000	17		
6HJ8	T-6½	Diode Pent.	9CY	6.3*	0.450	Video Det. T.V. I-F Amp.	3.2	125	56 ^m	125	11.5	3.6	200000	9300			
6HQ6	T-5½	Pentode	6HQ6	6.3	0.300	VHF Amp.	2.4	125	56 ^m	125	15	3.8	220000	10500			
6HR6	T-5½	Pentode	7BK	6.3*	0.450	FM I-F Amp.	3.0	200	68 ^m	115	13.2	4.3	500000	8500			
6HS8	T-6½	Twin Pentode	9FG	6.3	0.300	AGC/Sync. Amplifier	1.1	100	g3= 0V g3= 10V	67.5 67.5	4.4 7.0	IK = 8.5 Ma., Igl = 100 µa. IK = 7.1 Ma., Igl = 100 µa.					
6HW8	T-6½	Duo. Plate Sheet Beam	9NQ	6.3	0.300	Duo. Plate Sheet Beam	2.0	250	270 ^m	250	13	1.4	4000				
6HZ8	9-T9	Tri. Pentode	9DX	6.3	1.125	Gen. Pur. Tri. Video Amp.	1.0 8.0	200 250	2.0 100 ^m	170	3.5 29	6	4000 140000	70 12600			
6J4 GB-6J4WA (3)	T-5½	Triode	7BQ	6.3	0.400	Amplifier	2.5	150	100 ^m		15.0		4500	12000	55		
6J5 6J5GT	Metal T-9	Triode	6Q	6.3	0.300	Amplifier	2.75	250	8.0		9.0		7700	2600	20		
6J6 6J6A 6J6WA (3)	T-5½	Duotriode	7BF	6.3 6.3*	0.450 0.450	VHF Osc. VHF Amp. Mixer	1.65	150	10.0 50 ^m 820 ^m		30.0 8.5 4.8		Push-Pull Class C Operation				3500
6J7 6J7G 6J7GT	Metal ST-12 T-9	Pentode	7R 7R 7R	6.3	0.300	A-F Amp.	1.92	250	3.0	100	2.0	0.5	1.0 Meg <	1225			
6J11	Comp. T-9	Duo. Pent.	12BW	6.3	0.800	T.V. I-F Amp.	3.1	125	56 ^m	125	11	3.8	200000	13000			
6JC8	T-6½	Tri. Pentode	9PA	6.3*	0.450	VHF Osc. VHF Amp.	1.7 2.3	125 125	1.0 1.0	125	12 9	2.2	6000 300000	6500 5500	40		
6JE8	T-6½	Tri. Pentode	9DX	6.3	0.780	Gen. Purpose Video Amp.	1.0 4.0	200 250	2.0 82 ^m	170	4.5 22	4.0	140000	4200 12000	70		
6JK8	T-6½	Duotriode	9AJ	6.3	0.400	FM Osc. FM Amp.	1.0 2.0	100 135	1.0 1.2		5.3 10		8000 5400	6800 13000	55 70		
6JU8	T-6½	Quadruple Diode	9PQ	6.3	0.600	Color Det., FM Multiplex Det.		Max. Peak Inverse Plate Voltage = 300 Volts. Max. Peak Plate Current = 54 Ma.									
6K6GT	T-9	Power Pent.	7S	6.3	0.400	S.T. A1 Amp.	9.3	100 250 315	7.0 18.0 21.0	100 250 250	9.0 32.0 25.5	1.6 5.5 4.0	104000 68000 75000	1500 2300 2100		12000 7600 9000	350 3400 4500
6K7	Metal	Pentode	7R	6.3	0.300	R-F Amp.	3.0	100 250 250	1.0 3.0 3.0	100 100 125	9.5 7.0 10.5	2.7 1.7 2.6	150000 80000 600000	1650 1450 1650			
6K8	Metal	Tri. Hexode	8K	6.3	0.300	Mixer Osc.	.825	250	3.0	100	2.5	6.0	600000	350 ^a	(Hexode Section)		
6K11	Comp. T-9	Triple Triode	12BY	6.3*	0.600	Gen. Purpose	2.7 0.3 0.3	250 250 250	8.5 2.0 2.0		10.5 1.2 1.2		7700 62500 62500	2200 1600 1600	17 100 100		

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. † Filamentary Type. * Conversion Transconductance. † Plate to Plate. ■ Cathode Resistor (ohms). * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Amplifi-cation Factor	Ohms Load for Stated Power Output	Power Output Milli-watts		
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.														
6L6	Metal	Beam Pent.	7S	6.3	0.900	S.T. A1 Amp. S.T. A1 Amp. P.P. A1 Amp.	20.9	250	14.0	250	72.0	5.0	22500	6000	2500	6500		
6L6GB	T-12		7S			P.P. A1 Amp. P.P. AB1 Amp. P.P. AB2 Amp.		350 270 360 360	18.0 17.5 22.5 22.5	250 270 270 270	54.0 134-155† 88-132† 88-205†	2.5 11-17† 5-15† 5-16†	33000 23500	5200 5700 (Current & Output, 2 Tubes) (Current & Output, 2 Tubes)	4200 5000† 6600† 3800	10800 17500 26500 47000		
6L6GC	T-12	Beam Pent.	7S	6.3	0.900	P.P. AB1 Amp. P.P. AB1 Amp. P.P. AB1 Amp.	30	360 360 450	22.5 22.5 37	270 270 400	88-132† 88-140† 116-210†	5-15† 5-11† 5.6-22†	6600† 3800† 5600†	26500 18000 55000		
6L7	Metal	Heptode	7T	6.3	0.300	Mixer Amp. Amplifier	1.65	250 250	6.0 3.0	150 100	3.3 5.3	9.2 6.5	1 Meg. < 600000	350* 1100	G3 = Neg. 15 Volts (G3 = Neg. 3.0 Volts)		
6M11	Comp. T-9	Pentode Duotriode	12CA	6.3	0.750	Gen. Purpose	3.1 2.25	125 125	56* 1.0	125	11 7.0	3.4	20000 1000	13000 7000 70		
6N7GT 6N7	T-9 Metal	Duotriode	8B	6.3	0.800	Power Amp. Driver	1.1	300 250 294	0.0 5.0 6.0	17.5-35† 6.0 7.0	Per Pl., Cl. B Sections Paralled 11300 11000 3100 3200 35 35	8000† (Class A Driver)	10000 (Class A Driver)		
6Q7 6Q7GT	Metal T-9	Duodiode Tri.	7V 7V	6.3	0.300	Det. Amp.	0.55	100 250	1.5 3.0	0.8 1.1	58000 58000	1200 1200	70 70		
6Q11	Comp. T-9	Triple Triode	12BY	6.3*	0.600	Gen. Purpose	3.0 1.2 1.2	150 100 100	0 1.0 1.0	22 0.5 0.5	7000 80000 80000	2500 1250 1250	18 100 100		
6R7	Metal	Duodiode Tri.	7V	6.3	0.300	Det. Amp.	2.75	250	9.0	9.5	8500	1900	16		
6S4A	T-6½	Triode	9AC	6.3*	0.600	Vert. Defl. Amplifier	8.5	Characteristics Same as Type 6S4. (6S4A Designed for Series String TV Receivers.)									
6SA7 6SA7GT 6SA7GT 6SB7Y	Metal T-9 T-9 Metal	Heptode	8R 8AD 8AD 8R	6.3	0.300	Converter	1.1	100 250	2.0 2.0	100 100	3.3 3.5	8.5 8.5	50000 1.0 Meg.	425* 450*		
6SC7	Metal	Duotriode	8S	6.3	0.300	Amplifier	250	2.0	2.0	53000	1325	70	(Each Triode)		
6SF5	Metal	Triode	6AB	6.3	0.300	A-F Amp.	250	2.0	0.9	66000	1500	100		
6SF7	Metal	Diode Pent.	7AZ	6.3	0.300	Det. Amp.	3.85	100 250	1.0 1.0	100 100	12 12.4	3.4 3.3	20000 70000	1975 2050		
6SG7	Metal	Pentode	8BK	6.3	0.300	R-F Amp.	3.3	100 250 250	1.0 1.0 2.5	100 125 150	8.2 11.8 9.2	3.2 4.4 3.4	250000 900000 1 Meg.	4100 4700 4000		
6SH7	Metal	Pentode	8BK	6.3	0.300	R-F Amp.	3.3	100 250	1.0 1.0	100 150	5.3 10.8	2.1 4.1	350000 900000	4000 4900		
6SJ7 6SJ7GT 6SJ7GT (3) GB-6SJ7GT (3)	Metal T-9 T-9 T-9	Pentode	8N 8N 8N 8N	6.3	0.300	A-F Amp.	2.8	100 250	3.0 3.0	100 100	2.9 3.0	0.9 0.8	700000 1.0 Meg <	1575 1650		
6SK7 6SK7GT	Metal T-9	Pentode	8N 8N	6.3	0.300	R-F Amp.	4.4	100 250	1.0 3.0	100 100	13.0 9.2	4.0 2.6	120000 800000	2350 2000		
6SL7GT GB-6SL7GT (3)	T-9	Duotriode	8BD	6.3	0.300	Amplifier	1.1	250	2.0	2.3	44000	1600	70		
6SN7GTB GB-6SN7GT (3)	T-9	Duotriode	8BD	6.3	0.600	Amplifier	2.75	90 250	0 8.0	10.0 9.0	6700 7700	3000 2600	20 20		
6SQ7 6SQ7GT	Metal T-9	Duodiode Tri.	8Q 8Q	6.3	0.300	Det. Amp.	0.55	250	2.0	1.1	85000	1175	100		
6SR7	Metal	Duodiode Tri.	8Q	6.3	0.300	Det. Amp.	2.75	250	9.0	9.5	8500	1900	16		
6SS7	Metal	Pentode	8N	6.3	0.150	R-F Amp.	2.5	100 250	1.0 3.0	100 100	12.2 9.0	3.1 2.0	120000 1000000	1950 1850		
6T4	T-5½	Triode	7DK	6.3	0.225	UHF Osc.	3.85	80	150	18	1860	7000	13		
6T8A	T-6½	Triple Diode Tri.	9E	6.3 6.3*	0.450 0.450	Det. Amp.	1.1	100 250	1.0 3.0	0.8 1.0	54000 58000	1300 1200	70 70		



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6U5	T-9	Electron Ray	6R	6.3	0.300	Indicator	100 250	(Series Plate Res. 0.5 Meg., Target Current 1.0 Ma., Grid Bias -8.0 for 0° Shadow.) (Series Plate Res. 1.0 Meg., Target Current 4.0 Ma., Grid Bias -22.0 for 0° Shadow.)	
6U6GT	T-9	Beam Pent.	7S	6.3	0.750	Power Amp.	12.1	110 200	10.5 14.0	110 135	44.0 55.0	4.0 3.0	10000 20000	5600 6200	2000 3000	2000 5500
6U8A	T-6½	Tri. Pentode	9AE	6.3*	0.450	VHF Osc. VHF Amp.	2.5 3.0	125 125	1.0 1.0 110	13.5 9.5 3.5	5000 20000	7500 5000	40
6V3A	T-6½	Diode	9BD	6.3	1.750	T.V. Damper	2.97	P.I.V. = 6000 Volts Abs. Max. D.C. Plate Current = 135 Ma. Max.									
6V6	Metal T-9	Beam Pent.	7S	6.3	0.450	Power Amp. Class A1	13.2	180 250	8.5 12.5	180 250	29.0 45.0	3.0 4.5	50000 50000	3700 4100	5500 5000	2000 4500
6V6GT	T-9	Beam Pent.	7S	6.3	0.450	Power Amp. Class A1	13.2	180 250	8.5 12.5	180 250	29.0 45.0	3.0 4.5	50000 50000	3700 4100	5500 5000	2000 4500
6V6GTA	T-9	Beam Pent.	7S	6.3*	0.450	Amplifier Class AB1	13.2	180 250	8.5 12.5	180 250	29.0 45.0	3.0 4.5	50000 50000	3700 4100	5500 5000	2000 4500
6V8	T-6½	Triple Diode Triode	9AH	6.3	0.450	Det. Amp.	1.1	100 250	1.0 3.0	0.8 1.0	54000 58000	1300 1200	70 70
6W4GT	T-9	Diode	4CG	6.3	1.200	H-W Rect.	3.85	350 A.C. Volts, RMS, 125 Ma. D.C. Output. Condenser Input to Filter.									
6W4GTA	T-9	Diode	4CG	6.3	1.200	T.V. Damper	4.0	Max. Peak Inverse Plate Voltage = 3950 Volts. Max. D.C. Plate Current = 140 Ma.									
6W6GT	T-9	Beam Pent.	7S	6.3	1.200	Power Amp. Vert. Defl. Amplifier	11	110 200	7.5 180	110 125	49 46	4.0 2.2	13000 28000	8000 8000	2000 4000	2100 3800
6X4 GB-6X4WA (3)	T-5½	Duodiode	5BS	6.3	0.600	F-W Rect.	400 Volts RMS Per Plate, 55 Ma. D.C. Output Condenser Input to Filter.									
6X5GT	T-9	Duodiode	6S	6.3	0.600	F-W Rect.	325 A.C. Volts Per Plate, RMS, 70 Ma. Output Current. Condenser Input to Filter.									
6X5WGT (3)	T-9	Duodiode	6S	6.3	0.600	F-W Rect.	450 A.C. Volts Per Plate, RMS, 70 Ma. Output Current. Choke Input to Filter.									
6X8	T-6½	Triode Pentode	9AK	6.3	0.450	VHF Osc. VHF Amp.	1.7 2.3	125 125	1.0 1.0	12 9 2.2	6000 0.3 Meg.	6500 5500	40
6Y6GA	T-12	Beam Pent.	7S	6.3	1.250	Power Amp.	13.75	135 200	13.5 14.0	135 135	58.0 61.0	3.5 2.2	9300 18300	7000 7100	2000 2600	3600 6000
6Z4/84	ST-12	Duodiode	5D	6.3	0.500	F-W Rect.	325 A.C. Volts Per Plate, RMS, 60 Ma. Output Current. Condenser Input to Filter.									
7A4/XXL	Lock-in	Triode	5AC	6.3	0.300	Amplifier	2.75	90 250	0.0 8.0	10.0 9.0	6700 7700	3000 2600	20 20
7A5	Lock-in	Beam Pent.	6AA	6.3	0.750	Power Amp.	6.0	110 125	7.5 9.0	110 125	40.0 44.0	3.0 3.3	16000 17000	5800 6000	2500 2700	1500 2200
7A6	Lock-in	Duodiode	7DX	6.3	0.150	Det. Rect.	150 A.C. Volts Per Plate, RMS, 8 Ma. Current Output Per Plate.									
7A7	Lock-in	Pentode	8V	6.3	0.300	R-F Amp.	4.4	100 250	1.0 3.0	100 100	13.0 9.2	4.0 2.6	120000 800000	2350 2000
7A8	Lock-in	Octode	8U	6.3	0.150	Converter	1.1	100 250	3.0 3.0	75 100	1.8 3.0	2.7 3.2	650000 700000	375 [▲] 550 [▲]	(Ga = 100 V., 2.8 Ma.) (Ga = 250 V thru 20K Ohms.)
7AF7	Lock-in	Duotriode	8AC	6.3	0.300	Amplifier (per unit)	2.75	100 100 250	0 3.0 10	10.8 5.0 9.0	6500 8400 7600	2600 1900 2100	17 16 16
7AG7	Lock-in	Pentode	8V	6.3	0.150	R-F Amp.	2.2	250	250 [■]	250	6.0	2.0	1.0 Meg <	4200
7AK7 GB-7AK7 (3)	Lock-in	Pentode	8V	6.3	0.800	R-F Amp.	9.35	150 150 150	0 11 0	90 90 90	40 2.5 Max. 2.0 Max.	21 0.45 60 Max.	11500	6000
7AU7	T-6½	Duotriode	9A	7.0/ 3.5*	0.300/ 0.600	Amplifier	3.0	Characteristics Same as Type 12AU7A. (7AU7 Designed for Series String TV Receivers.)									
7B4	Lock-in	Triode	5AC	6.3	0.300	Amplifier	100 250	1.0 2.0	0.4 0.9	85000 66000	1150 1500	100 100

(1) See Frontal Section. (2) Design Maximum Values. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) † Maximum Signal. † Filamentary Type. † Conversion Transconductance. † Plate to Plate. † Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts		
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.														
7B5	Lock-in	Power Pent.	6AE	6.3	0.400	Power Amp.	9.35	100 250 315	7.0 18.0 21.0	100 250 250	9.0 32.0 25.5	1.6 5.5 4.0	104000 68000 75000	1500 2300 2100	12000 7600 9000	350 3400 4500		
7B6	Lock-in	Duodiode Tri.	8W	6.3	0.300	Det. Amp.	0.55	100 250	1.0 2.0	0.4 0.9	110000 91000	900 1100	100 100		
7B7	Lock-in	Pentode	8V	6.3	0.150	R-F Amp.	2.47	100 250	3.0 3.0	100 100	8.2 8.5	1.8 1.7	300000 750000	1675 1750		
7B8	Lock-in	Heptode	8X	6.3	0.300	Converter	1.1	100 250	1.5 3.0	50 100	1.1 3.5	1.3 2.7	600000 360000	360 ^A 550 ^A	(G _a = 100 V., 2.0 Ma.)			
7C5	Lock-in	Beam Pent.	6AA	6.3	0.450	Power Amp. Class A1 Class AB1	13.2	180 250 315 250 285	8.5 12.5 13.0 15.0 19.0	180 250 225 250 285	29.0 45.0 34.0 70-79† 70-92†	3.0 4.5 2.2 5-13† 4-13.5†	58000 52000 77000	3700 4100 3750	5500 5000 8500	2000 4500 5500 10000† 14000		
7C6	Lock-in	Duodiode Tri.	8W	6.3	0.150	Det. Amp.	0.66	100 250	0.0 1.0	1.0 1.3	100000 100000	850 1000	85 100		
7C7	Lock-in	Pentode	8V	6.3	0.150	R-F Amp.	1.1	100 250	3.0 3.0	100 100	1.8 2.0	0.4 0.5	1.2 Meg. 2.0 Meg.	1225 1300		
7DJ8	T-6½	Duotriode	9AJ	7.0	0.300	VHF Amp.	2.2	90	1.3	15	12500	33		
7ES8	T-6½	Duotriode	9AJ	7.2	0.300	VHF Amp.	1.8	90	1.4	15	2500	12500		
7EY6	T-9	Beam Pent.	7S	7.2*	0.600	Vert. Defl. Amplifier	11	Max. Peak Positive Pulse Plate Voltage = 2500 Volts. Max. D.C. Cathode Current = 60 Ma. Characteristics Same as Type 6EY6.									
7F7	Lock-in	Duotriode	8AC	6.3	0.300	A-F Amp.	1.1	100 250	1.0 2.0	0.65 2.3	62000 44000	1125 1600	70 70		
7F8	Lock-in	Duotriode	8BW	6.3	0.300	Osc. Amp.	3.85	250	500 ^M	6.0	3300	48		
GB-7F8W (3)	Lock-in	Duotriode	8BW	6.3	0.300	Osc. Amp.	3.5	250	200 ^M	11.0	5200	50		
7FC7	T-6½	Duotriode	9DD	7.2	0.300	VHF Amp.	1.9	Characteristics Same as Type 6FC7. (7FC7 Designed for Series String Receivers.)									
7H7	Lock-in	Pentode	8V	6.3	0.300	R-F Amp.	2.75	100 250	1.5 180 ^M	100 150	7.5 10.0	2.6 3.2	350000 800000	4000 4000		
7HG8	T-6½	Tri. Pentode	9MP	7.2	0.300	VHF Amp.	2.2	Characteristics Same as Type 6HG8. (7HG8 Designed for Series String Receivers.)									
7J7	Lock-in	Tri. Heptode	8BL	6.3	0.300	Hep. Mixer Tri. Osc.	0.55 1.74	100 250	3.0 0.05 Meg. 0.05 Meg.	100 100	1.5 1.4 3.2 5.0	2.6 2.8 1.5 Meg. (Triode Grid Current 0.3 Ma.) (Triode Grid Current 0.4 Ma.)	500000 280 ^A 290 ^A		
7K7	Lock-in	Duodiode Tri.	8BF	6.3	0.300	Det. Amp.	1.1	250	2.0	2.3	44000	1600	70		
7L7	Lock-in	Pentode	8V	6.3	0.300	R-F Amp.	4.4	100 250	1.0 1.5	100 100	5.5 4.5	2.4 1.5	100000 1.0 Meg.	3000 3100		
7N7	Lock-in	Duotriode	8AC	6.3	0.600	Amplifier	2.75	90 250	0.0 8.0	10.0 9.0	6700 7700	3000 2600	20 20		
7Q7	Lock-in	Heptode	8AL	6.3	0.300	Converter	1.1	100 250	2.0 2.0	100 100	3.3 3.5	8.5 8.5	500000 1.0 Meg.	525 ^A 550 ^A	(Osc. Grid Resistor 20000) (Osc. Grid Current 0.5 Ma.)			
7R7	Lock-in	Duodi. Pent.	8AE	6.3	0.300	Det. Amp.	2.2	100 100 250 250	2.0 1.0 2.0 1.0	100 100 100 100	3.4 5.5 3.5 5.7	1.0 2.2 1.0 2.1	500000 350000 1800000 1000000	2100 3000 2200 3200		
7S7	Lock-in	Tri. Heptode	8BL	6.3	0.300	Hep. Mixer Tri. Osc.	0.66	100 250 100 250	2.0 2.0 0.05 Meg. 0.05 Meg.	100 100	1.9 1.8 3.0 5.0	3.0 3.0 1.25 Meg. (Triode Grid Current 0.3 Ma.) (Triode Grid Current 0.4 Ma.)	500000 500 ^A 525 ^A		
7V7	Lock-in	Pentode	8V	6.3	0.450	R-F Amp.	4.4	300	160 ^M	150	10.0	3.9	300000	5800		
7W7	Lock-in	Pentode	8BJ	6.3	0.450	R-F Amp.	4.4	Characteristics Same as Type 7V7, Except Capacitances.									
7X7	Lock-in	Duodiode Tri.	8BZ	6.3	0.300	Det. Amp.	0.55	100 250	0 1.0	1.2 1.9	85000 67000	1000 1500	85 100		
7Y4	Lock-in	Duodiode	5AB	6.3	0.500	F-W Rect.	325 A.C. Volts Per Plate, RMS, 70 Ma. Output Current. Condenser Input to Filter. 450 A.C. Volts Per Plate, RMS, 70 Ma. Output Current. Choke Input to Filter.									



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milliwatts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
7Z4	Lock-in	Duodiode	5AB	6.3	0.900	F-W Rect.	325 A.C. Volts Per Plate, RMS, 100 Ma. Output Current.	Condenser Input to Filter. 450 A.C. Volts Per Plate, RMS, 100 Ma. Output Current. Choke Input to Filter.								
8AU8 8AU8A	T-6½	Tri. Pentode	9DX	8.4*	0.450	Tri. Amp. Pent. Amp.	2.75 3.3	Characteristics Same as Type 6AU8. (8AU8 and 8AU8A Designed for Series String Operation.) 8AU8A Characteristics Same as Type 6AU8A.									
8AW8A	T-6½	Tri. Pentode	9DX	8.4*	0.450	Sync. Sep. Video Amp.	1.1 3.57	Characteristics Same as Type 6AW8A. (8AW8A Designed for Series String TV Receivers.)									
8B10	Comp. T-9	Duodiode Duotriode	12BF	6.3*	0.600	Horiz. Phase Det./Osc.	3.0	Characteristics Same as Type 6B10. (8B10 Designed for Series String Receivers.)									
8BA8A	T-6½	Tri. Pentode	9DX	8.4*	0.450	Sync. Sep. Video Amp.	2.2 3.57	Characteristics Same as Type 6BA8A. (8BA8A Designed for Series String TV Receivers.)									
8BH8	T-6½	Tri. Pentode	9DX	8.4*	0.450	Tri. Amp. Pent. Amp.	2.75 3.3	Characteristics Same as Type 6BH8. (8BH8 Designed for Series String TV Receivers.)									
8BN8	T-6½	Duodiode Tri.	9ER	8.4*	0.450	Amplifier	1.65	Characteristics Same as Type 6BN8. (8BN8 Designed for Series String TV Receivers.)									
8BQ5	T-6½	Beam Pent.	9CV	8.0*	0.600	P.P.AB1 Amp.	13.2	Characteristics Same as Type 6BQ5. (8BQ5 Designed for Series String Receivers.)									
8CG7	T-6½	Duotriode	9AJ	8.4*	0.450	Amplifier	3.85	Characteristics Same as Type 6CG7. (8CG7 Designed for Series String TV Receivers.)									
8CM7	T-6½	Duotriode	9ES	8.4*	0.450	Vert. Osc. Vert. Defl. A.	1.37 5.5	Characteristics Same as Type 6CM7. (8CM7 Designed for Series String TV Receivers.)									
8CN7	T-6½	Duodiode Tri.	9EN	8.4/ 4.2*	0.225/ 0.450	Det. Amp.	1.1	Characteristics Same as Type 6CN7. (8CN7 Designed for Series String TV Receivers.)									
8CS7	T-6½	Duotriode	9EF	8.4*	0.450	Vert. Osc. Vert. Defl. A.	1.37 5.5	Characteristics Same as Type 6CS7. (8CS7 Designed for Series String TV Receivers.)									
8CW5	T-6½	Beam Pent.	9CV	8.0*	0.600	A-F Pwr. Amp.	13	Characteristics Same as Type 6CW5. (8CW5 Designed for Series String Receivers.)									
8CX8	T-6½	Tri. Pentode	9DX	8.0*	0.600	Tri. Amp. Video Amp.	2.0 5.0	Characteristics Same as Type 6CX8. (8CX8 Designed for Series String Receivers.)									
8CY7	T-6½	Duotriode	9LG	7.9*	0.600	Vert. Osc. Vert. Defl. A.	1.0 5.5	Characteristics Same as Type 6CY7. (8CY7 Designed for Series String TV Receivers.)									
8EB8	T-6½	Tri. Pentode	9DX	8.0*	0.600	A-F Amp. Video Amp.	1.0 5.0	Characteristics Same as Type 6EB8. (8EB8 Designed for Series String Receivers.)									
8ET7	T-6½	Duodiode Pentode	9LT	8.0*	0.600	Horiz. Phase Det. Video A.	5.0	Characteristics Same as Type 6ET7. (8ET7 Designed for Series String Receivers.)									
8FQ7	T-6½	Duotriode	9LP	8.4*	0.450	Gen. Purpose	4.0	Characteristics Same as Type 6FQ7. (8FQ7 Designed for Series String Receivers.)									
8GN8	T-6½	Tri. Pentode	9DX	8.0*	0.600	Triode Amp. Video Amp.	1.0 5.0	Characteristics Same as Type 6GN8. (8GN8 Designed for Series String Receivers.)									
8HG8	T-6½	Tri. Pentode	9MP	8.0*	0.300	VHF Amp.	1.6 2.2	Characteristics Same as Type 6HG8. (8HG8 Designed for Series String Receivers.)									
8JE8	T-6½	Tri. Pentode	9DX	8.2*	0.600	Gen. Purpose Video Amp.	1.0 4.0	Characteristics Same as Type 6JE8. (8JE8 Designed for Series String Receivers.)									
8JK8	T-6½	Duotriode	9AJ	8.4*	0.300	FM Osc. FM Amp.	1.0 2.0	100 130	1.0 1.2	5.3 10	8000 5400	1800 13000	55 70
8EM5	T-6½	Beam Pent.	9HN	8.4*	0.600	Vert. Defl. Amplifier	11	Characteristics Same as Type 6EM5. (8EM5 Designed for Series String Operation.)									
9A8	T-6½	Tri. Pentode	9DC	9.0	0.300	VHF Osc. VHF Amp.	5.5 8.25	Characteristics Same as Type 6BL8.									
9AU7	T-6½	Duotriode	9A	9.4/ 4.7*	0.225/ 0.450	Amplifier	3.0	Characteristics Same as Type 7AU7. (9AU7 Designed for Series String TV Receivers.)									
9BR7	T-6½	Duodiode Tri.	9CF	4.7* 9.4*	0.600 0.300	Det. Amp.	2.75	250 Peak	200 [■] Inverse Diode	10 Volts Max.,	10900 Peak	4000 Diode	60 Current = 60 Ma. Max.
9BR8	T-6½	Tri. Pentode	9FA	9.45	0.300	VHF Osc. VHF Amp.	2.97 3.0	150 250	56 [■] 68 [■] 110	18 10 3.5	5000 400000	8500 5200	40
9CL8	T-6½	Tri. Tetrode	9FX	9.5*	0.300	VHF Osc. VHF Amp.	2.97 3.0	Characteristics Same as Type 6CL8. (9CL8 Designed for Series String TV Receivers.)									

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
 † Filamentary Type. † Conversion Transconductance. † Plate to Plate. † Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
9DZ8	T-6½	Triode Beam Pent.	9EX	9.0	0.600	A-F Voltage Amp. and Power Amp.	.82 7.15	Characteristics Same as Type 6DZ8. (9DZ8 Designed for Series String Receivers.)									
9EF6	T-9	Beam Pent.	7S	9.4*	0.600	Vert. Defl. Amplifier	11	Characteristics Same as Type 6EF6. (9EF6 Designed for Series String TV Receivers.)									
9U8A	T-6½	Tri. Pentode	9AE	9.45*	0.300	VHF Osc. VHF Amp.	2.5 3.0	Characteristics Same as Type 6U8. (9U8A Designed for Series String TV Receivers.)									
9X8	T-6½	Tri. Pentode	9AK	9.5*	0.300	VHF Osc. VHF Amp.	1.65 2.2	Characteristics Same as Type 6X8. (9X8 Designed for Series String TV Receivers.)									
10BQ5	T-6½	Power Pent.	9CV	10.6*	0.450	A-F Pwr. Amp.	12	Characteristics Same as Type 6BQ5. (10BQ5 Designed for Series String Receivers.)									
10C8	T-6½	Tri. Pentode	9DA	10.5*	0.300	Tri. Amp. Pent. Amp.	2.0 2.2	250 135	390 ^m 100 ^m	135	7.3 11.5	3.2	12000 190000	4400 8000	53
10DA7	T-6½	Duotriode	9EF	10.5*	0.600	Vert. Osc. Vert. Defl. A.	2.2 6.6	Characteristics Same as Type 6DA7. (10DA7 Designed for Series String TV Receivers.)									
10DE7	T-6½	Duotriode	9HF	9.7*	0.600	Vert. Osc. Vert. Defl. A.	1.5 7.0	Characteristics Same as Type 6DE7. (10DE7 Designed for Series String TV Receivers.)									
10DR7	T-6½	Duotriode	9HF	9.7*	0.600	Vert. Amp. Vert. Osc.	7.0 1.0	Characteristics Same as Type 6DR7. (10DR7 Designed for Series String Receivers.)									
10EB8	T-6½	Tri. Pentode	9DX	10.5*	0.450	A-F Amp. Video Amp.	1.0 5.0	Characteristics Same as Type 6EB8. (10EB8 Designed for Series String Receivers.)									
10EG7	T-9	Duotriode	8BD	9.7*	0.600	Vert. Amp. Vert. Amp. Vert. Osc.	10 1.5	Max. Peak Positive Pulse Plate Voltage = 1500 Volts. Max. D.C. Cathode Current = 50 Ma. 150 17.5 45 800 7500 6 250 11.0 5.5 8750 2000 17.5 Characteristics Same as Type 6EM7. (10EM7 Designed for Series String Receivers.)									
10EM7	T-6½	Duotriode	8BD	9.7*	0.600	Vert. Defl. Amp./Osc.	1.5 10	Characteristics Same as Type 6EM7. (10EM7 Designed for Series String Receivers.)									
10EW7	9-T9	Duotriode	9HF	9.7*	0.600	Vert. Defl. Osc./Amp.	1.5 10	Characteristics Same as Type 6EW7. (10EW7 Designed for Series String Receivers.)									
10FD7	9-T9	Duotriode	9HF	9.7*	0.600	Vert. Defl. Amp./Osc.	1.5 10	Characteristics Same as Type 6FD7. (10FD7 Designed for Series String Receivers.)									
10FR7	9-T9	Duotriode	9HF	9.7*	0.600	Vert. Defl. Amp./Osc.	1.5 10	Characteristics Same as Type 6FR7. (10FR7 Designed for Series String Receivers.)									
10HF8	T-6½	Tri. Pentode	9DX	10.5*	0.450	Gen. Purpose Video Amp.	1.0 5.0	Characteristics Same as Type 6HF8.									
11AR11	Comp. T-9	Duo. Pent.	12DM	11.2*	0.450	T.V. I-F Amp.	3.1	Characteristics Same as Type 6AR11. (11AR11 Designed for Series String Receivers.)									
11C5	T-5½	Beam Pent.	7CV	11.6*	0.450	Power Amp.	4.9	Characteristics Same as Type 35C5. (11C5 Designed for Series String TV Receivers.)									
11CY7	T-6½	Duotriode	9LG	11*	0.450	Vert. Osc. Vert. Defl. A.	1.0 5.5	Characteristics Same as Type 6CY7. (11CY7 Designed for Series String TV Receivers.)									
11JE8	T-6½	Tri. Pentode	9DX	10.9*	0.450	Gen. Purpose Video Amp.	1.0 4.0	Characteristics Same as Type 6JE8. (11JE8 Designed for Series String Receivers.)									
12A6	Metal	Beam Pent.	7S	12.6	0.150	Power Amp.	8.25	250	12.5	250	30	3.5	70000	3000	7500	3400
12A8GT	T-9	Heptode	8A	12.6	0.150	Converter	1.1	Characteristics Same as Type 6A8G.									
12AB5	T-6½	Beam Pent.	9EU	12.6	0.200	S.T.A1 Amp. P.P.A1 Amp.	13.2	250 250	12.5 15	250 250	45 70	5 5	50000	4100	5000 10000	4500 10000
12AC6	T-5½	Pentode	7BK	12.6	0.150	R.F. Amp.	12.6	0	12.6	550µa	200µa	0.5 Meg.	730
12AD5	T-6½	Pentode	9AZ	12.6	0.100	R-F Amp.	2.2	100	2.5	100	6.0	1.75	600000	2200
12AD6	T-5½	Heptode	7CH	12.6	0.150	Hep. Mixer	12.6	2.2 Meg ⁴	12.6	350 µa.	1.5	320 ^A
12AD7	T-6½	Duotriode	9A	12.6/ 6.3	0.225/ 0.450	A-F Amp.	1.1	250	2	1.25	62500	1600	100
12AE6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	12.6	0	0.75	15000	1000	15
12AE6A	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	12.6	10 Meg ⁴	0.32	20000	715	14.3
12AE7	T-6½	Duotriode	9A	12.6	0.450	Dis. Triodes Voltage Amp. Pwr. Amp. Dr.	1.0 1.0	12.6	1.5 Meg ⁴	1.9	3150	4000	13
12AF3	T-6½	Diode	9CB	12.6*	0.600	T.V. Damper	6.0	Characteristics Same as Type 6AF3. (12AF3 Designed for Series String Receivers.)									



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts		
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.														
12AF6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.	12.6	0	12.6	1.1	0.45	0.35 Meg.	1500		
12AG6	T-5½	Heptode	7CH	12.6	0.150	Converter	12.6	0.85	12.6	0.55	1.4	300 ^A	G1 = 20000 Ohms; G1 = 0.050 Ma.			
12AJ6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	12.6	0	0.075	45000	1200	55		
12AL5	T-5½	Duodiode	6BT	12.6	0.150	Detector	Characteristics Same as Type 6AL5.										
12AL8	T-6½	Tri. Tetrode	9GS	12.6	0.550	Tri. Amp. Tet. Amp.	12.6	0.9 ⁴	0.5	13000	1000	13		
							12.6	G2=0.5 ⁴	G1=12.6	40	75	480	15000		
							Designed for Space-Charge Grid Operation.										
12AL11	Comp. T-9	Duo. Pent.	12BU	12.6*	0.450	FM Det. S.T. A1 Amp.	1.7 10	Characteristics Same as Type 6AL11. (12AL11 Designed for Series String Receivers.)									
12AQ5	T-5½	Beam Pent.	7BZ	12.6	0.225	Power Amp.	13.2	Characteristics Same as Type 6AQ5.									
12AS5	T-5½	Beam Pent.	7CV	12.6	0.400	S.T. A1 Amp.	6.0	Characteristics Same as Type 6AS5.									
12AT6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	0.55	Characteristics Same as Type 6AT6.									
12AT7	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	VHF Amp.	2.75	100	270 [¶]	3.7	4000	60		
12AT7WA (3)							250	200 [¶]	10.0	5500	60		
12AU6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6AU6.									
12AU7	T-6½	Duotriode	9A	12.6 6.3	0.150 0.300	Amplifier	3.0	250	8.5	10.5	7700	2200	17		
12AU7A							100	0	11.8	6500	3100	20		
12AV5GA	T-11 or T-12	Beam Pent.	6CK	12.6*	0.600	Horizontal Defl. Amp.	12.1	Characteristics Same as Type 6AV5GA. (12AV5GA Designed for Series String TV Receivers.)									
12AV6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	0.55	Characteristics Same as Type 6AV6.									
12AV7	T-6½	Duotriode	9A	12.6 6.3	0.225 0.450	A-F Amp.	2.97	100	120 [¶]	9.0	6100	6100	37		
							150	56 [¶]	18	4800	8500	41		
12AW6	T-5½	Pentode	7CM	12.6	0.150	R-F Amp.	2.2	250	200 [¶]	150	7.0	2.0	0.8 Meg.	5000		
							125	100 [¶]	125	7.2	2.1	0.5 Meg.	5100		
							100	100 [¶]	100	5.5	1.6	0.3 Meg.	4750		
12AX3	Comp. T-9	Diode	12BL	12.6*	0.600	T.V. Damper	5.3	Characteristics Same as Type 6AX3. (12AX3 Designed for Series String Receivers.)									
12AX4GT	T-9	Diode	4CG	12.6	0.600	T.V. Damper	5.28	P.I.V. = 4400 Volts Max., D.C. Plate Current = 125 Ma. Max. (12AX4GTA Designed for Series String TV Receivers.)									
12AX4GTA							P.I.V. = 5000 Volts Max., D.C. Plate Current = 125 Ma. Max.									
12AX4GTB	T-9	Diode	4CG	12.6*	0.600	T.V. Damper	5.28	P.I.V. = 5000 Volts Max., D.C. Plate Current = 125 Ma. Max.									
12AX7	T-6½	Duotriode	9A	12.6 6.3	0.150 0.300	Amplifier	1.1	100	1	0.5	80000	1250	100		
							250	2	1.2	62500	1600	100		
12AX7A	T-6½	Duotriode	9A	12.6 6.3	0.150 0.300	Audio Amp.	1.1	Low Noise and Low Microphoism Version of Identical Type 12AX7.									
12AY3	Novar T-9	Diode	9HP	12.6*	0.600	T.V. Damper	6.5	Characteristics and Ratings Same as Type 6AY3. (12AY3 Designed for Series String Receivers.)									
12AY7	T-6½	Duotriode	9A	12.6	0.150	Audio Amp.	1.65	250	4.0	3.0	1750	40		
12AZ7	T-6½	Duotriode	9A	6.3 12.6	0.450* 0.225	VHF Amp.	2.75	100	270 [¶]	3.7	15000	4000	60		
							250	200 [¶]	10.0	10900	5500	60		
12AZ7A	T-6½	Duotriode	9A	12.6/ 6.3*	0.225 0.450	VHF Osc./ Amp.	2.5	Characteristics Same as Type 12AZ7.									
12B3	T-6½	Diode	9BD	12.6*	0.600	T.V. Damper	Characteristics Same as Type 6B3. (12B3 Designed for Series String TV Receivers.)									
12B4A	T-6½	Triode	9AG	6.3*/ 12.6	0.600/ 0.300	Vert. Defl. Amplifier	6.0	Max. Peak Pos. Pulse Plate Voltage = 1000 Volts Max. D.C. Cathode Current = 30 Ma. (12B4A Designed for Series String TV Receivers.)									
							150	17.5	35	6500	6.5		
12BA6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6BA6.									
12BA7	T-6½	Heptode	8CT	12.6	0.150	Converter	2.2	Characteristics Same as Type 6BA7.									
12BD6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6BD6.									
12BE6	T-5½	Heptode	7CH	12.6	0.150	Converter	1.1	Characteristics Same as Type 6BE6.									
12BF6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	2.75	250	9.0	9.5	8500	1900	16	10000	300		

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. †† Filamentary Type. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ††† Conversion Transconductance. †††† Plate to Plate. ††††† Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Ampli-fication Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
12BH7 12BH7A	T-6½	Duotriode	9A	6.3*/ 12.6	0.600/ 0.300	Vert. Defl. Amplifier	3.85 6.6	Max. Peak Pos. Pulse Plate Voltage = 1500 Volts Max. (12BH7A Designed for Series String TV Receivers.)					D.C. Cathode Current = 20 Ma.	3100	17		
12BK5	T-6½	Beam Amp.	9BQ	12.6*	0.600	Power Amp.	9.9	Characteristics Same as Type 6BK5. (12BK5 Designed for Series String TV Receivers.)									
12BL6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.		12.6	0.65*	12.6	1.35	0.5	500000	1350			
12BN6	T-5½	Gated Beam	7DF	12.6	0.150	Quad. F.M. Detector		Characteristics Same as Type 6BN6.									
12BQ6GTA	T-11 T-9	Beam Pent.	6AM	12.6*	0.600	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6BQ6GTA. (12BQ6GTA Designed for Series String TV Receivers.)									
12BQ6GTB	T-9	Beam Pent.	6AM	12.6*	0.600	Horiz. Amp.	12.1	Characteristics Same as Type 6BQ6GTB. (12BQ6GTB Designed for Series String TV Receivers.)									
12BR7	T-6½	Duodiode Tri.	9CF	12.6/ 6.3	0.225/ 0.450	Det. Amp.	2.75	100 250	270 [■] 200 [■]		3.7 10.0		15000 10900	4000 5500	60 60		
12BV7	T-6½	Pentode	9BF	12.6/ 6.3	0.300/ 0.600	Video Amp.	6.87	250	68 [■]	150	27	6.0	85000	13000	1000		
12BW4	T-6½	Duodiode	9DJ	12.6	0.450	F-W Rect.		Characteristics Same as Type 6BW4									
12BX6	T-6½	Pentode	9AQ	12.6	0.150	VHF Amp.	2.5	Characteristics Same as Type 6BX6. (12BX6 Designed for Series String Receivers.)									
12BY7	T-6½	Pentode	9BF	6.3 12.6	0.600 0.300	Video Amp.	7.1	250	100 [■]	180	26	5.75	93000	11000	1035		
12BZ6	T-5½	Pentode	7CM	12.6	0.150	R-F Amp.	2.3	Characteristics Same as Type 6BZ6.									
12CZ7	T-6½	Duotriode	9A	6.3/ 12.6	0.600/ 0.300	Sync. Sep. or Amplifier	1.65	250	2		2.5		31800	3200	100		Cout Sec. 1 = 0.7 μf.
12C5	T-5½	Beam Pent.	7CV	12.6*	0.600	Power Amp.	6.6	120	8	110	49	4.0	10000	7500			2500 2300
12C8	Metal	Duodi. Pent.	8E	12.6	0.150	Det. Amp.	2.47	Characteristics Same as Type 6C8.									
12CA5	T-5½	Beam Pent.	7CV	12.6*	0.600	Power Amp.	5.5	Characteristics Same as Type 6CA5. (12CA5 Designed for Series String TV Receivers.)									
12CM6	T-6½	Beam Pent.	9CK	12.6	0.225	Power Amp.	13.2	Characteristics Same as Type 6CM6.									
12CN5	T-5½	Pentode	7CV	12.6	0.450	I-F Amp.		12.6	2.2 Meg ⁴	12.6	4.5	0.35	40000	3800			
12CR6	T-5½	Diode Pent.	7EA	12.6	0.150	Audio Amp.	2.75	250	2	100	9.6	2.6	800000	2200			
12CS6	T-5½	Dual Control Heptode	7CH	12.6	0.150	Sync. Sep.	11	100	0.0 Gr. 1 1.0 Gr. 1	30 30	0.8 0.75	1.1	1.0 Meg.	950 Gr. 1 1250 Gr. 3		Grid 3 Volts = 0 Grid 3 Volts = 1.0	
12CT8	T-6½	Tri. Pentode	9DA	12.6*	0.300	Sync. Amp. Video Amp.	2.5 2.75	150 200	150 [■] 82 [■]		9.0 125		8200 150000	4900 7000	40		
12CU5	T-5½	Beam Pent.	7CV	12.6*	0.600	Power Amp.	6.6	Characteristics Same as Type 6CU5. (12CU5 Designed for Series String TV Receivers.)									
12CU6	T-12	Beam Pent.	6AM	12.6*	0.600	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6BQ6G, Except Max. D.C. Plate Supply = 550 Volts. (12CU6 Designed for Series String TV Receivers.)									
12CX6	T-5½	Pentode	7BK	12.6	0.150	R-F Amp.		12.6	2.2 Meg ⁴	12.6	3.0	1.4	40000	3100			
12CY6	T-5½	Pentode	7BK	12.6	0.200	R-F Amp.		12.6	2.2 Meg ⁴	12.6	1.6	0.4	140000	3250			
12D4	T-9	Diode	4CG	12.6*	0.600	T.V. Damper	5.5	Max. Inverse Peak Plate Voltage = 4400 Volts. Max. D.C. Plate Current = 155 Ma.									
12D4A	T-9	Diode	4CG	12.6*	0.600	T.V. Damper	8.0	Max. Peak Inverse Plate Voltage = 5000 Volts. Max. D.C. Plate Current = 185 Ma. Characteristics Same as Type 6D4A.									
12DB5	T-6½	Beam Pent.	9GR	12.6*	0.600	Vert. Defl. Amplifier	11	Characteristics Same as Type 6DB5. (12DB5 Designed for Series String TV Receivers.)									
12DE8	T-6½	Diode Pent.	12DE8	12.6	0.200	R-F or I-F Amplifier		12.6	0.8 ⁴	12.6	1.3	0.5	300000	1500			
12DF5	T-6½	Duodiode	9BS	12.6 6.3	0.450 0.900	F-W Rect.		325 A.V. Volts Per Plate, RMS, 100 Ma. Output Current. Condenser Input. 450 A.C. Volts Per Plate, RMS, 100 Ma. Output Current. Choke Input.									
12DF7	T-6½	Duotriode	9A	12.6 6.3	0.150 0.300	Audio Amp.	1.1	Characteristics Same as Type 12AX7. (Special Low Noise.)									
12DJ8	T-6½	Duotriode	9AJ	12.6	0.180	VHF Amp.	2.0	Characteristics Same as Type 6DJ8.									
12DK5	T-6½	Pentode	9GT	12.6	0.300	R-F Amp.		12.6	2.2 Meg ⁴	12.6	2.0	0.65	100000	3300			
12DK7	T-6½	Duodiode Tetrode	9HZ	12.6	0.500	Det. Power Amp. Driver	0.55	12.6	2.2 Meg ⁴	12.6	6.0	1.0	4000	5000		3500	10



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts	
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.													
12DL8	T-6½	Duodiode Tetrode	9HR	12.6	0.550	Det. Power Amp. Driver	12.6	G2 = 2 G1 = 12.6	8	75	480	15000	800	40		
12DM4	T-9	Diode	4CG	12.6*	0.600	T.V. Damper	6.5	Characteristics Same as Type 6DM4. (12DM4 Designed for Series String Receivers.)										
12DM5	T-5½	Beam Pent.	7CV	12.6*	0.450	Power Amp.	6.0	110	7.5	110	49.0	4.0	14000	7500	2500	1900	
12DM7	T-6½	Duotriode	9A	6.3 12.6	0.260 0.130	A-F Amp.	1.1	Low Noise and Low Microphonism Version of Type 12AX7.										
12DQ4	T-9	Diode	4CG	12.6*	0.600	T.V. Damper	6.0	Characteristics Same as Type 6DQ4. (12DQ4 Designed for Series String Receivers.)										
12DQ6A	T-12	Beam Pent.	6AM	12.6*	0.600	Horiz. Defl. Amplifier	16.5	Characteristics Same as Type 6DQ6A. (12DQ6A Designed for Series String TV Receivers.)										
12DQ6B	T-12	Beam Pent.	6AM	12.6*	0.600	Horiz. Defl. Amplifier	17	Characteristics Same as Type 6DQ6B. (12DQ6B Designed for Series String Receivers.)										
12DQ7	T-6½	Pentode	9BF	12.6/ 6.3*	0.300 0.600	Video Amp.	6.5	200	68 [■]	125	26	5.6	53000	10500	
12DS7	T-6½	Duodiode Tetrode	9JU	12.6	0.400	Det. Power Driver	12.6	2.2 Meg ⁴	G1 = 12.6	35-15†	80	700	35	
12DS7A	T-6½	Duodiode Tetrode	9JU	12.6	0.400	Det. Power Driver	12.6	2.2 Meg ⁴	G1 = 12.6	35-11†	80	700	45	
12DT5	T-6½	Beam Pent.	9HN	12.6*	0.600	Vert. Defl. Amplifier	9.0	Characteristics and Ratings Same as Type 6DT5. (12DT5 Designed for Series String Receivers.)										
12DT6	T-5½	Gated Beam	7EN	12.6	0.150	Quad FM Det.	1.7	Characteristics Same as Type 6DT6.										
12DT7	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	A-F Amp.	1.1	Characteristics Same as Type 12AX7. Controlled for Hum and Noise.										
12DT8	T-6½	Duotriode	9AJ	12.6	0.150	A-F Amp.	2.75	100 250	270 [■] 200 [■]	3.7 10	15000 10900	4000 5500	60 60	
12DU7	T-6½	Duodiode Tetrode	9JX	12.6	0.250	Det. Power Amp. Driver	12.6	2.2 Meg ⁴	12.6	12	1.5	6000	6200	2700	25	
12DV7	T-6½	Duodiode Tri.	9JY	12.6	0.150	Det. Amp.	12.6	2.2 Meg ⁴	0.4	19000	750	14	
12DV8	T-6½	Duodiode Tetrode	9HR	12.6	0.375	Detector, Pwr. Amp. Dr.	12.6	18 Ohm [■] and 4.7 Meg ⁴	G1 = 12.6	6.8	54	900	8500	7.6	1250	5	
12DW5	T-6½	Beam Pent.	9CK	12.6*	0.600	Vert. Defl. Amplifier	11	Max. Peak Positive Plate Voltage = 2200 Volts. Max. D.C. Cathode Current = 65 Ma.										
12DW7	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	Sect. 1 A-F Voltage Amp. Sect. 2 A-F Phase Inverter	1.2 3.3	100 250	1.0 2.0	0.5 1.2	80000 62500	1250 1600	100 100	
12DW8	T-6½	Diode-Duo-Triode	9JC	12.6	0.450	Dissimilar Tri's Voltage Amp. Pwr. Amp. Dr.	0.5 0.5	12.6 12.6	1.5 Meg ⁴ 1.0 Meg ⁴	1.9 7.5	3520 970	2700 6500	9.5 6.4	
12DZ6	T-5½	Pentode	7BK	12.6	0.190	R-F Amp.	12.6	G1 = 10 Meg ⁴ G3 = 0	12.6	4.5	2.2	25000	3800	
12DZ8	T-6½	Tri. Beam Pentode	9EX	12	0.450	A-F Voltage Amp. and Power Amp.825	Characteristics Same as Type 6DZ8. (12DZ8 Designed for Series String Receivers.)									
12EA6	T-5½	Pentode	7BK	12.6	0.190	I-F Amp.	12.6	G1 = 10 Meg ⁴ G3 = 0	12.6	3.2	1.4	32000	3800	
12EC8	T-6½	Tri. Pentode	9FA	12.6	0.225	FM Osc. FM Amp.	12.6	0	2.4	6000	4700	25	
12ED5	T-5½	Pentode	7CV	12.6	0.450	S.T. A1 Amp.	6.25	110 125	4.0 4.5	110 125	32 37	4 7	14000 14000	8100 8500	4500 4500	1100 1500	
12EF6	T-9	Beam Pent.	7S	12.6*	0.450	Vert. Defl. Amplifier	11	Characteristics Same as Type 6EF6. (12EF6 Designed for Series String TV Receivers.)										
12EG6	T-5½	Heptode	7CH	12.6	0.150	Mixer Oscillator	12.6	0.8 ⁴	12.6	.04	2.47	150000	800	

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. † Filamentary Type. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) † Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
12EH5	T-5½	Beam Pent.	7CV	12.6*	0.600	S.T. A1 Amp.	5.5	Characteristics Same as Type 6EH5. (12EH5 Designed for Series String Receivers.)									
12EK6	T-5½	Pentode	7BK	12.6	0.190	FM Amp.	12.6	2.2 ⁴	12.6	4.0	1.7	50000	4200
12EL6	T-5½	Duodiode Tri.	7FB	12.6	0.150	Det. Amp.	12.6	1.0 Meg ⁴75	45000	1200	55
12EM6	T-6½	Diode Tetrode	9HV	12.6	0.500	Det. Power Amplifier	0.55	12.6	15 Meg ⁴	12.6	6.0	1.0	4000	5000	3500	10
12EN6	T-9	Beam Pent.	7S	12.6*	0.600	Vert. Defl. Amplifier	7.0	Max. Peak Positive Pulse Plate Voltage = 1200 Volts.		200	9.5	110	50	2.2	28000	8000	Max. D.C. Cathode Currents = 50 Ma.
12EQ7	T-6½	Diode Pent.	9LP	12.6	0.150	Det. R-F Amp.	3.0	Characteristics Same as Type 6EQ7.									
12EZ6	T-5½	Pentode	7BK	12.6	0.175	R-F or I-F Amplifier	12.6	2.2 Meg ⁴	12.6	1.9	0.7	400000	2700
12F5GT	T-9	Triode	5M	12.6	0.150	Amplifier	Characteristics Same as Type 6F5GT.									
12F8	T-6½	Duodi. Pent.	9FH	12.6	0.150	Amplifier	12.6	0	12.6	1.0	0.38	0.33 Meg.	1000
12FA6	T-5½	Heptode	7CH	12.6	0.150	Converter	12.6	0.5	12.6	.45	1.0	800000	320 ^A
								2.2 Meg ⁴ Osc. Grid Values = 2.5 Volts RMS across 33000 Ohm Res.									
12FB5	T-6½	Beam Pent.	9CV	12.6	0.300	S.T. A1 Amp.	6.6	170	10.3	180	31	7.3	5000	2250
12FK6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	12.6	2.2 Meg ⁴	1.3	6200	1200	74
12FM6	T-5½	Duodiode Tri.	7BT	12.6	0.150	Det. Amp.	12.6	2.2 Meg ⁴	1.0	7700	1300	10
12FQ8	T-6½	Twin, Double-Plate Triode	9KT	12.6	0.150	Sect. 1 Double Plate Triode	0.5	250	1.5	1.5	76000	1250	95
						Sect. 2 Double Plate Triode	0.5	250	1.5	1.5	76000	1250	95
12FR8	T-6½	Tri. Pentode Diode	9KU	12.6	0.320	Det. Amp. R-F Amp.	12.6	2.2 Meg ⁴	1.0	40000	1200	10
						R-F Amp.	12.6	2.2 Meg ⁴	12.6	1.9	0.8	400000	2700
12FT6	T-5½	Duodiode Triode	7BT	12.6	0.150	Det. Power Amp. Driver	12.6	2.2 Meg ⁴	0.6	13000	1000	14
12FV7	T-6½	Duotriode	9A	6.3/ 12.6	0.900/ 0.450	Relay Control Tube	2.5	100	2.0	16	2250	9600
12FX8	T-6½	Tri. Heptode	9KV	12.6	0.270	Tri. R-F Amp. Heptode Conv.	12.6	2.2 Meg ⁴	12.6	1.3	0.29	1.25	500000	1400	10	Self Osc. with 33 K Rg1
								12.6	Rg3 2.2Meg ⁴	12.6	0.29	1.25	500000	300 ^A
12FX8A	T-6½	Tri. Heptode	9KV	12.6	0.270	R-F Amp. Converter	12.6	2.2 Meg ⁴	1.3	1400	300 ^A	10	EC1 = 1.6 V (RMS)	
								12.6	G3=2.2M ⁴	12.6	0.29	1.25	Rg1 = 33 K Ohms
12G8	T-6½	Duotriode	9CZ	12.6	0.400	Amplifier	12.6	0	Input Tri.	3.0	8500	2600	22	2000	25
								12.6	Output Tri.	7.2
12GA6	T-5½	Heptode	7CH	12.6	0.150	Converter	12.6	G ³ =2.2 M ⁴	12.6	0.3	0.8	1.0 Meg.	140
							
								EC1 = 1.6 Volts (RMS), Rg1 = 33000 Ohms, IC1 = .06 Ma.									
12GC6	T-12	Beam Pent.	8JX	12.6*	0.600	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GC6. (12GC6 Designed for Series String Receivers.)									
12GE5	Comp. T-12	Beam Pent.	12BJ	12.6*	0.600	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GE5. (12GE5 Designed for Series String Receivers.)									
12GN6	T-5½	Pentode	7FW	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6GN6.									
12GJ5	Novar T-12	Beam Pent.	9NM	12.6*	0.600	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GJ5. (12GJ5 Designed for Series String Receivers.)									
12GT5	Novar T-12	Beam Pent.	9NZ	12.6*	0.600	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GT5. (12GT5 Designed for Series String Receivers.)									
12GW6	T-12	Beam Pent.	6AM	12.6*	0.600	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GW6. (12GW6 Designed for Series String Operation.)									
12H6	Metal	Duodiode	7Q	12.6	0.150	Rectifier	Characteristics Same as Type 6H6.									
12J5GT	T-9	Triode	6Q	12.6	0.150	Amplifier	2.75	Characteristics Same as Type 6J5GT.									
12J7GT	T-9	Pentode	7R	12.6	0.150	R-F Amp.	.825	Characteristics Same as Type 6J7G.									
12J8	T-6½	Duo. Tetrode	9GC	12.6	0.300	Det. Amp.	12.6	2.2 Meg ⁴	12.6	12	1.5	6000	5500	2700	20



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
12K5	T-5½	Tetrode	7FD	12.6	0.400	Power Amp. Driver	12.6	G2=2	G1=12.6	8	75	480	15000	7.2	800	40
							(Designed for Space-Change Grid Operation.)										
12K7GT	T-9	Pentode	7R	12.6	0.150	R-F Amp.	3.0	Characteristics Same as Type 6K7G.									
12K8	Metal	Tri. Hexode	8K	12.6	0.150	Mixer Osc. Converter	3.0	Characteristics Same as Type 6K8GT.									
12L6GT	T-9	Beam Pent.	7S	12.6*	0.600	Power Amp.	11	Characteristics Same as Type 25L6GT. (12L6GT Designed for Series String TV Receivers.)									
12Q7GT	T-9	Duodiode Tri.	7V	12.6	0.150	Det. Amp.	0.55	Characteristics Same as Type 6Q7GT.									
12R5	T-5½	Beam Pent.	7CV	12.6*	0.600	Vert. Defl. Amplifier	4.95	Max. Peak Positive Pulse Plate Voltage = 1500 Volts. Max. D.C. Cathode Current = 45 Ma.									
							110 8.5 110 40.0 3.3 13000 7000 										
12SA7	Metal	Heptode	8R	12.6	0.150	Converter	1.1	Characteristics Same as Type 6SA7.									
12SA7GT	T-9		8AD														
12SC7	Metal	Duotriode	8S	12.6	0.150	A-F Amp.	3.85	Characteristics Same as Type 6SC7.									
12SF5	Metal	Triode	6AB	12.6	0.150	A-F Amp.	Characteristics Same as Type 6SF5.									
12SF5GT	T-9																
12SF7	Metal	Diode Pent.	7AZ	12.6	0.150	Det. Amp.	3.85	Characteristics Same as Type 6SF7.									
12SG7	Metal	Pentode	8BK	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6SG7.									
12SH7	Metal	Pentode	8BK	12.6	0.150	R-F Amp.	3.3	Characteristics Same as Type 6SH7.									
12SJ7	Metal	Pentode	8N	12.6	0.150	A-F Amp.	2.75	Characteristics Same as Type 6SJ7.									
12SJ7GT	T-9		8N														
12SK7	Metal	Pentode	8N	12.6	0.150	R-F Amp.	4.4	Characteristics Same as Type 6SK7.									
12SK7GT	T-9		8N														
12SL7GT	T-9	Duotriode	8BD	12.6	0.150	Amplifier	1.1	Characteristics Same as Type 6SL7GT.									
12SN7GTA	T-9	Duotriode	8BD	12.6	0.300	Vertical Osc. Amp.	3.85	Characteristics Same as Type 6SN7GTA.									
12SQ7	Metal	Duodiode Tri.	8Q	12.6	0.150	Det. Amp.	0.55	Characteristics Same as Type 6SQ7.									
12SQ7GT	T-9																
12SR7	Metal	Duodiode Tri.	8Q	12.6	0.150	Det. Amp.	2.75	Characteristics Same as Type 6SR7.									
12U7	T-6½	Duotriode	9A	12.6	0.150	Class A1 Amp.	12.6	0	1.0	12500	1600	20
12V6GT	T-9	Beam Pent.	7S	12.6	0.225	Power Amp.	13.2	180	8.5	180	29	3	50000	3700	5500	2000
							250 12.5 250 45 4.5 50000 4100 5000										
12W6GT	T-9	Beam Pent.	7S	12.6*	0.600	Power Amp. Vert. Defl. Amplifier	11	Characteristics Same as Type 6W6GT. (12W6GT Designed for Series String TV Receivers.)									
12X4	T-5½	Duodiode	5BS	12.6	0.300	F-W Rect.	Characteristics Same as Type 6X4.									
13DE7	T-6½	Duotriode	9HF	13.0*	0.450	Vert. Osc. Vert. Defl. Amplifier	1.5	Characteristics Same as Type 16DE7. (13DE7 Designed for Series String TV Receivers.)									
							7.0										
13DR7	T-6½	Duotriode	9HF	13*	0.450	S. 2 Ver. Amp. S. 1 Ver. Osc.	1.0	Characteristics Same as Type 6DR7. (13DR7 Designed for Series String Receivers.)									
							7.0										
13EM7	T-9	Duotriode	8BD	13*	0.450	Vert. Defl. Amp./Osc.	1.5	Characteristics Same as Type 6EM7. (13EM7 Designed for Series String Receivers.)									
							10										
13FD7	9-T9	Duotriode	9HF	13.0*	0.450	Vert. Defl. Amp./Osc.	1.5	Characteristics Same as Type 6FD7. (13FD7 Designed for Series String Receivers.)									
							10										
13FR7	9-T9	Duotriode	9HF	13.0*	0.450	Vert. Defl. Amp./Osc.	1.5	Characteristics Same as Type 6FR7. (13FR7 Designed for Series String Receivers.)									
							10										
14A7	Lock-in	Pentode	8V	12.6	0.150	R-F Amp.	4.4	Characteristics Same as Type 7A7.									
14AF7/XXD	Lock-in	Duotriode	8AC	12.6	0.150	Amplifier	2.75	Characteristics Same as Type 7AF7.									

(1) See Frontal Section. (3) Has Special Mechanical and/or Life Characteristics. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
 (2) Design Maximum Values. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. † Plate to Plate. ■ Cathode Resistor (ohms).
 ‡ Maximum Signal. †† Filamentary Type. ††† Conversion Transconductance.



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
14B6	Lock-in	Duodiode Tri.	8W	12.6	0.150	Det. Amp.	0.55	Characteristics Same as Type 7B6.									
14C5	Lock-in	Beam Pent.	6AA	12.6	0.225	Power Amp.	13.2	Characteristics Same as Type 7C5.									
14C7	Lock-in	Pentode	8V	12.6	0.150	R-F Amp.	1.1	100	1.0	100	5.7	1.8	400000	2275
								250	3.0	100	2.2	0.7	1.0 Meg.	1575
14F7	Lock-in	Duotriode	8AC	12.6	0.150	A-F Amp.	1.1	Characteristics Same as Type 7F7.									
14F8	Lock-in	Duotriode	8BW	12.6	0.150	Osc. Amp.	3.85	Characteristics Same as Type 7F8.									
14GT8	T-6½	Duodiode Triode	9KR	14	0.150	FM Det. Audio Amp.	1.1	250	3.0	0.7	72000	1000	72
14JG8	T-6½	Duodiode Triode	9KR	14	0.150	FM Det./A-F Amp.	1.1	250	2.0	2	41000	2200	90
14Q7	Lock-in	Heptode	8AL	12.6	0.150	Converter	1.1	Characteristics Same as Type 7Q7.									
14R7	Lock-in	Duodi. Pent.	8AE	12.6	0.150	Det. Amp.	2.2	Characteristics Same as Type 7R7.									
15AF11	Comp. T-9	Pentode Duotriode	12DP	14.7*	0.450	Video Amp. AGC Keyer Svc. Sep.	Characteristics Same as Type 6AF11. (15AF11 Designed for Series String Receivers.)									
15CW5	T-6½	Beam Pent.	9CV	15	0.300	A-F Pwr. Amp.	13	Characteristics Same as Type 6CW5. (15CW5 Designed for Series String Receivers.)									
15EA7	T-9	Duotriode	8BD	14.8*	0.450	Vert. Defl. Amp./Osc.	1.0	Characteristics Same as Type 6EA7. (15EA7 Designed for Series String Receivers.)									
							10										
15EW6	T-5½	Pentode	7CM	15.	0.150	VHF Amp.	3.1	125	56 ^m	125	11	3.2	200000	14000
16GK6	T-6½	Beam Pent.	9PU	16*	0.300	Power Amp.	13.2	Characteristics Same as Type 6GK6. (16GK6 Designed for Series String Receivers.)									
17AV5GA	T-11 or T-12	Beam Pent.	6CK	16.8*	0.450	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6AV5GA. (17AV5GA Designed for Series String TV Receivers.)									
17AX4GT	T-9	Diode	4CG	16.8	0.450	T.V. Damper	5.28	Characteristics Same as Type 6AX4GT. (17AX4GT Designed for Series String TV Receivers.)									
17AX4GTA	T-9	Diode	4CG	16.8*	0.450	T.V. Damper	5.3	Maximum Peak Inverse Plate Voltage = 5000 Volts. Maximum D.C. Plate Current = 125 Ma.									
17AY3	Novar T-9	Diode	9HP	16.8*	0.450	T.V. Damper	6.5	Characteristics and Ratings Same as Type 6AY3. (17AY3 Designed for Series String Receivers.)									
17BH3	Novar T-9	Diode	9HP	17*	0.600	T.V. Damper	6.5	Characteristics and Ratings Same as Type 6BH3.									
17BQ6GTB	T-12	Beam Pent.	6AM	16.8*	0.450	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6BQ6GTB. (17BQ6GTB Designed for Series String TV Receivers.)									
17C5	T-5½	Beam Pent.	7CV	16.8*	0.450	Power Amp.	6.6	Characteristics Same as Type 12C5. (17C5 Designed for Series String TV Receivers.)									
17C8	T-6½	Duodi. Pent.	9T	17	0.100	Det. R-F Amp.	1.65	200	295 ^m	60	5	1.75	1 Meg.	2200
17C9A	T-6½	Duotetrode	10F	16.8*	0.150	VHF Amp.	2.5	Characteristics Same as Type 6C9. (17C9A Designed for Series String Receivers.)									
17CA5	T-5½	Beam Pent.	7CV	16.8*	0.450	Power Amp.	5.5	Characteristics Same as Type 12CA5. (17CA5 Designed for Series String TV Receivers.)									
17D4	T-9	Diode	4CG	16.8*	0.450	T.V. Damper	5.5	Maximum Peak Inverse Plate Voltage = 4400 Volts. Maximum D.C. Plate Current = 155 Ma.									
17D4A	T-9	Diode	4CG	16.8*	0.450	T.V. Damper	8.0	Characteristics Same as Type 12D4. (17D4 Designed for Series String Receivers.)									
17DE4	T-9	Diode	4CG	17.0*	0.600	T.V. Damper	6.5	Characteristics and Ratings Same as 6DE4. (17DE4 Designed for Series String Receivers.)									
17DM4	T-9	Diode	4CG	16.8*	0.450	T.V. Damper	6.5	Characteristics Same as Type 6DM4. (17DM4 Designed for Series String Receivers.)									
17DQ4	T-9	Diode	4CG	16.8*	0.450	T.V. Damper	6.0	Characteristics Same as Type 6DQ4. (17DQ4 Designed for Series String Receivers.)									
17DQ6	T-12	Beam Pent.	6AM	16.8*	0.450	Horiz. Defl. Amplifier	16.5	Characteristics Same as Type 6DQ6. (17DQ6 and 17DQ6A Designed for Series String TV Receivers.)									
17DQ6A	T-12	Beam Pent.	6AM	16.8*	0.450	Horiz. Defl. Amplifier	18	Characteristics Same as Type 6DQ6A.									
17DQ6B	T-12	Beam Pent.	6AM	16.8*	0.450	Horiz. Defl. Amplifier	18	Characteristics Same as Type 6DQ6B. (17DQ6B Designed for Series String Receivers.)									
17GJ5	Novar T-12	Beam Pent.	9NM	16.8*	0.450	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GJ5. (17GJ5 Designed for Series String Receivers.)									
17GT5	Novar T-12	Beam Pent.	9NZ	16.8*	0.450	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GT5. (17GT5 Designed for Series String Receivers.)									
17GW6	T-12	Beam Pent.	6AM	16.8*	0.450	Horiz. Defl. Amplifier	17.5	Characteristics Same as Type 6GW6. (17GW6 Designed for Series String Operation.)									
17H3	T-6½	Diode	9FK	17.5*	0.300	T.V. Damper	3.0	Maximum Peak Inverse Plate Voltage = 2000 Volts. Maximum D.C. Output Current = 75 Ma.									




AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts	
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.													
17HC8	9-T9	Tri. Pentode	9EX	16.8*	0.450	Vert. Defl. Osc./Amp.	1.0	Characteristics Same as Type 6HC8. (17HC8 Designed for Series String Receivers.)										
17JK8	T-6½	Duotriode	9AJ	16.8*	0.150	FM Osc. FM Amp.	1.0 2.0	100 135	1.0 1.2	5.3 10	8000 5400	6800 13000	55 70	
17L6GT	T-9	Beam Pent.	7S	16.8*	0.450	Power Amp.	11	Characteristics Same as Type 25L6GT. (17L6GT Designed for Series String TV Receivers.)										
17R5	T-5½	Beam Pent.	7CV	16.8*	0.450	Vert. Defl. Amplifier	4.95	Characteristics Same as Type 12R5. (17R5 Designed for Series String TV Receivers.)										
17W6GT	T-9	Beam Pent.	7S	16.8*	0.450	A-F Pwr. Amp.	12	Characteristics Same as Type 6W6GT. (6W6GT Designed for Series String Receivers.)										
18A5	T-9	Beam Pent.	6CK	18.5*	0.300	Horiz. Defl. Amplifier	9.0	Max. Peak Positive Pulse Plate Voltage = 3000 Volts. Max. D.C. Cathode Current = 90 Ma.										
18DZ8	T-6½	Tri. Beam Pentode	9EX	18.0	0.300	A-F Voltage Amp. and Power Amp.	.825 7.15	Characteristics Same as Type 6DZ8. (18DZ8 Designed for Series String Receivers.)										
18FW6	T-5½	Pentode	7BK	18.0	0.100	R-F or I-F Amplifier	2.5	100	68 [¶]	100	11	4.4	250000	4400	
18FX6	T-5½	Heptode	7CH	18.0	0.100	Converter	1.0	100	1.5	100	2.3	6.2	400000	480	Osc. Grid Res. = 20000 Ohms Osc. Grid Current = 0.5 Ma.			
18FY6	T-5½	Duodiode Tri.	7BT	18.0	0.100	A-F Amp.	0.5	100	1.0	0.6	77000	1300	100	
18GD6	T-5½	Pentode	7BK	18.0	0.100	R-F Amp.	2.5	100	150 [¶]	100	5.0	2.0	500000	4300	
18GE6	T-5½	Duodiode Tri.	7BT	18.0	0.100	Det. Amp.	0.5	100	1.0	1.0	40000	1700	70	
18HB8	T-6½	Triode Beam Pentode	9ME	18	0.300	Voltage Amp. S.T. A1 Amp.	.75 6.5	115 115	410 [¶] 150 [¶]	2.5 33	3900 6250	74	3500 1000	
19AQ5	T-5½	Beam Pent.	7BZ	18.9	0.150	Power Amp.	13.2	Same as 6AQ5.										
19AU4	T-9	Diode	4CG	18.9*	0.600	T.V. Damper	6.6	Characteristics Same as Type 6AU4GT. (19AU4 Designed for Series String TV Receivers.)										
19AU4GTA	T-9	Diode	4CG	18.9*	0.600	T.V. Damper	6.6	Characteristics Same as Type 6AU4GTA. (19AU4GTA Designed for Series String TV Receivers.)										
19BG6G	ST-16	Beam Pent.	5BT	18.9	0.300	Amplifier	22	Characteristics Same as Type 6BG6G.										
19BG6GA	T-12	Beam Pent.	5BT	18.9	0.300	Amplifier	22	Characteristics Same as Type 6BG6G.										
19C8	T-6½	Triple Dio. Tri.	9E	18.9	0.150	Det. Amp.	1.1	100	1.0	0.5	80000	1250	100	
19CL8A	T-6½	Tri. Tetrode	9FX	18.9	0.150	VHF Osc. VHF Amp.	2.97 3.0	Characteristics Same as Type 6CL8A.										
19DE7	T-6½	Duotriode	9HF	19.4*	0.300	Vert. Defl. Amp. and Osc.	7.0 1.5	Characteristics Same as Type 6DE7. (19DE7 Designed for Series String Receivers.)										
19EA8	T-6½	Tri. Pentode	9AE	18.9	0.150	Tri. VHF Amp. Pent. Amp.	3.0 3.1	Characteristics Same as Type 6EA8.										
19EZ8	T-6½	Triple Triode	9KA	18.9	0.150	VHF Amp.	2.0	125	1.0	4.2	13600	4200	57	
19HR6	T-5½	Pentode	7BK	18.9*	0.150	FM I-F Amp.	3.0	Characteristics Same as Type 6HR6. (19HR6 Designed for Series String Receivers.)										
19HV8	T-6½	Tri. Pentode	9FA	18.9	0.150	A-F Amp. I-F Amp.	0.5 3.0	100 125	1.0 1.0	0.8 12	4 4	54000 200000	1300 6500	70
19J6	T-5½	Duotriode	7BF	18.9	0.150	VHF Osc. Amplifier	1.65	Characteristics Same as Type 6J6.										
19T8	T-6½	Triple Diode Triode	9E	18.9	0.150	Det. Amp.	1.1	Characteristics Same as Type 6T8.										
19V8	T-6½	Triple Diode Triode	9AH	18.9	0.150	Det. Amp.	1.1	100 250	1.0 3.0	0.8 1.0	54000 58000	1300 1200	70 70	
19X8	T-6½	Tri. Pentode	9AK	18.9	0.150	VHF Osc. Amplifier	1.65 2.2	Characteristics Same as Type 6X8.										
20EQ7	T-6½	Diode Pent.	9LQ	20	0.100	Det. R-F Amp.	3.0	Characteristics Same as Type 6EQ7.										

(1) See Frontal Section.
(2) Design Maximum Values.
‡ Maximum Signal.

















(3) Has Special Mechanical and/or Life Characteristics.
(4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
‡ Filamentary Type. † Conversion Transconductance.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
‡ Plate to Plate. † Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
20E27	T-6½	Duotriode	9PG	20*	0.100	A-F Amp.	1.2	100 250	1.0 2.0	0.5 1.2	80000 62500	1250 1600	100 100
21EX6	T-12	Beam Pent.	5BT	21.5*	0.600	Horiz. Defl. Amplifier	22	Characteristics Same as Type 6EX6. (21EX6 Designed for Series String Receivers.)									
22BH3	Novar T-9	Diode	9HP	22.4*	0.450	T.V. Damper	6.5	Characteristics and Ratings Same as Type 6BH3.									
22DE4	T-9	Diode	4CG	22*	0.450	T.V. Damper	6.5	Characteristics and Ratings Same as Type 6DE4. (22DE4 Designed for Series String Receivers.)									
25AV5GA	T-11 or T-12	Beam Pent.	6CK	25.0	0.300	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6AV5GA.									
25AX4GT	T-9	Diode	4CG	25.0	0.300	T.V. Damper	5.28	P.I.V. = 4000 Volts Max. D.C. Plate Current = 125 Ma. Max.									
25BK5	T-6½	Beam Pent.	9BQ	25.0	0.300	Power Amp.	9.9	Characteristics Same as Type 6BK5.									
25BQ6GA	T-11	Beam Pent.	6AM	25.0	0.300	Horiz. Defl. Amplifier	12.1	Characteristics and Ratings Same as Type 6BQ6G.									
25BQ6GT	T-9	Beam Pent.	6AM	25.0	0.300	Horiz. Defl. Amplifier	12.1	Characteristics Same as Type 6BQ6GT.									
25BQ6GTB	T-9	Beam Pent.	6AM	25.0	0.300	Horiz. Amp.	12.1	Characteristics Same as Type 6BQ6GTB.									
25C5	T-5½	Beam Pent.	7CV	25.0	0.300	Power Amp.	6.6	120	8	110	49	4.0	10000	7500	2500	2300
25CA5	T-5½	Beam Pent.	7CV	25.0	0.300	Power Amp.	5.5	Characteristics Same as Type 6CA5.									
25CD6GB	T-12	Beam Pent.	5BT	25.0*	0.600	Horiz. Defl. Amplifier	22	Characteristics Same as Type 6CD6GA. (25CD6GB Designed for Series String TV Receivers.)									
25DK4	T-5½	Diode	5BQ	25	0.150	H-W Rect.	117 A.C. Volts, RMS, 90 Ma. D.C. Output. (Condenser Input to Filter.)									
25DN6	T-12	Beam Pent.	5BT	25.0*	0.600	Horiz. Defl. Amplifier	16.5	Peak Positive Pulse Plate Voltage = 6600 Volts Max. D.C. Cathode Current = 200 Ma. (25DN6 Designed for Series String TV Receivers.)									
25DQ6A	T-12	Beam Pent.	6AM	25*	0.300	Horiz. Defl. Amplifier	16.5	Characteristics Same as Type 6DQ6A. (25DQ6A Designed for Series String Receivers.)									
25DT5	T-6½	Beam Pent.	9HN	25*	0.300	Vert. Defl. Amplifier	9.0	Characteristics Same as Type 6DT5. (25DT5 Designed for Series String Operation.)									
25EH5	T-5½	Beam Pent.	7CV	25	0.300	S.T. A1 Amp.	5.5	Characteristics Same as Type 6EH5.									
25L6GT	T-9	Beam Pent.	7S	25.0	0.300	Power Amp. P-PA1 Amp.	11	110 200	7.5 180 ^M	110 125	49.0 46	4.0 2.2	13000 28000	8000 8000	2000 4000	2100 3800
25W4GT	T-9	Diode	4CG	25.0	0.300	H-W Rect.	3.85	350 A.C. Volts RMS, 125 Ma. D.C. Output. Condenser Input to Filter.									
25W6GT	T-9	Beam Pent.	7S	25.0	0.300	Power Amp.	11	110 225	7.5 30	110	50 22	4.0 Tri. Conn.	13000 1600	8000 3800 6.2	2000	2100
25Z5	ST-12	Duodiode	6E	25.0	0.300	Doubler	Characteristics Same as Type 25Z6GT.									
25Z6GT	T-9	Duodiode	7Q	25.0	0.300	Doubler H-W Rect.	117 A.C. Volts Per Plate, RMS, 75 Ma. Output Current. 235 A.C. Volts, RMS, 75 Ma. Output Current Per Plate.									
27GB5	Magnoval T-9	Beam Pent.	9HN	27	0.300	Horiz. Defl. Amplifier	17	Characteristics and Ratings Same as Type 6GB5. (27GB5 Designed for Series String Receivers.)									
28D7	Lock-in	Duo. Beam Pentode	8BS	28.0	0.400	Amplifier (per section)	3.0	28	390 ^M	28	9.0	0.7	4000	80
28D7W (3)						P.P. A2 Total	28	3.5	28	12.5	1.0	4200	3400	4000	100
GB-28D7W (3)						P.P. A2 Total	28	0	28	64.0	4.0	1500 [†]	600
28GB5	Magnoval T-9	Beam Pent.	9HN	28	0.300	Horiz. Defl. Amplifier	17	Characteristics and Ratings Same as Type 6GB5.									
32ET5	T-5½	Beam Pent.	7CV	32	0.100	Power Amp.	5.4	110	7.5	110	30	2.8	21500	5500	2800	1200
EL34/6CA7	T-10 (SP)	Beam Pent.	8ET	6.3	1.500	S.T. A1 Amp. P.P.AB1 Amp.	27.5	250 430	13.5 235 ^M	250 425	100 126-140 [†]	15 10-15 [†]	15000	11000	2000	11000 37000
GZ34	T-11	Duodiode	5L	5.0 [†]	1.900	F-W Rect.	Characteristics and Ratings Same as Type 5AR4.									
34GD5	T-5½	Beam Pent.	7CV	34	0.100	S.T. A1 Amp.	5.0	110	7.5	110	35	3	13000	5700	2500	1300
35A5	Lock-in	Beam Pent.	6AA	35.0	0.150	Power Amp.	9.35	110 200	7.5 180 ^M	110 110	40.0 43.0	3.0 2.0	14000 34000	5800 6100	2500 5000	1500 3000
35B5	T-5½	Beam Pent.	7BZ	35.0	0.150	Power Amp.	4.95	110	7.5	110	40.0	3.0	5800	2500	1500
35C5	T-5½	Beam Pent.	7CV	35.0	0.150	Power Amp.	4.95	110	7.5	110	40	3.0	5800	2500	1500
35CD6GA	T-12	Beam Pent.	5BT	35.0*	0.450	Horiz. Defl. Amplifier	22	Characteristics Same as Type 6CD6GA. (35CD6GA Designed for Series String TV Receivers.)									




AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
35DZ8	T-6½	Tri. Beam Pentode	9EX	35	0.150	A-F Voltage Amp. and Power Amp.	.825 7.15	Characteristics Same as Type 6DZ8. (35DZ8 Designed for Series String Receivers.)									
35EH5	T-5½	Beam Pent.	7CV	35	0.150	A-F Pwr. Amp.	5.5	Characteristics Same as Type 6EH5.									
35GL6	T-5½	Beam Pent.	7FZ	35	0.150	S.T. A1 Amp.	5.5	110	7.5	110	45-47†	3-9†	12000	7500	2500	1800
35HB8	T-6½	Triode Beam Pent.	9ME	35	0.150	Voltage Amp. S.T. A1 Amp.	.75 6.5	Characteristics Same as Type 18HB8.									
35L6GT	T-9	Beam Pent.	7S	35.0	0.150	Power Amp.	9.35	110 200	7.5 8.0	110 110	40.0 43.0	3.0 2.0	14000 34000	5800 6100	2500 5000	1500 3000
35W4	T-5½	Diode	5BQ	35.0	0.150	H-W Rect.	117 A.C. Volts, RMS, 60 Ma. Output Current with Panel Lamp. 117 A.C. Volts, RMS, 100 Ma. Output Current without Panel Lamp.									
35Y4	Lock-in	Diode	5AL	35.0	0.150	H-W Rect.	235 Max. A.C. Volts, RMS, 60 Ma. Output Current with Panel Lamp. 235 Max. A.C. Volts, RMS, 100 Ma. Output Current without Panel Lamp.									
35Z3	Lock-in	Diode	4Z	35.0	0.150	H-W Rect.	235 Max. A.C. Volts Per Plate, RMS, 100 Ma. Output Current. Condenser Input to Filter.									
35Z5GT	T-9	Diode	6AD	35.0	0.150	H-W Rect.	Characteristics Same as Type 35Y4.									
36AM3	T-5½	Diode	5BQ	36	0.100	H-W Rect.	117 A.C. Volts, RMS, 75 Ma. Capacitor Input to Filter.									
36AM3A	T-5½	Diode	5BQ	36	0.100	H-W Rect.	120 A.C. Volts Per Plate, RMS, 75 Ma. Condenser Input to Filter.									
EL37	Curved Bulb	Beam Pent.	7S	6.3	1.400	S.T. A1 Amp. P.P.AB1 Amp.	250 400	13.5 36	250 400	100 100-276†	13.5 12-72†	13500	11000	2500 3250†	11500 69000
40A1	T-9	Ballast	8ES	Horiz. Reg.	Avg. Operating Current—0 Ma. at 20 Volts; 150 Ma. at 40 Volts; 155 Ma. at 60 Volts.									
40B2	T-9	Ballast	8ES	Horiz. Reg.	Avg. Operating Current—140 Ma. at 20 Volts; 150 Ma. at 40 Volts; 155 Ma. at 60 Volts.									
40FR5	T-5½	Power Pent.	7CV	40	0.100	A-F Power Amplifier	5.2	110 115	7.5 180 [■]	110 115	32 34	3 7	20000	6000	2800 3200	1500 1300
41	ST-12	Power Pent.	6B	6.3	0.400	Power Amp.	9.35	Characteristics Same as Type 6K6GT.									
42	ST-14	Power Pent.	6B	6.3	0.700	Power Amp.	12.1	Characteristics Same as Type 6F6G.									
43	ST-14	Power Pent.	6B	25.0	0.300	Power Amp.	5.83	Characteristics Same as Type 25A6GT.									
45	ST-14	Triode	4D	2.5 ⁴	1.500	Power Amp.	11	180 250 275	31.5 50.0 56.0	31.0 34.0 36.0	1650 1610 1700	2125 2175 2050	3.5 3.5 3.5	2700 3900 4600	830 1600 2000
50A1	T-6½	Ballast	9CM	Fil. Ballast	Avg. Operating Current—59 Ma. at 30 Volts; 54 Ma. at 50 Volts; 56 Ma. at 65 Volts.									
50A5	Lock-in	Beam Pent.	6AA	50.0	0.150	Power Amp.	11	110 200	7.5 8.0	110 110	49.0 50.0	4.0 1.5	13000 28000	8000 8000	2000 4000	2100 3800
50AX6G	ST-14	Duodiode	7Q	50.0	0.300	F-W Rect.	Characteristics Same as Type 6AX6G.									
50B5	T-5½	Beam Pent.	7BZ	50.0	0.150	Power Amp.	6.6	120	8	110	49	4.0	10000	7500	2500	2300
50BK5	T-6½	Beam Pent.	9BQ	50.0	0.150	Power Amp.	9.9	250	5.0	250	35	3.5	0.1 Meg.	8500	6500	3500
50BM8	T-6½	Tri. Pentode	9EX	50	0.100	A-F Tri. Amp. Power Amp.	1.1 7.7	100 100 200	0 6 16 100 200	3.5 26 35 5 7	28000 15000 20000	2500 6800 6400	70 3900 5600 1050 3500
50C5	T-5½	Beam Pent.	7CV	50.0	0.150	Power Amp.	6.6	120	8	110	49.	4.0	10000	7500	2500	2300
50CA5	T-5½	Beam Pent.	7CV	50	0.150	Power Amp.	5.5	Characteristics Same as Type 6CA5.									
50DC4	T-5½	Diode	5BQ	50	0.150	H-W Rect.	117 A.C. Volts Per Plate, RMS, 110 Ma. Output Current. Heater Top Voltage (Pin 4 to Pin 6) = 7.5 Volts.									
50EH5	T-5½	Beam Pent.	7CV	50	0.150	S.T. A1 Amp.	5.5	Characteristics Same as Type 6EH5.									
50FA5	T-5½	Beam Pent.	7CV	50	0.150	S.T. A1 Amp.	5.2	110	7.5	110	40	3	13000	5800	2500	1500
50FE5	T-6½	Beam Pent.	8KB	50	0.150	S.T. A1 Amp. P.P. AB1 Amp.	14.5	Characteristics Same as Type 6FE5.									
50FK5	T-5½	Power Pent.	7CV	50	0.100	S.T. A1 Amp.	5.0	110	62 [■]	110	32	8.5	14000	12800	3000	1200

(1) See Frontal Section.
(2) Design Maximum Values.
† Maximum Signal.


(3) Has Special Mechanical and/or Life Characteristics.
(4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
‡ Filamentary Type. ▲ Conversion Transconductance.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
¶ Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts		
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.														
50FY8	T-6½	Tri. Beam Pentode	9EX	50	0.150	Tri. Volt. Amp. Pent. S.T.A1 A. Pent. P.P.A1 A.	1.0 1.0	125 125 125	1.5 120 [■] 62 [■] 125 125	2.5 70-66† 10-19†	17000 5000 7500	2700 5000 7500	46 2000 4000† 3000 6000		
50HC6	T-5½	Pentode	7FZ	50	0.150	S.T. A1 Amp.	5.5	110	62 [■]	115	42	11.5	11000	14600	3000	1.4		
50L6GT	T-9	Beam Pent.	7S	50.0	0.150	Power Amp.	11	Characteristics Same as Type 25L6GT.											
50X6	Lock-in	Duodiode	7DX	50.0	0.150	H-W Rect. Doubler	235 Volts RMS Per Plate, 75 Ma. D.C. Output Per Plate. 117 Volts RMS Per Plate, 75 Ma. D.C. Output.											
50Y6GT	T-9	Duodiode	7Q	50.0	0.150	F-W Rect.	Characteristics Same as Type 25Z6GT.											
50Y7GT	T-9	Duodiode	8AN	46.0	0.150	Doubler H-W Rect.	117 A.C. Volts, RMS, 65 Ma. Output with Panel Lamp. 150 A.C. Volts, RMS, 65 Ma. Output Per Plate with Panel Lamp. 235 A.C. Volts, RMS, 65 Ma. Output Per Plate with Panel Lamp.											
60E3	T-5½	Diode	60E3	60	0.150	H-W Rect.	117 Volts, RMS, 110 Ma. D.C. Output. Condenser Input.											
60FX5	T-5½	Pentode	7CV	60	0.100	S.T. A1 Pwr. Amplifier	5.5	110	62 [■]	115	36-35	10-12	17500	13500	3000	1300		
KT66	Curved Bulb	Beam Pent.	7S	6.3	1.270	S.T.A1 Amp. P.P.AB1 Amp.	250 450	15 250 [■]	250 415	85 105-125†	6.3 5-18†	22500	6300	2200 8000†	7250 30000		
75	ST-12	Duodiode Tri.	6G	6.3	0.300	Det. Amp.	250	2.0	0.9	91000	1100	100		
78	ST-12	Pentode	6F	6.3	0.300	R-F Amp.	3.0	90 180 250	3.0 3.0 3.0	90.0 75.0 100	5.4 4.0 7.0	1.3 1.0 1.7	300000 1 Meg.	1275 1100 1450		
80	ST-14	Duodiode	4C	5.0	2.000	F-W Rect.	350 A.C. Volts Per Plate, RMS, 125 Ma. Output Current. Condenser Input to Filter. 500 A.C. Volts Per Plate, RMS, 125 Ma. Output Current. Choke Input to Filter.											
83	ST-16	Duodiode	4C	5.0	3.00	F-W Rect.	450 A.C. Volts Per Plate, RMS, 225 Ma. Output Current. Condenser Input to Filter.											
84/6Z4	ST-12	Duodiode	5D	6.3	0.500	F-W Rect.	325 A.C. Volts Per Plate, RMS, 60 Ma. Output Current. Condenser Input to Filter.											
EL84/6BQ5	T-6½	Beam Pent.	9CV	6.3	0.760	Power Amp.	13.2	Characteristics Same as Type 6BQ5.											
EL86	T-6½	Beam Pent.	9CV	6.3	0.760	A-F Pwr. Amp.	13	Characteristics Same as Type 6CW5.											
EF86/6267	T-6½	Pentode	9CQ	6.3	0.200	A-F Amp.	1.1	250	2.0	140	3.0	0.6	2.5 Meg.	1800		
KT88	ST-16	Beam Pent.	7S	6.3	1.800	P.P.AB1 Amp.	450	65	450	100-240†	(Plate and Grid No. 2 Current.)	3800†	65000			
VR-90-105-150								Now Listed as OB3, OC3 and OD3.											
117L7/M7GT	T-9	Diode Beam Pentode	8AO	117	0.090	H-W Rect. Power Amp.	6.6	117 A.C. Volts, RMS, 75 Ma. Output Current.	105	5.2	105	43	4.0	17000	5300	4000	850
117Z6GT	T-9	Duodiode	7Q	117	0.075	Voltage Dblr.	117 A.C. Volts Per Plate, RMS, 60 Ma. Output Current.											
407A GB-407A (3)	T-6½	Duotriode	407A	40 20	0.050 0.100	Amplifier	1.35	150	240 [■]	8.2	6370	5500		
408A GB-408A (3)	T-5½	Pentode	7BD	20	0.050	Amplifier	1.7	120	200 [■]	120	7.0	2.2	340000	5000		
417A	T-6½	Triode	9V	6.3	0.300	UHF R-F Amp.	4.0	Characteristics Same as Type 5842.											
807 807W (3)	ST-16 T-12	Beam Pent.	5AW	6.3	0.900	P.P.AB1 Amp. P.P.AB2 Amp. P.P.AB2 Amp.	25	400 400 600	45 25 30 300 300	60-140† 90-240† 60-200† 2.15† 0.7-16†	(Current, Output for 2 Tubes) (Current, Output for 2 Tubes) (Current, Output for 2 Tubes)	3000 3200 6400	15000 55000 80000				
884	ST-12	Gas Triode	6Q	6.3	0.600	Relay Tube	300	30	75	For Relay Operation Limit Time to 30 Secs. 300 Ma. Pe Current. 16 Volt Tube Drop.							
FM1000	Lock-in	Heptode	FM 1000	6.3	0.300	F-M Det.											
1216 (3) GB-1216 (3)	T-5½	Duotriode	7BF	6.3	0.300	Computer	0.55	100 150 150	470 [■] 0 10	4.8 4.8 Min. 0.1 Max. Plate Res. = 20K Ohms. Plate Res. = 20K Ohms.	7950 3400	27 Grid Res. = 47K Ohms. Grid Res. = 47K Ohms.			
1217 (3) GB-1217 (3)	T-5½	Heptode	7CH	6.3	0.300	Dual-Control Computer	1.0	67.5 67.5 150	0 4 0	67.5 67.5 75	Grid No. 3 = 0 Volts Grid No. 3 = 0 Volts 5.8	2400 1700 9	Rb=20K, RG ¹ =47K, RG ² =470 Ohms				
1221	ST-12	Pentode	6F	6.3	0.300	Amplifier	.825 Special Non-Microphonic Tube, Characteristics Same as Type 6C6.												



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milliwatts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
1222A	ST-14	Beam Pent.	1222	6.3	0.900	Power Amp.	20.9	Characteristics Similar to Type 6L6GA.									
1223	ST-12	Pentode	7R	6.3	0.300	Amplifier	.825	"G" Equivalent of Type 1221 Above.									
1229	ST-12	Tetrode	4K	2.0	0.060		Special Type 32. Made for Low Grid Current Application.									
1230	T-9	Triode	4D	2.0	0.060		Special Type 30. Made for Low Grid Current Applications.									
1231	Lock-in	Pentode	8V	6.3	0.450	R-F Amp. Tet. Amp.	300	200 [■]	150	10.0	2.5	700000	5500	3850
1232	Now Known as Type 7G7.																
1236A	T-9	Diode	1236A	1.9	0.450	Regulator	Plate Voltage = 330 Volts (Abs. Max.). D.C. Current = 0.8 Ma. (Abs. Max.). Plate Current = 0.63 Ma. Plate Load Resistance = 0.25 Meg.									
1238	Lock-in	Duo. Beam Amplifier	8BS	28.0	0.400	Amplifier	3.3	Characteristics Similar to 28D7.									
1247	T-3	Diode	1247	0.7	0.065	R-F Probe	300 A.C. Volts RMS, 0.4 Ma. D.C. Plate Current.									
1265	ST-12	Diode	4AJ	Voltage Reg.	Starting Voltage = 135, Operating Voltage = 90, Operating Current = 5 to 30 Ma.									
1266	T-9	Diode	4AJ No Jumper	Regulator	Voltage Regulator Similar to Type OB3/VR-90-30, Except Regulating at 70 Volts.									
1267	T-9	Gas Triode	4V	Relay Tube	Similar to Type OA4G.									
1273	Lock-in	Pentode	8V	6.3	0.300	Amplifier	1.1	Characteristics Same as Type 7C7 (Special Non-Microphonic Tube).									
1274	T-9	Duodiode	6S	6.3	0.600	F-W Rect.	Characteristics Same as Type 7Y4.									
1275	ST-16	Duodiode	4C	5.0	1.750	F-W Rect.	Similar to Type 5Z3.									
1276	ST-16	Triode	4D	4.5	1.140	Power Amp.	16.5	Similar to Type 6A3.									
1280	Lock-in	Pentode	8V	12.6	0.150	Amplifier	1.1	Characteristics Same as Type 14C7 (Special Non-Microphonic Tube).									
1284	Lock-in	Pentode	8V	12.6	0.150	R-F Amp.	250	3	100	9.0	2.5	800000	200	
1291	Now Known as Type 3B7.																
1293	Lock-in	Triode	4AA	1.4	0.110	Oscillator	90	0	5.2	1500	15
1294	Now Known as Type 1R4																
1299	Now Known as Type 3D6.																
1612	Metal	Heptode	7T	6.3	0.300	Mixer Amp.	1.65	Characteristics Same as Type 6L7.									
1614	T-10 Sp.	Beam Pent.	7S	6.3	0.900	P.P.AB1 Amp.	21	360	22.5	270	88-132†	15†	6600	26500
								530	36	340	60-160†	20†	7200	50000
1625	ST-16	Beam Pent.	5AZ	12.6	0.450	P.P.AB1 Amp. P.P.AB2 Amp.	25	Characteristics Same as Type 807.									
2050	ST-12	Gas Tetrode	6BS	6.3	0.600	Relay Tube	400	5.0	0	100
2050A								220	4.0	0	75
5636 (3)	T-3	Pentode	8DC	6.3	0.150	Mixer	1.1	100	150 [■]	100	3.6	5.3	320000	1280 ^A
5639 (3)	T-3	Beam Pent.	8DL	6.3	0.450	Power Amp.	4.0	150	100 [■]	100	21	4	50000	9000	1000
5641 (3)	T-3	Diode	6CJ	6.3	0.450	H-W Rect.	117 A.C. Volts Per Plate, RMS, 48 Ma. D.C. Output. Condenser Input to Filter. 235 A.C. Volts Per Plate, RMS, 45 Ma. D.C. Output. Condenser Input to Filter.									
5642	T-3	Diode	5642	1.25	0.200	H-W Rect.	Pulse Type Rectifier for Television Service, 10000 Volts Peak Inverse.									
5643 (3)	T-3	Gas Tetrode	8DD	6.3	0.150	Relay Tube	150	5 A.C.	0	16
5644 (3)	T-3	Gas Diode	4CN	Voltage Reg.	Starting Voltage at 130, Operating Voltage 95, Operating Current 5 to 25 Ma.									
5647 (3)	T-1	Diode	5647	6.3	0.150	Detector	117 Volts, RMS Plate, 9 Ma. D.C. Output.									
5651	T-5½	Gas Diode	5BO	Volt. Ref.	Starting Voltage = 115 Volts Max. Operating Voltage = 92 Volts Max. Operating Current = 3.5 Ma. Max.									
5651WA (3)																	
5654/6AK5W(3)	T-5½	Pentode	7BD	6.3	0.175	VHF Amp.	1.65	120	200 [■]	120	7.5	2.5	340000	5000
5654/6AK5W/6096																	
GB-5654(3)																	

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) †† Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
5670(3) GB-5670(3) 5670WA(3)	T-6½	Duotriode	8CJ	6.3	0.350	VHF Amp.	1.35	150	240 ^m	8.2	6370	5500	35
5686	T-6½	Beam Pent.	9G	6.3	0.350	Power Amp.	8.25	250	12.5	250	27	5.0	3100	9000	2700
5687 (3) GB-5687 (3)	T-6½	Duotriode	9H	6.3 12.6	0.900 0.450	Amplifier	4.2	250 180	12.5 7.0	23 12	3000 2000	5400 8500	16 17
5691	T-9	Duotriode	8BD	6.3	0.600	A-F Amp.	1.0	250	2	2.3	44000	1600	70
5692	T-9	Duotriode	8BD	6.3	0.600	A-F Amp.	1.75	250	9	6.5	9100	2200	20
5693	Metal	Pentode	8N	6.3	0.300	A-F Amp.	2.0	250	3	100	3.0	0.85	1650
5702 5702WA (3) 5702WB (3)	T-3	Pentode	5702	6.3	0.200	VHF Amp.	120	200 ^m	120	7.5	2.5	340000	5000
5703 5703WA (3) 5703WB (3)	T-3	Triode	5703	6.3	0.200	VHF Osc.	3.3	120	220 ^m	9.0	5000	25
5704 (3)	T-2	Diode	5704	6.3	0.150	VHF Det.	3.3	150 Volts, RMS Plate, 9 Ma. D.C. Output Current.									
5718 (3)	T-3	Triode	8DK	6.3	0.150	UHF Amp.	3.3	100 150	150 ^m 180 ^m	8.5 13.0	4650 4150	5800 6500	27 27
5719 (3)	T-3	Triode	8DK	6.3	0.150	UHF Amp.	.55	150	680 ^m	1.85	30500	2300	70
5722 (3)	T-5½	Diode	5CB	4.9 ∇	1.600	Noise Diode	200	For Noise Generator Service 1b 35 Ma. Max.								
5725 (3) GB-5725 (3) 5725/6AS6W(3)	T-5½	Pentode	7CM	6.3	0.175	Mixer	1.65	120	2	120	5.2	3.5	3200
5726/6AL5W(3) GB-5726 (3) 5726/6AL5W/6097(3)	T-5½	Duodiode	6BT	6.3	0.300	Rectifier	117 Volts, RMS Plate, 9 Ma. D.C. Output Current Per Plate.									
5744	T-3	Triode	5744	6.3	0.200	A-F Amp.	250	500 ^m	4	4000	70
5749/6BA6W(3) GB-5749	T-5½	Pentode	7BK	6.3	0.300	R-F Amp.	3.3	100 250	68 ^m 68 ^m	100 100	10.8 11.0	4.4	250000	4300
5750 (3) 5750/6BE6W(3) GB-5750 (3)	T-5½	Heptode	7CH	6.3	0.300	Converter	1.1	Characteristics Same as Type 6BE6.									
5751WA (3) 5751 (3) GB-5751 (3)	T-6½	Duotriode	9A	6.3 12.6	0.350 0.175	A-F Amp.	0.8	Characteristics Same as Type 12AX7.									
5783	T-3	Gas Diode	5783	Voltage Reg.	Starting Voltage at 115 Volts. Operating Voltage 85. Operating Current 1.5 to 3.5 Ma.									
5784	T-3	Pentode	5784	6.3	0.200	Amplifier	1.87	120	2	120	5.2	3.5	3200
5785	T2x3	Diode	5785	1.25 ∇	0.015	H-W Rect.	1235 Volts, RMS Plate, 100 μ a D.C. Output Current.									
5787	T-3	Gas Diode	5783	Voltage Reg.	Starting Voltage at 135 Volts. Operating Voltage 100. Operating Current 5 to 25 Ma.									
5814 (3) GB-5814A (3) 5814WA (3)	T-6½	Duotriode	9A	6.3/ 12.6	0.350/ 0.175	Class A Amplifier	3.0	100 250	0 8.5	11.8 10.5	6250 7700	3100 2200	19.5 17.0
5823	T-5½	Gas Triode	4CK	Relay Tube	Peak Cathode Ma. = 100 Max. D.C. Cathode Ma. = 25 Max. Starter Anode Volt Drop = 61 Volts. Anode Drop = 62 Volts.									
5824 (3)	ST-14	Beam Pent.	7S	25.0	0.300	Power Amp.	13.7	135	22	135	61	2.5	15000	5000	1700	4300
5840 (3)	T-3	Pentode	8DL	6.3	0.150	R-F Amp.	1.1	100	150 ^m	100	7.5	2.4	260000	5000
5842 (3)	T-6½	Triode	9V	6.3	0.300	UHF R-F Amplifier	4.0	150	62 ^m	26	1800	24000	43
5844 (3) GB-5844 (3)	T-5½	Duotriode	7BF	6.3	0.300	Computer	1.0	100	470 ^m	4.8	7550	3700	28
5845	T-5½	Duodiode	5CA	5.0 ∇	0.435	Control Diode	300max.	2.0max.




AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Trans-conductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milliwatts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
5847 (3)	T-6½	Pentode	9X	6.3	0.300	R-F Amp.	3.3	150	110 [■]	150	13	4.5	12500
5851	T-3	Pentode	6CL	1.25 [†] 2.50 [†]	0.110 0.055	R-F Amp.	1.65	125 180	7.5 7.0	125 135	5.5	0.9	175000	1600	650
5871	T-9	Beam Pent.	7S	6.3	0.450	Power Amp.	13.2	Characteristics Same as Type 6V6GT.									
5879	T-6½	Pentode	9AD	6.3	0.150	A-F Amp.	1.37	250 250	3 8	100	1.8	0.4	2000000	1000
													13700	1530	21
5881	T-11	Beam Pent.	7S	6.3	0.900	Power Amp.	25.3	Characteristics Same as Type 6L6G.									
5889	T-3	Pentode	5889	1.25 [†]	7.5 Ma	Amplifier	12	2.0005	.005	1.8 Meg.	(For Low Grid Current Applications.)		
5896 (3)	T-3	Duodiode	8DJ	6.3	0.300	F-W Rect.	150 Volts, RMS Per Plate, 18 Ma. D.C. Output Current.									
5899 (3)	T-3	Pentode	8DL	6.3	0.150	R-F Amp.	1.1	100	120 [■]	100	7.2	2.2	260000	4500
5902 (3)	T-3	Pentode	8DL	6.3	0.450	Power Amp.	4.0	110	270 [■]	110	30	2.2	15000	4200	1000
5903 (3)	T-3	Duodiode	8DJ	26.5	0.075	UHF Det.	PIV = 460 Volts, PKIb = 60 Ma., Ib = 10 Ma. and EHK = 360 Volts.									
5904 (3)	T-3	Triode	8DK	26.5	0.045	UHF Osc./ Amp.	26.5	2.2 Meg ⁴	3.0	4000	5000	20
5905 (3)	T-3	Pentode	8DL	26.5	0.045	UHF Amp.	26.5	2.2 Meg ⁴	26.5	2.1	0.75	150000	2850
5906 (3)	T-3	Pentode	8DL	26.5	0.045	UHF Amp.	1.1	100	150 [■]	100	7.5	2.4	260000	5000
5907 (3)	T-3	Pentode	8DL	26.5	0.045	UHF Amp.	26.5	2.2 Meg ⁴	26.5	2.7	1.1	100000	3000
5908 (3)	T-3	Pentode	8DC	26.5	0.045	UHF Amp.	26.5	2.2 Meg ⁴	26.5	3.3	2.0	31000	2200
5910 (3)	T-5½	Pentode	6AR	1.4 [†]	0.050	R-F Amp.	90	0	90	1.6	0.45	1500000	900
5915 (3)	T-5½	Dual Control Heptode	7CH	6.3	0.300	Computer	1.0	150	0	75	5.8	9.0	Grid No. 3 Voltage = 0 Rb = 20K Ohms				
5915A (3)								150	10.0	75	0	0	Grid No. 3 Voltage = 0				
GB-5915A (3)								150	0	75	0	14.0	Grid No. 3 Voltage = -10				
5916 (3)	T-3	Pentode	8DC	26.5	0.045	Dual-Control Mixer	1.1	100	150 [■]	100	5.3	3.6	110000	3200
5931 (3)	T-12	Duodiode	5T	5.0 [†]	3.000	F-W Rect.	Characteristics Same as Type 5U4G.									
GB-5931 (3)																	
5932 (3)	T-12	Beam Pent.	7S	6.3	0.900	Power Amp.	2.2	Characteristics Same as Type 6L6G.									
GB-5932 (3)																	
5933 (3)	T-12	Beam Pent.	5AW	6.3	0.900	Power Amp.	25	Characteristics Same as Type 807W.									
5933WA (3)																	
GB-5933 (3)																	
5963 (3)	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	Computers	2.5	67.5 150	0 0	8.5 5.4	6600	3200	21
GB-5963 (3)													(Rb = 20000 Ohms)		
5964 (3)	T-5½	Duotriode	7BF	6.3	0.450	Computers	1.5	100 150	50 [■] 0	9.5 5.0	6500	6000	39
GB-5964 (3)													(Rb = 20000 Ohms)		
5965A	T-6½	Duotriode	9A	6.3/ 12.6	0.450/ 0.225	Computer	2.4	150	220 [■]	8.5	7000	6700	47
GB-5965 (3)																	
5968	T-3	Duotriode	8DQ	1.25 [†]	0.120	VHF Mixer	45	0	0.7	1300	50
5969	T-3	Duotetrode	8DR	1.25 [†]	0.200	VHF Amp. or VHF Osc.	0.96	135	3.0	45	6.0	0.6	1700
								Class A Ratings									
5970	T-3	Duo. Pentode	8DS	1.25 [†]	0.160	VHF Amp.	45	5 Meg ⁴	45	3.0	0.9	170000	1850
5977 (3)	T-3	Triode	8DK	6.3	0.150	Amplifier	3.3	100	270 [■]	10.0	3650	4500	16
5987 (3)	T-3	Triode	8DM	6.3	0.450	Amplifier	4.0	100	18	9.0	1850	4.1
5998A	T-12	Duotriode	8BD	6.3	2.400	Passing Tube for V.R. Serv.	15	110	105 [■]	100	350	15500	5.4

(1) See Frontal Section.
 (2) Design Maximum Values.
 † Maximum Signal.


(3) Has Special Mechanical and/or Life Characteristics.
 (4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
 † Filamentary Type. † Conversion Transconductance.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
 † Plate to Plate. † Cathode Resistor (ohms).



SYLVANIA TUBES


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts	
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.													
6000	T-11	Beam Pent.	6CK	26.5	0.280	Class "C" Amp./Osc.	25	400 600	60 60	200 225	125 100	16 18	RG = 12000 Ohms, PK R-F = 75 V, IG1 = 5 Ma, Driving Power = 0.4 Watt, RG = 20K Ohms, PK. R-F = 75 V, IG1 = 3 Ma., Driving Pwr. = 0.23 Watts	58000 52000	3700 4100	5500 5000 10000†	2800 4500 10000
6005 (3) GB-6005 (3) 6005/6AQ5W/6095(3) 6005/6AQ5W (3)	T-5½	Beam Pent.	7BZ	6.3	0.450	S.T. Class A1 S.T. Class A1 P.P. Class AB1	11	180 250 250	8.5 12.5 15	180 250 250	29. 45. 70-79†	3.0 4.5 5-13†
6021 (3)	T-3	Duotriode	8DG	6.3	0.300	UHF Amp.	1.1	100	150 ^m	6.5	6480	5400	35
6028	T-5½	Pentode	7BD	20	0.050	Amplifier	1.87	120	180 ^m	120	7.5	2.5	300000	5000
GB-6080 6080	T-12	Duotriode	8BD	6.3	2.500	Passing Tube for V.R. Service	13	135	250 ^m	200	280	7000	2
6082A	T-12	Duo Power Triode	8BD	26.5	0.600	Power Amp.	13	135	250 ^m	125	280	7000	2
6097	T-5½	Duotriode	6BT	6.3	0.300	F-W Rect.	Characteristics Same as Type 5726/6AL5W.										
6101 (3) GB-6101	T-5½	Duotriode	7BF	6.3	0.450	VHF Osc./Amp.	1.6	Characteristics Same as Type 6J6.										
6110 (3)	T-3	Duotriode	8DJ	6.3	0.150	UHF Det.	Peak Inverse Voltage = 460 Volts. Peak Anode Current = 26.4 Ma. Per Plate.										
6111 (3)	T-3	Duotriode	8DG	6.3	0.300	Med. Mu Amplifier	1.1	100	220 ^m	8.5	4200	4750	20
6112 (3)	T-3	Duotriode	8DG	6.3	0.300	High Mu Amplifier	.55	100 150	1500 ^m 820 ^m	0.8 1.75	38900 28000	1800 2500	70 70
6118 (3)	Metal	Duotriode Tri.	7V	6.3	0.300	Det. Amp.	100 250	1.0 3.0	0.8 1.0	58000 58000	1200 1200	70 70
6135 (3) GB-6135 (3)	T-5½	Triode	6BG	6.3	0.170	VHF Osc./Amp.	3.8	Characteristics Same as Type 6C4.										
6145 GB-6145 (3)	Lock-in	Pentode	8V	6.3	0.600	Computer	11	150	0	100	34	8.0	0.1 Meg.	9700
6146	T-12	Beam Pent.	7CK	6.3	1.250	P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB2 Amp.	20	600 500 600	45 44 44	180 175 165	26-200† 27-242† 22-207†	1-23† 0.7-18† 0.6-17†	(Current, Output for 2 Tubes) (Current, Output for 2 Tubes) (Current, Output for 2 Tubes)	7000† 4600† 6800†	8200 8300 9000
6147	T-3	Power Pent.	6CL	1.25†	0.125	VHF Power Amplifier	1.5	125	7.5	125	5.5	0.9	175000	1600
6186 (3) 6186 (3) 6186/6AG5WA(3) GB-6186 (3)	T-5½	Pentode	7BD	6.3	0.300	VHF Amp.	2.5	250	200 ^m	150	7	2	5000
6187	T-5½	Pentode	6187	6.3	0.175	VHF Amp.	1.6	120	2.0	120	5.2	3.5	3200
6188	T-9	Duotriode	8BD	6.3	0.300	D.C. Amp.	1.1	250	2.0	2.3	44000	1600	70
6189 (3) 6189/12AU7WA(3) GB-6189 (3)	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	Osc./Amp.	3.0	Characteristics Same as Type 12AU7.										
6201 (3) GB-6201 (3)	T-6½	Duotriode	9A	6.3 12.6	0.300 0.150	VHF Amp.	2.5	Characteristics Same as Type 12AT7.										
6205 (3)	T-3	Pentode	8DC	6.3	0.150	UHF Amp.	1.1	100	150 ^m	100	7.5	2.4	0.26 Meg.	5000
6206 (3)	T-3	Pentode	8DC	6.3	0.150	UHF Amp.	1.1	100	120 ^m	100	7.5	2.0	0.26 Meg.	4500
6211A	T-6½	Duotriode	9A	12.6/ 6.3	0.150/ 0.300	Computer	1.3	100	2.0	6.6	6500	4700	31
6308 (3)	T-3	Gas Diode	8EX	Voltage Reg.	Starting Voltage at 115 Volts. Operating Voltage at 87 Volts and Current at 3.5 Ma. Max.										
6336A	TT-16	Duo Power Triode	8BD	6.3	5.000	Passing Tube for V.R. Serv.	30	190 200 ^m	182	300	13500	2.7
							RK = 200 Ohm Per Section, RG = 500 Ohm Per Section.											



AVERAGE CHARACTERISTICS


TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6350 (3) GB-6350 (3)	T-6½	Duotriode	9CZ	6.3 12.6	0.600 0.300	Computer	3.85	150	5.0	11.0	...	3900	4600	18
6352 (3)	T-3	Duodiode	8EY	3.0 [†] Series	0.360 Series	Regulator	Temperature Limited Diode. Max. Ef. = 4.0. Max. Eb. = 275. Max. Ib. = 1.1 Ma.									
6354	T-5½	Diode	7DU	Voltage Reg.	Starting Voltage at 180. Operating Volts 150. Operating Current 5 Ma. Min., 30 Ma. Max.									
6394A	TT-16	Duo Power Triode	8BD	26.5	1.300	Passing Tube for V.R. Serv.	30	Characteristics Same as Type 6336A.									
6463	T-6½	Duotriode	9CZ	6.3 12.6	0.600 0.300	Computer	4.4	200 250	11.0 620 [■]	14.5	...	3850	5200	20
6486A	T-6½	Pentode	9DV	6.3	0.250	Dual Control Pentode	2.0	120	2	120	3.5	3.3	3250
6516	T-5½	Beam Pent.	6CH	6.3	0.200	VHF/AF Power Amp.	5.2	250	13.5	250	16.0	2.25	150000	2550	16000	1400
6520	T-16	Duo Power Triode	8BD	6.3	2.500	Passing Tube for V.R. Serv.	15.4	Characteristics Same as Type 6AS7G.									
6528	ST-16	Duo Power Triode	8BD	6.3	5.000	Passing Tube for V.R. Serv.	30	100	4	185	...	245	37000	9
6550	ST-16	Beam Pent.	7S	6.3	1.600	S.T. A1 Amp. P.P.AB1 Amp.	38.5	400 600	16.5 33	225 300	87.0 100-280†	4.0 3-33†	27000 (Current, Output for 2 Tubes)	9000	3000 5000†	20000 100000
6582A	T-6½	Pentode	9EJ	6.3	0.250	R-F Pent.	2.0	120	180 [■]	120	7.5	2.5	5 Meg.	4500
6611	T-2x3	Pentode	6611	1.25 [†]	0.020	VHF Amp.	0.1	30 45	5 Meg. ⁴ 5 Meg. ⁴	30 45	1.0 1.0	0.35 0.35	400000 400000	1000
6612	T-2x3	Pentode	6612	1.25 [†]	0.080	VHF Amp.	0.2	30 45	2 Meg. ⁴ 2 Meg. ⁴	30 45	3.0 3.0	1.0 1.0	180000 180000	3000
6626	T-5½	Gas Diode	5BO	Voltage Reg.	Starting Voltage = 165. Operating Voltage = 148. Operating Current = 5 to 30 Ma.									
6627	T-5½	Gas Diode	5BO	Voltage Reg.	Starting Voltage = 130. Operating Voltage = 108. Operating Current = 5 to 30 Ma.									
6660/6BA6	T-5½	Pentode	7BK	6.3	0.300	R-F/I-F Amp.	3.3	100 250	68 [■] 68 [■]	100 100	10.8 11	4.4 4.2	250000 1 Meg.	4300 4200
6661/6BH6	T-5½	Pentode	7CM	6.3	0.150	R-F/I-F Amp.	3.3	100 250	200 [■] 95 [■]	100 100	3.6 7.4	1.4 2.9	700000 1.4 Meg.	3400 4600
6662/6BJ6	T-5½	Pentode	7CM	6.3	0.150	R-F/I-F Amp.	3.3	100 250	80 [■] 80 [■]	100 100	9 9.2	3.5 3.3	250000 1.3 Meg.	3650 3600
6663/6AL5	T-5½	Duodiode	6BT	6.3	0.300	Detector	A.C. Voltage Per Plate = 117 Volts. D.C. Output Current = 9.0 Ma.									
6664	T-5½	Triode	5CE	6.3	0.150	VHF Amp./Osc.	2.9	Characteristics Same as Type 6AB4.									
6669/6AQ5	T-5½	Beam Pent.	7BZ	6.3	0.450	A-F Pwr. Amp.	12	250	12.5	250	45	4.5	52000	4100	5000	4500
6676	T-5½	Pentode	7CM	6.3	0.300	VHF Amp.	2.3	Characteristics Same as Type 6CB6.									
6677/6CL6	T-6½	Beam Pent.	9BV	6.3	0.650	R-F Osc./Amp.	8.5	250	3.0	150	30	7	150000	11000	7500	2800
6678/6U8	T-6½	Tri. Pentode	9AE	6.3	0.450	VHF Osc./Amp.	3.0	150 250	56 [■] 68 [■] 110	18 10	...	5000 400000	8500 5200	40
6679/12AT7	T-6½	Duotriode	9A	6.3/ 12.6	0.300/ 0.150	VHF Osc./Amp.	2.8	100 250	270 [■] 270 [■]	3.7 10	...	15000 10900	4000 5500	60 60
6680/12AU7	T-6½	Duotriode	9A	6.3/ 12.6	0.300/ 0.150	Gen. Purpose	3.0	100 250	0 8.5	11.8 10.5	...	6500 7700	3100 2200	20 17
6681/12AX7	T-6½	Duotriode	9A	6.3/ 12.6	0.300/ 0.150	A-F Amp.	1.1	100 250	1.0 2.0	0.5 1.2	...	80000 62500	1250 1600	100 100
6690 (3)	T-3	Duotriode	8GQ	6.3	0.300	Video Amp.	1.1	100	100 [■]	8.0	4800	35

(1) See Frontal Section. (2) Design Maximum Values. † Maximum Signal. (3) Has Special Mechanical and/or Life Characteristics. (4) Average Contact Potential Bias Developed Across Specified Grid Resistor. * Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.) ‡ Filamentary Type. † Plate to Plate. ■ Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
6788 (3)	T-3	Pentode	8DL	6.3	0.175	Audio Amp.	0.5	100	1500 [■]	100	0.7	0.1	1.2 Meg.	1100
GB-6814 (3)	T-3	Triode	8DK	6.3	0.150	Computer	2.2	100	0	10	4800	6000	29
6832	T-3	Duotriode	8DG	6.3	0.400	D.C. Amp.	0.1	100	3000 [■]	0.8	1050
6840	T-6½	Duotriode	9CZ	12.6 6.3	0.400 0.800	Computer	4.0	250	620 [■]	14	3400	7100	20
6851	T-6½	Duotriode	9A	6.3	0.250	Amplifier	1.0	250	3100 [■]	1.0	60000	1200	70
6854	T-6½	Duotriode	9FV	6.3	0.500	Amplifier	1.65	150	240 [■]	8.2	6500	5225	35
6870	T-6½	Beam Pent.	9BF	6.3 12.6	0.600 0.300	VHF Power Amplifier	6.9	250	120 [■]	250	25.0	3.5	230	8500
6872	T-3	Pentode	6872	6.3	0.200	VHF Amp.	1.1	120	200 [■]	120	7.75	2.7	340000	4100
6877	T-6½	Power Triode	9GB	6.3	0.800	Power Amp.	150	12	75	2000	6500	3.75	12000
6883 (3)	T-12	Beam Pent.	7CK	12.6	0.625	Power Amp.	20	Characteristics Same as Type 6146.									
6893 (3)	T-9	Beam Pent.	7CK	12.6	0.400	Power Amp.	10	Characteristics Same as Type 2E26.									
6900	T-6½	Duotriode	9H	6.3	1.000	Pulse Amp.	4.25	120	2	36	1700	11500	18.5
6919	T-5½	Duodiode	6BT	6.3	0.200	F-W Rect. Computer	Maximum Inverse Peak Plate Voltage = 300 Volts. Maximum Peak Plate Current = 30 Ma. Maximum D.C. Output Current = 10 Ma. (Design Max. Values.)									
6922	T-6½	Duotriode	9AJ	6.3	0.300	VHF Amp.	1.65	90	120 [■]	12	2800	11500	33
6939	T-6½	Duotetrode	9HL	6.3 12.6	0.600 0.300	P.P.A1 Amp. P.P.A1 Amp.	3.0 200	150 200	3.5 3.5	150 150	27-31.6 28-31.6	3.6-12.2 6-15.4	7000 7500	10560 17400	1750 2660
6943 (3)	T-3	Pentode	8DC	6.3	0.175	R-F Amp.	1.0	100	150 [■]	100	8	2.3	300000	3600
6944 (3)	T-3	Pentode	8DC	6.3	0.175	R-F Amp.	1.0	100	150 [■]	100	7	2.1	280000	3200
6945 (3)	T-3	Beam Pent.	8DL	6.3	0.350	Power Amp.	3.0	100	270 [■]	100	25	1.5	20000	3500	3000	800
6946 (3)	T-3	Triode	8DK	6.3	0.175	Amplifier	1.5	100	270 [■]	9.0	3800	16.5
6947 (3)	T-3	Duotriode	8DG	6.3	0.350	Amplifier	0.75	150	270 [■]	6.5	4000	35
6948 (3)	T-3	Duotriode	8DG	6.3	0.350	Amplifier	0.50	100	1500 [■]	0.8	1650	70
6954	T-5½	Pentode	7CM	6.3	0.300	Dual-Control Computer	3.3	150	1.0	150	5.8	6.6	50000	2050	Grid No. 3 = -3.0 Volts.		
6955	T-6½	Duotriode	9A	6.3 12.6	0.350 0.175	Amplifier	3.0	100 250	0 8.5	13.0 11.5	5800 7000	3500 2350	21.3 16.5
6968	T-5½	Pentode	7BD	6.3	0.175	VHF Amp.	1.81	Characteristics Same as Type 6AK5.									
6973	T-6½	Beam Pent.	9EU	6.3*	0.450	S.T. A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	13.2	250 300 350	15 230 [■] 22	250 300 280	46 80-96† 58-106†	3.5 6-14† 3.5-14†	73000	4800	5500 7500	15000† 20000†
7001	T-5½	Beam Tetrode	7EJ	6.3	0.450	Power Amp.	5.5	120	250 [■]	120	35	4	4800
7025 7025A	T-6½	Duotriode	9A	12.6 6.3	0.150 0.300	Audio Amp.	1.1	Characteristics Same as Type 12AX7, except Controlled for Noise and Hum.									
7027 7027A	T-12	Beam Pent.	8HY	6.3	0.900	P.P.AB1 Amp.	27.5	330 400 450 400 380 410	24 25 30 200 [■] 180 [■] 220 [■]	330 300 350 300 380 410	122-184† 102-152† 95-194† 112-128† 138-170† 134-155†	5.6-18.5† 6-17† 3.4-19.2† 7-16† 5.6-20† (Cathode Current) Ultra-Linear Circuit.	4500† 6600† 6000† 6600† 4500† 8000†	31500 34000 50000 32000 36000 24000	
7032	T-5½	Heptode	7CH	6.3	0.300	Computer	1.1	150 150 150 150	G1+3=0 G1+3=0 6.0 0	75 75 75 75	3.5 3.5 <0.1 <0.1	6.0 G3+1=470K 6.0 G3+1=470K <0.3 G3+1=470K 8.8 G3+1=470K	1400 650	G1 = Control Grid G3 = Control Grid G3 = 0 Volts G3 = -6 Volts	
7036	T-5½	Heptode	7CH	6.3	0.300	Dual Control Computer	0.9	Characteristics Same as Type 5915A.									




AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milliwatts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
7044 GB-7044 (3)	T-6½	Duotriode	9H	6.3 12.6	0.900 0.450	Computer	4.5	120	2.0	36	...	1750	12000	21
7054	T-6½	Power Pent.	9BF	13.5	0.275	S.T.A1 Amp. Class "C" Amplifier	5.0	250 300	120 [¶] 12	150 175	19 26	3.5 5.5	100000	11500	4000
7055	T-5½	Duodiode	6BT	13.5	0.155	Detector	117 A.C. Volts Per Plate, RMS, 9 Ma. Output Current.	300 Ohms Min.
7056	T-5½	Pentode	7CM	13.5	0.150	VHF Amp.	2.0	200	180 [¶]	150	9.5	2.8	600000	6200
7057	T-6½	Duotriode	9AJ	13.5	0.180	VHF Amp.	2.2	150	220 [¶]	10	5300	6800	36
7058	T-6½	Duotriode	9A	13.5	0.155	A-F Amp.	1.0	250	2	1.25	...	61000	1650	100
7059	T-6½	Tri. Pentode	9AE	13.5	0.195	VHF Osc. VHF Amp.	2.5 2.8	150 250	56 [¶] 68 [¶] 110	18 10 3.5	4700 400000	8500 5200	40
7060	T-6½	Tri. Pentode	9DX	13.5	0.280	VHF Osc. VHF Amp.	2.5 3.0	150 200	150 [¶] 82 [¶] 125	9 15 3.4	8200 150000	4900 7000	40
7061	T-6½	Beam Pent.	9EU	13.5	0.210	S.T.A1 Amp.	9.0	200	10	200	35.5	9	60000	4200	5000	3000
7077	Ceramic and Metal	Triode	7077	6.3	0.240	UHF R-F Amplifier	1.0	250	82 [¶]	6.4	8900	9000	80
7105	T-12	Duo Power Triode	8BD	12.6	1.250	Passing Tube for V.R. Serv.	13.2	Characteristics Same as Type 6080WA.									
7119	T-6½	Duotriode	9H	6.3 12.6	0.640 0.320	Computer	4.5	120 150	2.0 14	36 0.2	15000	24
7137 GB-7137 (3)	T-5½	Triode	7BQ	6.3	0.225	VHF Amp.	2.25	150	100 [¶]	13.5	8500	40
7150	Spec. Base T-9	Tetrode	9JH	6.3	0.450	VHF Amp.	4.0	135	G1 = +8V RK = 260 Ohms	135	27.5	8.5	30000	35800
7167	T-5½	Tetrode	7EW	13.5	0.090	VHF Amp.	2.0	250	1.0	80	10	1.4	125000	8000
7189	T-6½	Beam Pent.	9CV	6.3	0.760	S.T.A1 Amp. P.P.AB1 Amp. P.P.AB2 Amp.	13.2	250 400 375	7.3 16 220 [¶]	250 300 375	48 15-105† 75-81†	5.5 1.6-25† (Cathode Current)	40000	11300	19.5	(G1 to G2)	24000 16500
7199	T-6½	Tri. Pentode	9JT	6.3	0.450	A-F Tri. Amp. A-F Pent. Amplifier	2.4 3.0	215 100 220	8.5 1000 [¶] 62 [¶] 50 130	9 1.1 12.5	0.35 1 Meg. 3.5	8100 1500 7000	2100 1500	17
7212	T-12	Beam Pent.	8EC	6.3	1.250	P.P.AB1 Amp. P.P.AB2 Amp.	20	600 500 600	45 40 44	180 185 165	26-200† 15-215† 22-207†	1-23† 2-25† 0.6-17†	7000 5500 6800	82000 70000 90000
7227	T-6½	Pentode	9BA	27.5	0.175	Power Amp.	2.2	27.5	2.5	27.5	11	1.1	8000	5500	4	70
7233	T-6½	Triode	9FR	6.3	1.250	Passing Tube for V.R. Serv.	7.5	50	22 [¶]	120	230	17500	4
7236	T-12	Duotriode	8BD	6.3	2.400	Passing Tube for V.R. Serv.	15	120	14	100	12500	4.8
7239	T-6½	Beam Pent.	9KH	6.3	0.300	Pulse Amp. and Shunt Reg.	4.0	300 100	5.0	100 100	10.5 43	2.6 13.5	300000	4200
7241	TT-18	Triode	7241	6.3	7.500	Passing Tube for V.R. Serv.	100	190 200 [¶] RG = 500 Ohms	550	67	40000	2.7
7242	TT-18	Triode	7241	6.3	7.500	Passing Tube for V.R. Serv.	100	100 4 RG = 500 Ohms	555	82	111000	9.0
7244 7244A	T-5½	Duotriode	7BF	6.3	0.450	Amplifier	1.1	100	50 [¶]	9.0	6300	6000	38
7245	T-5½	Triode	7BQ	6.3	0.400	VHF Amp.	2.25	150	100 [¶]	13.5	4500	11000	50

(1) See Frontal Section.
(2) Design Maximum Values.
† Maximum Signal.


(3) Has Special Mechanical and/or Life Characteristics.
(4) Average Contact Potential Bias Developed Across Specified Grid Resistor.
‡ Filamentary Type.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)
¶ Plate to Plate.
■ Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
7246	T-2x3	Triode	7246	1.25 \uparrow	0.150	VHF Amp./Osc./Det.	0.7	105	2.5	4.5	2700	22
7258	T-6 $\frac{1}{2}$	Tri. Pentode	9DA	13.5	0.210	Gen. Amp. VHF Amp.	2.8 2.3	150 125	3 56 \blacksquare	125 12	15	3.8	170000	4500 7800	21
7316	T-6 $\frac{1}{2}$	Duotriode	9A	6.3 12.6	0.300 0.150	Computer	2.7	250 100	8.5 0	10.5 11.8	7700 6250	2200 3100	17 19.5
7318	T-6 $\frac{1}{2}$	Duotriode	9A	6.3 12.6	0.350 0.175	Pulse Amp.	1.35	100 250	0 8.5	13 11.5	5800 7000	3500 2350	21.3 16.5
7320	T-6 $\frac{1}{2}$	Beam Pent.	9CV	6.3	0.760	Power Amp.	12	Characteristics Same as Type 6BQ5.									
7327 (3)	T-3	Duotriode	8DG	6.3	0.300	Pulse Amp. Blocking Osc.	0.95	150	25	Pulse Applied to Grid = 40 Volts at $t_p = 10 \mu\text{sec.}$, $p_{rr} = 1000 \text{ Pps.}$, $t_r = 0.2 \mu\text{sec. Max.}$, $t_f = 0.2 \mu\text{sec. Max.}$, PEAK Plate Current = 400 Ma. Min.							
7355	T-9	Beam Pent.	8KN	6.3	0.800	S.T.A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	18	250 300 400	15 21 34	225 250 300	62-74 \uparrow 100-185 \uparrow 56-175 \uparrow	3.2-16.5 \uparrow 5.5-24 \uparrow 3.5-24 \uparrow	42000	7600	2500 4000 \uparrow 5000 \uparrow	9000 28500 40000
7358	T-12	Pentode	8EC	6.3	1.250	Pulse Mod.	10	200 3000 175	200 300	100 15 4	7000	4.2 (G2 to G1)	IC1 = 2.5 Ma., RL = 100 Watts. 1500 Ohm-Non Ind. Res.	
7360	T-6 $\frac{1}{2}$	Beam Defl. Tube	9KS	6.3	0.350	Balanced Mod. Dble. Sideband Balanced Mixer Single Sideband	1.5 1.5	150 25 Volts = Defl. Electrode Voltage, PK to PK R-F Grid No. 1 Volts = 10 Volts, Push-Pull Double Sideband Output Voltage = 4 Volts.	1200 \blacksquare 1200 \blacksquare	175 175	1.5 1.5	0.75 0.75	5000 \uparrow 10000 \uparrow
7370	T-6 $\frac{1}{2}$	Duotriode	9H	20/ 40	0.260/ 0.130	Computer	4.75	120 250	2.0 12.5	36 12	1560 3000	11500 5400	18 16
7382	T-5 $\frac{1}{2}$	Triode	7382	6.3	0.300	A-F Amp.	0.55	Characteristics Same as Type 12AX7, except Controlled for Noise and Hum.									
7408	T-9	Beam Pent.	7S	6.3	0.450	A-F Pwr. Amp.	14	Characteristics Same as Type 6V6GT.									
7430	Special	Pentode	7430	6.3	0.200	R-F Amp.	1.87	120 180	2.0 2.0	120 120	7.5 7.7	2.5 2.4	300000 500000	5000 5100
7489	T-6 $\frac{1}{2}$	Duotriode	9A	6.3/ 12.6	0.300/ 0.150	A-F Amp.	3.0	250	8.5	10.5	7700	2200	17
7490	T-6 $\frac{1}{2}$	Duotriode	9A	6.3/ 12.6	0.600/ 0.300	A-F/D.C. Amp.	5.0	250	4.6	6.0	2350	32
7492	T-6 $\frac{1}{2}$	Duotriode	9DA	6.3/ 12.6	0.300/ 0.150	R-F Amp. and Computer	2.8	250	200 \blacksquare	10	5500	60
7494	T-6 $\frac{1}{2}$	Duotriode	9A	12.6/ 6.3	0.150/ 0.300	A-F Amp.	1.1	250	2	1.25	59000	1600	95
7495	T-6 $\frac{1}{2}$	Beam Tetrode	9K	6.0	0.750	VHF Power Amplifier	12	250	7.5	250	45	7 Max.	7000	G1 to G2 = 16.
7496	T-5 $\frac{1}{2}$	Pentode	7BK	6.3	0.300	R-F Amp.	3.3	250	68 \blacksquare	100	11	4.2	1 Meg.	4400
7498	T-5 $\frac{1}{2}$	Pentode	7DB	6.3	0.300	R-F Amp.	3.0	250	160 \blacksquare	250	9.85	2.6	7620	75
7499	T-6 $\frac{1}{2}$	Pentode	9BA	6.3	0.750	Video Amp.	12	250	4.5	250	40	6.0	11000	26
7500	T-6 $\frac{1}{2}$	Beam Tetrode	9AH	6.3	0.450	A-F Power Amplifier	13	250	12.5	250	45	5.5	50000	4100
7502	T-5 $\frac{1}{2}$	Heptode	7CH	6.3	0.300	Converter	1.1	250	1.5	100	3.0	7.5	1.0 Meg.	7250
7543	T-5 $\frac{1}{2}$	Pentode	7BK	6.3	0.300	A-F Amp.	3.3	Characteristics Same as Type 6AU6. Type 7543 has a Folded Coil Heater for Low Noise Operation.									
GB-7550 7550 (3)	T-3	Duotriode	8DG	6.3	0.525	Pulse Amp.	2.0	300	30	1400	8000	10000
7561	T-9	Beam Pent.	7561	25	0.300	S.T.A1 Amp. S.T.A1 Amp. S.T.AB1 Amp.	13	115 250 250	8.0 15 18	115 150 150	55 48-51 \uparrow 50-110 \uparrow	2.5 1-7 \uparrow .8-14 \uparrow	5000 3000	6000 17000



AVERAGE CHARACTERISTICS

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transconductance Micros.	Amplification Factor	Ohms Load for Stated Power Output	Power Output Milli-watts		
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.														
7576	T-3	Triode	7576	6.3	0.450	VHF Amp.	4.1	200	0	15.5	10700	46		
Designed to be Used as a Grounded Grid Amplifier.																			
7581	T-12	Pentode	7S	6.3	0.900	P.P.AB1 Amp.	35	360	22.5	270	88-132†	5-15†	6600‡	26.5		
								360	22.5	270	88-140†	5-11†	3800‡	18		
								450	37	400	116-210†	5.6-22†	5600‡	55		
7581A	T-12	Beam Pent.	7S	6.3*	0.900	S.T.A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	35	250	14	250	72	5	22500	6000	2500	6500		
								360	22.5	270	88-132†	5-15†	6600‡	26500		
								450	37	400	116-210†	5.6-22†	5600‡	55000		
7586	M-N	Triode	12AQ	6.3*	0.140	VHF Amp.	1.0	75	130■	10.5	2900	11500	33		
7587	M-N	Tetrode	12AS	6.3	0.150	VHF Amp.	2.2	125	68■	50	10	2.7	200000	10600		
7591	T-9	Beam Pent.	8KG	6.3	0.800	S.T.A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	19	300	10	300	55-65†	7-16†	29000	10200	4000	11000		
								300	12.5	300	86-116†	12-26†	6600‡	23000		
								350	15.5	350	92-130†	13-29†	6600‡	30000		
								400	16	350	85-143†	11-27†	6600‡	37000		
								450	16.5	350	77-153†	10-27†	6600‡	43000		
								450	21	400	66-144†	9.4-30†	6600‡	45000		
								450	200■	400	82-94†	11.5-22†	9000‡	28000		
								400	20.5	80-138†	11.5-22†	6600‡	32000		
								425	185■	88-104†	13-17.5†	6600‡	26000		
Ultra-Linear Conn. 40% Ultra-Linear Conn. 40%																			
7631	T-5½	Duodiode	6BT	6.3	0.300	Detector	Max. Peak Inverse Plate Voltage = 360 Volts. Max. Peak Plate Current = 10 Ma.									
7643	T-6½	Tri. Pent.	9AE	6.3	0.330	VHF Amp./Osc.	1.7	100	120■	14	5000	18		
							2.1	170	155■	170	10	2.8	400000	6200	40		
7687	T-6½	Tri. Pentode	9AE	6.3	0.500	A-F Amp.	2.4	215	8.5	7.5	7200	2500	18		
							3.0	220	62■	130	10	3.4	500000	5800		
7688	Special Base T-7½	Triple Triode	12BA	6.3	0.450	A-F Amp.	3.0	Characteristics Same as Type 12AU7.									
7689	Special Base T-7½	Triple Triode	12BA	6.3	0.450	A-F Amp.	1.1	Characteristics Same as Type 12AX7.									
7690	Special Base T-7½	Triple Triode	12BA	6.3	0.450	A-F Amp.	2.8	Characteristics Same as Type 12AT7.									
7693	T-5½	Pentode	7EN	6.3	0.150	R-F Amp.	2.6	250	100■	150	7.4	2.9	1.3 Meg.	4600	G1 to G2=48		
7694	T-5½	Pentode	7EN	6.3	0.150	R-F Amp.	3.3	250	80■	100	9.2	3.3	1.0 Meg.	3800	G1 to G3=25		
7695	9-T9	Pentode	9PX	50	0.150	S.T.A1 Amp. P.P.AB1 Amp.	16	130	11	130	100	5-14†	7000	11000	1100	4500		
								140	50■	140	210-220†	9-20†	1500‡	10000		
7701	T-6½	Beam Pent.	9MS	13.6	0.160	VHF Class C Amplifier	9.0	250	12.5	250	28	3.1	31000	3600		
7716	T-6½	Tri. Pentode	9DX	13.6	0.350	High Mu High GM	1.0	125	1.0	1.5	35000	2900	102		
							5.0	200	68■	125	24	5.2	70000	10000		
7717	T-5½	Tetrode	7EW	6.3	0.200	VHF Amp.	2.0	125	1.0	80	10	1.4	125000	8000		
7719	T-6½	Triode	9MX	12.6/ 6.3	0.225/ 0.450	Computer	6.0	300	10.5	4	7100	3500	25		
7720	Ceramic and Metal	Triode	7720	6.3	0.240	VHF Amp.	1.0	150	82■	7.5	10500	90		
7721	T-6½	Pentode	9EQ	6.3	0.320	VHF Amp.	4.0	190	400■	160	22	6.0	120000	35000		
7722	T-6½	Pentode	9EQ	6.3	0.320	VHF Amp.	4.0	190	370■	160	20	6.0	100000	26000		
G1 = +8 Volts.																			
7724	T-6½	Duodiode Tri.	9KR	14	0.150	A-F Amp.	250	3.0	0.7	72000	1000	72		

(1) See Frontal Section.

(2) Design Maximum Values.

† Maximum Signal.

(3) Has Special Mechanical and/or Life Characteristics.

(4) Average Contact Potential Bias Developed Across Specified Grid Resistor.


◆ Filamentary Type.

▲ Conversion Transconductance.

* Controlled Heater Warm-up Time (applies to parallel connections of types having a tapped heater.)


‡ Plate to Plate.

■ Cathode Resistor (ohms).



SYLVANIA TUBES

TYPE	CONSTRUCTION			EMITTER		USE	Plate Diss. Watts ²	Plate Volts	Negative Grid Volts	Screen Volts	Plate Current Ma.	Screen Current Ma.	Plate Resis. Ohms	Transcon-ductance Micros.	Amplifi-cation Factor	Ohms Load for Stated Power Output	Power Output Milli-watts
	Bulb Size or Style ¹	Class	Basing Diag.	Volts	Amps.												
7728	T-6½	Duotriode	9A	6.3/12.6	0.300/0.150	VHF Amp.	2.8	Characteristics Same as Type 12AT7.									
7729	T-6½	Duotriode	9A	6.3/12.6	0.300/0.150	A-F Amp.	1.1	Characteristics Same as Type 12AX7.									
7730	T-6½	Duotriode	9A	6.3/12.6	0.300/0.150	Gen. Purpose	3.0	Characteristics Same as Type 12AU7.									
7731	T-6½	Tri. Pent.	9AE	6.3	0.450	VHF Osc. VHF Amp.	3.0 3.0	Characteristics Same as Type 6U8.									
7732	T-5½	Pentode	7CM	6.3	0.300	VHF Amp.	2.3	Characteristics Same as Type 6CB6.									
7733	T-6½	Pentode	9BF	6.3/12.6	0.600/0.300	Video Amp.	6.5	Characteristics Same as Type 12BY7A.									
7734	T-6½	Tri. Pentode	9LC	6.3	0.900	V.R. Voltage Control Tube	7.0 1.0	150 150	21 2.0	150 150	35 5.5	1.7 1.7	1080 340000	5000 3200	5.4
7738	T-5½	Triode	7DK	6.3	0.225	VHF Class C Amplifier	5.0	200	100 ^m	12	9500	80
7751	T-9	Beam Pent.	7S	6.3	1.200	Pulse Amp.	10	100	8.2	100	100	7	5000	14000	G1 to G2 = 5.6	
7754	9-T9	Beam Pent.	9PX	6.3	1.200	A-F Power Amplifier	16	Characteristics Same as Type 7695.									
7759	T-3	Duotriode	8DG	26.5	0.090	VHF Amp./Osc.	1.1	100	150 ^m	6.5	5400	35
7760	T-3	Duotriode	8DG	26.5	0.090	VHF Amp./Osc.	26.5	2.2 Meg ⁴	3	5000	20
7761	T-3	Pentode	8DL	26.5	0.110	Video Amp.	4.0	150	100 ^m	100	21	4	50000	9000
7762	T-3	Beam Pent.	8DL	26.5	0.110	S.T. A1 Amp.	4.0	110	270 ^m	110	30	2.2	15000	4200	3000	1000
7768	Ceramic and Metal	Triode	7768	6.3	0.400	VHF Amp.	5.5	200	270 ^m	24	4500	50000	225
7803	T-6½	Duotriode	9AJ	6.3	0.365	VHF Osc. Doubler	3.5	90 160	1.3 70	15 26	12500	33	Rg1 = 33K Ohms (Class "C" Doubler to 175 Mc) 1000 Ig1 = 2.5 Ma. PK R-F Grid Volts = 77	
7841	Ceramic and Metal	Diode	7841	6.3	0.215	Detector	Max. Peak Inverse Plate Voltage = 350 Volts. Max. D.C. Output Current = 5.0 Ma.									
7861	T-6½	Duotriode	8CJ	12.6	0.175	Gen. Purpose	1.3	150	240 ^m	8.2	6400	5500	35
7867	T-12	Beam Pent.	5BT	6.3	2.500	S.T. A1 Amp. P.P.AB1 Amp. P.P.AB1 Amp.	24	250 250 250	120 ^m 200 ^m 35	90 150 150	80 114-128† 58-210†	1.0 2-17† 1.4-26†	12000	10000	3000 6000† 5000†	7500 28000 65000



RESISTANCE COUPLED AMPLIFIER DATA

TYPE	TABLE
5AV8	B,C
5B8	B,C
6AB4	A
6AN8, 6AN8A, 5AN8	B,C
6AQ6	D
6AS8, 5AS8	C
6AT6, 12AT6	D
6AU6, 6AU6A, 3AU6, 4AU6, 12AU6	E
6AV6, 3AV6, 12AV6, 4AV6	G
6AV11	L
6AX8	H,I
6B10	L
6BE8, 5BE8	H,I
6BF6, 12BF6	J
6BJ8	K
6BR8, 6BR8A, 5BR8	H,I
6BT8, 5BT8	C
6BY8	E
6C4	L
6C10	G
6CG7, 8CG7	K
6CH8	B,C
6CN7, 8CN7	D
6CR6	X
6CU8	B,C
6DR4	G
6EU7	G
6F5, 6F5GT, 12F5GT	F
6FM8	Y
6FQ7, 8FQ7	K
6J5, 6J5GT, 12J5, 12J5GT	K
6J7, 6J7GT, 12J7GT, 12J7	M
6K11	L,G
6Q7, 6Q7GT, 12Q7GT	D
6Q11	L,G
6R7	J
6SC7, 12SC7	N
6SF5, 6SF5GT, 12SF5, 12SF5GT	F
6SH7, 12SH7	E
6SJ7, 6SJ7GT, 12SJ7, 12SJ7GT	O
6SL7GT, 12SL7GT	N
6SN7GTB, 8SN7GTB, 12SN7GTA	K
6SQ7, 6SQ7GT, 12SQ7, 12SQ7GT	P
6SR7, 12SR7	J
6ST7	J
6T8A, 5T8, 19T8	D
6U8, 6U8A, 5U8, 9U8A	H,I
7A4, 14A4	K
7B4	F
7B6, 14B6	P
7C7, 14C7	M
7E6, 14E6	J
7F7, 14F7	N
7K7	N
7N7, 14N7	K
12AT7	A
12AU7, 12AU7A, 9AU7, 7AU7	L
12AV7	Q
12AX7, 6AX7	G
12AY7	R
12AZ7A	A
12DM7	G
12DT7	L
12DT8	A
12DW7	G,L

TYPE	TABLE
13D2	K
18FY6	G
19HV8	D
20EZ7	G
1273	M
1280	M
1620	M
5687	W
5691	N
5692	K
5693	O
5751	G
5879	V
6072	R
6113	N
6118	D
6135	L
6136	E
6180	K
6201	A
6267	U
6320	N
6321	K
6678	H,I
6679	A
6680	L
6681	G
7025, 7025A	G
7058	G
7059	H,I
7199	S,T
7258	B,C
7316	L
7382	G
7543	E
7687	S,T
7688	L
7689	G
7690	A
7728	A
7729	G
7730	L
7731	H,I
7889	D
B36	K
B65	K
B152	A
B309	A
B329	L
B339	G
DH77	D
EABC80	D
EBC90	D
EBC91	G
EC90	L
EC92	A
ECC81	A
ECC82	L
ECC83	G
ECF82	H,I
EF86	U
EF94	E
H63	F
HBC90	D
HBC91	G
HF94	E
L63	K
L77	L
PCF82	H,I
Z63	M

SYMBOLS USED

SYMBOL	FUNCTION	UNIT
Rb	Plate Load Resistor	Megohms
Rc2	Screen Dropping Resistor	Megohms
Rcf	Grid Resistor of Following Tube	Megohms
Ebb	Plate Supply Voltage	Volts
Eb	Plate Voltage at Plate	Volts
Ec or Ec1	Negative Grid Voltage	Volts
Ec2	Screen Grid Voltage	Volts
Esig	Input Signal	RMS Volts
Eout	Output to Following Grid	RMS Volts
Ib	Plate Current	Ma.
Ic2	Screen Grid Current	Ma.
Cc	Coupling Condenser	mfd.
Cc2	Screen By-pass Condenser	mfd.

Values of capacity are not specified since these are dependent mostly on the frequency characteristic required in each individual case.

$$\text{For low frequency limit} = f_1 \quad Cc = \frac{1.6 \times 10^6}{f_1 R_{cf}} \text{ mfd.}$$

$$Ck = \frac{1.6 \times 10^6}{f_1 R_k} \text{ mfd.} \quad Cc2 = \frac{1.6 \times 10^6}{f_1 R_{c2}} \text{ mfd.}$$

Some text books show a more complicated method for calculating these by-pass condensers, but this method is quite rapid and gives conservative values. The loss due to incomplete by-passing will be less than 1% except for the cathode by-pass where it will be about 3%. The size condenser may be halved where economy is essential unless stages are cascaded and highest quality is required.

Table A

	Ebb = 100 Volts						Ebb = 250 Volts							
	0.1		0.27		0.47		0.1		0.27		0.47			
Rb														
Rcf	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	0.27	0.47	1.0	1.0	
Rk	1500	1800	3900	3900	4700	5600	6800	680	680	1800	1800	2200	3300	3900
Ib	0.54	0.51	0.23	0.23	0.22	0.150	0.141	1.62	1.62	0.89	0.69	0.65	0.41	0.40
Ec1	-0.81	-0.92	-0.90	-0.90	-1.04	-0.840	-0.960	-1.10	-1.10	-1.24	-1.24	-1.43	-1.35	-1.56
Eb	45.2	48.1	37.1	37.1	39.6	28.7	32.7	86.9	86.9	62.3	62.3	75.6	55.7	59.9
Esig	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Eout	3.0	3.0	2.8	3.0	3.1	2.95	3.0	3.90	4.10	3.55	3.70	3.65	3.50	3.60
Gain	30.0	30.0	28.0	30.0	31.0	29.5	30.0	39.0	41.0	35.5	37.0	36.5	35.0	36.0
% Dist.	1.9	1.7	1.9	1.7	1.4	1.8	1.4	.54	1.0	1.0	.92	.79	.89	.75
Esig(1)	0.54	0.29	0.30	0.29	0.38	0.22	0.34	0.61	0.49	0.54	0.56	0.71	0.64	0.77
Eout	6.6	8.7	8.4	8.4	11.5	6.5	10.0	23.0	19.7	19.0	20.6	25.5	22.1	27.0
Gain	30.0	30.0	28.0	28.9	30.3	29.5	29.4	37.0	40.2	35.2	36.8	35.9	34.5	35.1
% Dist.	3.9	4.7	5.0	4.5	4.9	3.6	4.1	4.4	4.2	4.7	4.2	4.6	4.8	4.6

Table B

	Ebb = 100 Volts						Ebb = 250 Volts					
	.047		0.1		0.27		.047		0.1		0.27	
Rb												
Rcf	.1	.27	.1	.47	.27	.47	.1	.27	.1	.47	.27	.47
Rk	1200	1200	2200	3300	6800	8200	560	660	1000	1200	3900	3900
Ib	1.33	1.33	0.70	0.64	.275	.260	3.84	3.84	1.98	1.95	0.76	0.76
Ec1	-1.6	-1.6	-1.5	-2.1	-1.9	-2.1	-2.2	-2.2	-2.0	-2.3	-3.0	-3.0
Eb	36	36	29	34	24	28	66	66	50	53	42	42
Esig	.1	.1	.1	.1	.1	.1	.1	.1	.1	.1	.1	.1
Eout	1.25	1.27	1.13	1.22	1.10	1.12	1.45	1.50	1.37	1.44	1.25	1.28
Gain	12.5	12.7	11.3	12.2	11.0	11.2	14.5	15.0	13.7	14.4	12.5	12.8
% Dist.	0.9	0.9	0.9	0.7	0.6	0.6	0.7	0.7	0.7	0.7	0.5	0.5
Esig(1)	0.60	0.63	.60	.98	.88	1.07	1.17	1.17	1.02	1.28	1.65	1.65
Eout	7.4	8.0	6.8	11.5	9.7	12.0	17.0	17.5	14.0	18.5	20.7	21.1
Gain	12.3	12.7	11.3	11.7	11.0	11.2	14.5	15.0	13.7	14.4	12.5	12.8
% Dist.	4.7	4.5	4.6	4.9	4.7	4.3	5.2	5.0	5.0	4.6	4.8	4.2

Note (1) For Self Bias Operation This is Taken at the Grid Current Point With Less Than 1/2 μa. Grid Current.

RESISTANCE COUPLED AMPLIFIER DATA

Table C Pentode Section

Rb	Ebb = 100 Volts						Ebb = 250 Volts					
	0.1		0.27		0.47		0.1		0.27		0.47	
Rc ₂	.33		1.0		1.8		.33		1.0		1.8	
R _{cf}	.27	.47	.27	.47	1.0	1.0	.27	.47	.27	.47	1.0	1.0
R _k	1000	1000	2700	2700	4700	4700	390	330	1000	1000	1000	1800
I _b	.66	.66	.256	.256	.256	.151	.151	1.88	1.95	.73	.73	.44
I _{c₂}	.205	.205	.076	.076	.076	.043	.043	.60	.61	.23	.23	.23
E _{c₁}	-.86	-.86	-.89	-.89	-.89	-.91	-.91	-.97	-.85	-.96	-.96	-1.0
E _{c₂}	33.8	33.8	24.0	24.0	24.0	22.5	22.5	52.0	45.0	20.0	20.0	27.0
E _b	34.0	34.0	31.0	31.0	31.0	29.0	29.0	62.0	55.0	53.0	53.0	43.0
E _{aig}	.05	.05	.05	.05	.05	.05	.05	.1	.1	.1	.1	.1
E _{out}	6.0	6.8	5.9	7.0	8.4	6.4	8.2	22.0	24.0	23.0	27.6	28.6
Gain	120	136	118	140	168	128	164	220	240	230	276	266
% Dist.	1.5	1.3	2.6	2.0	1.30	2.1	1.8	1.5	1.8	2.8	2.4	3.0
E _{aig} (1)	.1	.09	.08	.1	.1	.08	.09	.22	.13	.15	.16	.14
E _{out}	11.6	12.0	9.2	13.8	16.6	10.4	15.2	45.6	31.0	34.0	43.0	34.6
Gain	116	133	115	138	166	130	160	208	238	226	268	247
% Dist.	3.4	2.6	4.5	4.7	3.9	4.7	4.7	4.1	3.1	5.0	4.5	5.0

Table D

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
R _{cf}	0.27	0.47	0.27	0.47	1.0	1.0	0.27	0.47	0.27	0.47	1.0	1.0
R _k	3300	3300	5600	5600	6800	8200	10,000	1800	2200	3300	3900	4700
I _b	.288	.288	.161	.161	.146	.108	.099	.95	.88	.476	.46	.425
E _c	-.95	-.95	-.9	-.9	-.99	-.89	-.99	-1.71	-1.94	-1.57	-1.79	-2.0
E _b	71.2	71.2	56.5	56.5	60.6	49.2	53.5	155	162	121.5	125.8	104.4
E _{aig}	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
E _{out}	3.53	3.82	4.1	4.53	4.73	4.63	4.9	4.23	4.4	4.9	5.2	5.4
Gain	35.3	38.2	41	45.3	47.3	46.3	49	42.3	44	49	52	54
% Dist.	.55	0.9	1.6	1.2	1.1	1.5	1.2	.7	.3	.25	.3	.2
E _{aig} (1)	.23	.24	.19	.2	.25	.19	.25	.39	.89	.63	.77	.91
E _{out}	8	8.9	7.75	8.93	11.8	8.7	12.2	33.3	38.5	30.8	39.6	49
Gain	34.8	37.1	40.8	44.6	47.2	45.8	48.8	42.2	43.3	48.9	51.4	53.9
% Dist.	3.6	3.4	3.95	3.4	4.15	3.9	4.6	3.67	4.28	3.4	4.3	4.75

Table E

Rb	Ebb = 100 Volts						Ebb = 250 Volts					
	.1		.27		.47		.1		.27		.47	
R _{c₂}	.27		.68		1.2		.27		.68		1.2	
R _{cf}	.27	.47	.27	.47	1.0	1.0	.27	.47	.27	.47	1.0	1.0
R _k	1200	1200	2700	2700	4700	4700	470	470	1000	1000	1200	1500
I _b	.57	.57	.246	.246	.246	.143	.143	1.74	1.74	.74	.74	.44
I _{c₂}	.24	.24	.106	.106	.106	.063	.063	.68	.68	.30	.30	.29
E _{c₁}	-1.0	-1.0	-1.0	-1.0	-1.0	-1.0	-1.1	-1.1	-1.1	-1.0	-1.2	-0.9
E _{c₂}	41	41	28	28	28	25	25	66	66	46	46	52
E _b	46	46	34	34	34	33	33	76	76	50	50	55
E _{aig}	.05	.05	.05	.05	.05	.05	.05	0.1	0.1	0.1	0.1	0.1
E _{out}	5.8	6.0	5.6	6.9	8.3	6.4	8.5	19.0	20.0	20.5	25.0	29.8
Gain	116	120	112	138	166	128	170	190	200	205	298	251
% Dist.	3.6	3.7	3.9	3.3	2.4	4.7	3.5	2.7	2.5	3.4	1.1	0.8
E _{aig} (1)	.07	.07	.06	.09	.11	.05	.07	.32	.32	.26	.22	.29
E _{out}	8.0	8.3	6.6	12.0	16.5	6.4	11.5	54.0	56.0	37.0	47.7	67.0
Gain	114	119	110	133	150	128	164	169	185	185	217	231
% Dist.	5.1	4.9	4.7	4.9	3.5	4.7	4.7	4.9	3.3	5.1	2.6	3.3

Table F

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
R _{cf}	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	0.27	0.47	
R _k	3900	3900	5600	5600	6800	8200	10,000	1500	800	2700	2700	
I _b	0.22	0.22	0.144	0.144	0.13	0.10	0.091	0.84	0.76	0.443	0.443	
E _c	-0.86	-0.86	-0.81	-0.81	-0.88	-0.82	-0.91	-1.26	-1.37	-1.19	-1.19	
E _b	78	78	61.1	61.1	64.9	53	57.2	166	174	131	131	
E _{aig}	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	
E _{out}	4.25	4.3	4.8	5.35	5.62	5.4	6.4	5.65	5.8	6.5	7.15	
Gain	42.5	43.0	48.0	53.5	56.2	54.0	64.0	56.5	58.0	65.0	71.5	
% Dist.	4.1	4.1	4.3	3.7	3.2	4.1	3.6	0.9	0.9	1.0	1.0	
E _{aig} (1)	0.12	0.12	0.1	0.1	0.13	0.1	0.15	0.47	0.54	0.39	0.39	
E _{out}	5.1	5.15	4.8	5.35	7.25	5.4	9.0	26.5	30.5	24.5	27.5	
Gain	42.5	43.0	48	53.5	55.8	54.0	60.0	56.4	56.5	63.0	70.5	
% Dist.	5.1	5.0	4.3	3.7	4.6	4.1	5.0	4.5	5.3	5.1	4.2	

Note (1) For Self Bias Operation This is Taken at the Grid Current Point With Less than 1/2 μa. Grid Current.

Table G

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
R _{cf}	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	0.27	0.47	
R _k	4700	5600	8200	10,000	10,000	12,000	15,000	1800	1800	3300	3300	
I _b	.23	.204	.132	.117	.117	.092	.08	.84	.84	.45	.45	
E _c	-1.08	-1.143	-1.03	-1.17	-1.17	-1.10	-1.2	-1.51	-1.51	-1.49	-1.49	
E _b	77.0	79.6	64.4	68.4	68.4	56.8	62.4	166	166	128	128	
E _{aig}	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	
E _{out}	3.6	3.8	4.2	4.35	5.0	4.7	5.2	5.4	5.7	6.1	6.6	
Gain	36.0	38.0	42.0	43.5	50.0	47.0	52.0	54.0	57.0	61.0	66.0	
% Dist.	3.4	3.4	3.6	3.2	2.6	3.2	2.6	3.0	3.0	2.2	2.2	
E _{aig} (1)	.14	.14	.11	.14	.17	.13	.17	.5	.5	.41	.45	
E _{out}	5.0	5.2	4.6	6.0	8.3	6.1	8.5	26.5	28.5	24.5	29.0	
Gain	35.7	37.2	41.8	42.9	48.8	46.9	50.0	53.0	52.0	59.8	64.4	
% Dist.	5.0	5.1	4.1	4.9	5.1	4.4	5.0	5.0	4.4	4.95	4.4	

Table H Triode Section

Rb	Ebb = 100 Volts						Ebb = 250 Volts					
	.047		0.1		0.27		.047		0.1		0.27	
R _{cf}	0.1	0.27	0.1	0.47	0.27	0.47	0.1	0.27	0.1	0.47	0.27	0.47
R _k	1000	1200	1800	2700	4700	5600	470	470	820	1200	2700	3300
I _b	1.2	1.1	0.64	0.56	0.26	0.25	3.5	3.5	1.56	1.73	0.72	0.68
E _c	-1.2	-1.3	-1.2	-1.5	-1.2	-1.4	-1.6	-1.6	-1.5	-2.1	-1.9	-2.2
E _b	43	47	35	43	29	32	84	84	63	75	54	64
E _{aig}	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
E _{out}	2.0	2.10	1.98	2.05	1.96	2.00	2.45	2.63	2.38	2.45	2.25	2.25
Gain	20.0	21.0	19.8	20.5	19.6	20.0	24.5	26.3	23.8	24.5	22.5	22.5
% Dist.	1.4	1.2	1.5	1.0	1.2	1.0	0.8	0.8	0.9	0.7	0.7	0.6
E _{aig} (1)	.37	.49	.35	.62	.40	.53	.78	.78	.66	1.04	1.02	1.25
E _{out}	7.4	10.0	6.9	12.5	7.7	10.5	19.1	20.3	15.7	25.5	22.5	28.0
Gain	20.0	20.4	19.7	20.1	19.2	19.8	24.5	26.1	23.8	24.5	22.1	22.4
% Dist.	4.6	5.1	4.5	5.1	4.2	4.1	4.8	4.4	4.5	4.7	4.9	4.7

Table I Pentode Section

Rb	Ebb = 100 Volts						Ebb = 250 Volts					
	0.1		0.27		0.47		0.1		0.27		0.47	
R _{c₂}	.27		.68		1.2		.33		.82		1.2	
R _{cf}	.27	.47	.27	.47	1.0	.47	1.0	.27	.47	.27	.47	
R _k	1000	1000	2200	2200	2700	3300	3900	390	470	820	1000	
I _b	.65	.65	.28	.28	.27	.17	.16	1.75	1.70	.74	.73	
I _{c₂}	.26	.26	.12	.12	.11	.07	.07	.62	.61	.270	.265	
E _{c₁}	-0.9	-0.9	-0.9	-0.9	-1.0	-0.8	-0.9	-0.9	-1.0	-0.8	-1.0	
E _{c₂}	30	30	18	18	25	16	16	46	49	29	33	
E _b	35	35	24	24	27	20	25	75	80	53	55	
E _{aig}	.1	.1	.1	.1	.1	.1	.1	.1	.1	.1	.1	
E _{out}	7.9	9.0	8.2	9.8								

RESISTANCE COUPLED AMPLIFIER DATA

Table K

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.047		0.10		0.27		0.047		0.10		0.27	
	0.1	0.27	0.1	0.47	0.27	0.47	0.1	0.27	0.1	0.47	0.27	0.47
Rcf	1800	2200	3300	1700	8200	10000	1500	2200	2700	3900	6800	8200
Rk	1.05	0.97	0.57	0.50	0.24	0.22	2.79	2.4	1.49	1.31	0.61	0.58
Ib	-1.89	-2.13	-1.90	-2.35	-1.93	2.19	-4.18	-5.28	-4.03	-5.11	-4.15	4.74
Ec	50.6	54.4	43.0	50.0	36.5	40.9	119	137	101	119	85	94
Eb	0.5	0.5	0.5	0.5	0.5	0.5	1.0	1.0	1.0	1.0	1.0	1.0
Esig	6.6	7.1	6.8	7.4	7.3	7.4	14.8	15.0	15.2	16.2	15.9	16.2
Eout	13.2	14.2	13.6	14.8	14.6	14.8	14.8	15.0	15.2	16.2	15.9	16.2
Gain	1.9	1.8	2.4	2.0	2.0	1.7	1.4	1.4	1.8	1.3	1.6	1.3
% Distortion	0.95	1.13	0.95	1.3	0.95	1.20	2.70	3.50	2.55	3.40	2.64	3.05
Esig (1)	12.5	15.5	12.9	19.2	13.7	17.7	39.9	52.5	38.4	53.0	42.0	49.4
Eout	13.1	13.9	13.6	14.7	14.4	14.7	14.7	15.0	15.0	16.1	15.9	16.2
Gain	3.9	4.2	4.9	4.7	4.4	4.5	4.1	4.9	4.9	4.6	4.7	4.5
% Distortion												

Table L

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.047		0.1		0.27		0.047		0.1		0.27	
	0.1	0.27	0.1	0.47	0.27	0.47	0.1	0.27	0.1	0.47	0.27	0.47
Rcf	1200	1200	2200	2700	6800	8200	1000	1000	1500	1800	4700	6800
Rk	1.22	1.22	.66	.628	.259	.246	3.2	3.2	2.67	3.10	3.21	4.28
Ib	1.465	1.465	1.45	1.695	1.76	2.02	3.2	3.2	2.67	3.10	3.21	4.28
Ec	42.7	42.7	34	37.2	30	33.6	150.5	150.5	72	78	65	80
Eb	0.5	0.5	0.5	0.5	0.5	0.5	1.0	1.0	1.0	1.0	1.0	1.0
Esig	6.25	6.6	6.35	6.75	6.3	6.3	13.5	14.1	13.8	14.3	13.4	13.2
Eout	12.5	13.2	12.7	13.5	12.6	12.6	13.5	14.1	13.8	14.3	13.4	13.2
Gain	4.0	3.6	4.3	2.9	3.0	2.5	3.3	3.1	3.8	2.8	2.5	2.0
% Distortion	0.65	0.65	0.57	0.77	0.71	0.98	1.70	1.70	1.34	1.70	1.80	2.52
Esig (1)	8.1	8.6	7.2	10.4	8.9	12.4	23.0	24.0	18.5	24.5	24.1	33.1
Eout	12.5	13.2	12.6	13.5	12.5	12.6	13.5	14.1	13.8	14.3	13.4	13.1
Gain	4.8	4.4	4.8	4.6	4.6	5.0	4.9	4.6	5.0	5.0	4.9	5.0
% Distortion												

Table M

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	1.0	0.47	1.0
Rcf	1000	1000	2200	2700	2200	3900	3900	470	470	1000	1000	1500
Rk	0.62	0.62	0.27	0.27	0.27	0.168	0.168	1.76	1.76	0.75	0.75	0.75
Ib	0.145	0.145	0.064	0.064	0.064	0.465	0.465	0.41	0.41	0.177	0.177	0.177
Ec	-0.765	-0.765	-0.735	-0.735	-0.735	-0.622	-0.622	-1.02	-1.02	-0.927	-0.927	-0.81
Ec1	31.9	31.9	23.3	23.3	23.3	16.3	16.3	57.2	57.2	37.5	37.5	37.5
Eb	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Esig	7.0	8.05	8.0	10.0	12.0	9.8	12.5	10.6	12.0	13.0	17.0	20.4
Eout	70.0	80.5	80	100	120	98	125	106	120	130	170	204
Gain	2.7	2.4	3.7	2.7	2.3	3.2	1.9	1.6	1.4	1.5	1.6	2.0
% Distortion	0.18	0.18	0.14	0.14	0.14	0.14	0.14	0.4	0.4	0.27	0.27	0.27
Esig (1)	12.3	13.9	10.8	13.8	16.7	13.2	17.0	40.3	45.2	33.0	41.6	49.5
Eout	68.5	77.2	77.2	98.7	119	94.5	121.5	101	113	122	154	183.5
Gain	4.7	4.1	5.5	4.6	3.8	4.9	5.0	4.3	4.4	5.0	5.9	4.3
% Distortion												

Table N

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	1.0	0.47	1.0
Rcf	1200	1200	2700	2700	4700	4700	1500	500	500	1200	1200	1800
Rk	0.645	0.645	0.259	0.259	0.165	0.165	1.77	1.77	0.675	0.675	0.402	0.402
Ib	0.18	0.18	0.068	0.068	0.068	0.045	0.045	0.50	0.50	0.183	0.183	0.183
Ec	0.99	0.99	0.882	0.882	0.882	0.99	0.99	-1.27	-1.27	-1.03	-1.03	-1.03
Ec1	29.8	29.8	18.5	18.5	18.5	19.0	19.0	55	55	30.5	30.5	25.5
Eb	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Esig	6.85	7.8	8.2	10.2	12.5	10.2	13.1	10.2	11.5	13.6	17.9	21.6
Eout	68.5	78.0	82	102	125	102	131	102	115	136	179	216
Gain	0.6	0.7	3.4	2.6	2.3	3.2	1.7	0.7	0.8	2.2	1.8	1.5
% Distortion	0.2	0.2	0.14	0.14	0.13	0.13	0.13	0.5	0.5	0.25	0.25	0.25
Esig (1)	13.15	14.9	11.1	13.9	17.2	12.8	16.6	47	54	33	41.8	50
Eout	65.8	74.5	79.4	99.5	123	98.5	128	94	108	132	167.5	200
Gain	3.0	2.9	5.1	4.3	3.7	4.6	5.0	4.2	5.0	5.2	4.4	4.7
% Distortion												

Table O

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.10		0.27		0.47		0.10		0.27		0.47	
	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	1.0	0.47	1.0
Rcf	3300	3300	5600	5600	6800	8200	1800	2200	3300	3900	3900	4700
Rk	0.30	0.30	0.169	0.169	0.152	0.112	0.917	0.83	0.475	0.44	0.44	0.312
Ib	-0.99	-0.99	-0.948	-0.948	-1.03	-0.844	-0.92	-1.65	-1.83	-1.57	-1.72	-1.47
Ec	70	70	54.3	54.3	59.9	41.7	47.3	158.3	167	122	131	103
Eb	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Esig	3.2	3.23	3.7	4.15	4.5	4.28	4.65	4.0	4.1	4.5	5.0	5.25
Eout	32.0	32.3	37.0	41.5	45.0	42.8	46.5	40.0	41.0	45.0	50.0	52.5
Gain	1.3	1.3	1.8	1.5	1.4	1.8	1.4	0.6	0.5	0.6	0.5	0.4
% Dist.	0.33	0.33	0.21	0.21	0.34	0.2	0.3	0.87	1.03	0.83	0.97	0.97
Esig (1)	10.3	10.4	7.7	8.6	14.8	8.5	13.5	33.6	41.5	36.3	46.6	48.8
Eout	31.2	31.5	36.6	41.0	43.5	42.5	45.0	38.6	40.2	43.7	48.0	50.4
Gain	4.9	4.8	4.0	3.1	5.0	3.4	4.4	4.0	4.8	4.5	4.8	3.8
% Dist.												

Table P

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	0.1		0.27		0.47		0.1		0.27		0.47	
	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	1.0	0.47	1.0
Rcf	3900	3900	5600	6800	8200	10000	1800	1800	2700	3300	3900	4700
Rk	0.214	0.214	0.138	0.126	0.126	0.095	0.086	0.725	0.725	0.43	0.395	0.365
Ib	0.835	-0.835	0.774	-0.857	-0.857	-0.78	-0.86	-1.31	-1.31	-1.16	-1.30	-1.42
Ec	78.6	78.6	62.8	66.0	66.0	55.3	59.6	177.5	177.5	134	143.5	151.5
Eb	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Esig	3.3	3.5	4.1	4.5	5.0	4.9	5.2	4.37	4.78	5.50	5.92	6.13
Eout	33.0	35.0	41.0	45.0	50.0	49.0	52.0	43.7	47.8	55.0	59.2	61.3
Gain	2.7	2.6	3.2	3.0	2.5	3.1	2.6	0.8	0.7	0.8	0.8	0.7
% Dist.	0.16	0.16	0.10	0.17	0.17	0.12	0.19	0.55	0.55	0.40	0.53	0.61
Esig (1)	5.15	5.5	4.1	7.3	8.2	5.75	9.7	23.9	26.0	21.8	31.2	37.0
Eout	32.2	34.4	41.0	43.0	48.1	48.0	51.0	43.5	47.4	54.5	59.0	62.4
Gain	4.5	4.0	3.2	5.0	4.5	4.0	5.0	4.5	4.0	3.3	4.0	3.3
% Dist.												

Table Q

RESISTANCE COUPLED AMPLIFIER DATA

Table S Triode Section

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS					
	.047		0.10		0.27		.047		0.10		0.27	
Rcf	0.1	0.27	0.1	0.47	0.27	0.47	0.1	0.27	0.1	0.47	0.27	0.47
Rk	1500	1500	2700	3300	8200	8200	560	680	1200	1500	3300	3900
Ib	1.24	1.24	0.69	0.64	0.26	0.26	3.79	3.69	1.95	1.86	0.74	0.73
Ecl	-1.86	-1.86	-1.86	-2.11	-2.13	-2.22	-2.12	-2.51	-2.34	-2.79	-2.44	-2.85
Eb	39.8	39.8	29.1	33.9	27.7	24.9	69.9	74.0	52.7	61.2	47.6	50.2
Esig	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5
Eout	5.4	5.7	5.2	5.4	4.8	5.0	6.8	6.8	6.2	6.4	5.7	5.7
Gain	10.8	11.4	10.4	10.8	9.6	10.0	13.6	13.6	12.4	12.7	11.4	11.4
% Dist.	3.6	3.2	3.7	2.4	2.8	2.4	2.2	1.8	2.1	1.6	1.7	1.4
Esig(1)	0.73	0.71	0.67	0.87	0.7	0.9	1.03	1.33	1.14	1.52	1.27	1.56
Eout	7.8	8.1	6.9	9.5	8.6	9.0	14.2	18.3	14.4	19.5	14.5	17.7
Gain	10.7	11.4	10.3	10.9	9.6	10.0	13.8	13.8	12.6	12.8	11.4	11.3
% Dist.	3.0	4.6	4.7	4.7	5.0	4.4	4.8	5.0	5.0	5.0	4.6	4.7

Table T Pentode Section

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS							
	0.1		0.27		0.47		0.1		0.27		0.47			
Rc2	0.33		0.82		1.5		0.33		1.0		1.8			
Rcf	0.27	0.47	0.27	0.47	1.0	0.47	1.0	0.27	0.47	0.27	0.47	1.0	0.47	1.0
Rk	1500	1500	3300	3300	3300	5600	5600	470	470	1200	1200	1200	2200	2200
Ib	.612	.612	.273	.273	.273	.159	.159	1.84	1.84	.69	.69	.69	.404	.404
Ic2	.209	.209	.095	.095	.095	.054	.054	.610	.610	.21	.21	.21	.123	.123
Ecl	-1.23	-1.23	-1.21	-1.21	-1.21	-1.19	-1.19	-1.15	-1.15	-1.08	-1.08	-1.08	-1.16	-1.16
Ec2	29.8	29.8	20.9	20.9	20.9	17.8	17.8	50.9	50.9	38.9	38.9	38.9	27.5	27.5
Eb	37.6	37.6	25.1	25.1	25.1	24.1	24.1	64.9	64.9	62.4	62.4	62.4	58.8	58.8
Esig	.05	.05	.05	.05	.05	.05	.05	.05	.05	.05	.05	.05	.05	.05
Eout	5.0	5.8	5.2	6.3	7.2	5.85	7.1	10.0	11.0	10.2	12.5	14.4	11.8	14.2
Gain	100	116	104	126	144	107	142	200	220	204	250	288	236	284
% Dist.	2.8	2.6	2.0	1.5	1.5	2.9	2.7	2.2	1.7	2.3	2.2	2.2	2.3	2.1
Esig(1)	.09	.11	.09	.09	.09	.07	.07	.14	.19	.09	.08	.09	.11	.15
Eout	9.1	12.2	9.1	11.5	13.2	8.15	10.2	26.5	39.5	17.8	19.5	25.4	25.0	41.0
Gain	101	111	101	128	147	107	146	189	208	198	244	282	227	273
% Dist.	4.6	4.9	5.0	5.0	4.6	5.0	5.0	4.5	4.1	3.4	3.4	5.0	4.9	4.9

Table U

Rb	Ebb = 100 VOLTS						Ebb = 250 VOLTS							
	0.1		0.27		0.47		0.1		0.27		0.47			
Rc2	0.56		1.5		2.7		0.56		1.5		2.7			
Rcf	0.27	0.47	0.27	0.47	1.0	0.27	0.47	0.27	0.47	0.27	0.47	1.0	0.47	1.0
Rk	1500	1800	3300	3300	3300	5600	5600	820	820	1200	1500	1500	1800	2200
Ib	0.51	0.48	0.23	0.23	0.23	0.13	0.13	1.47	1.47	0.68	0.65	0.65	0.41	0.39
Ic2	0.10	0.10	0.05	0.05	0.05	0.03	0.03	0.29	0.29	0.13	0.13	0.13	0.08	0.07
Ecl	-0.92	-1.10	-0.91	-0.91	-0.91	-0.91	-0.91	-1.44	-1.44	-0.97	-1.17	-1.17	-0.88	-1.10
Ec2	43	43	24	24	24	18	18	87	87	54	54	54	33	60
Eb	48	51	37	37	37	38	38	102	102	66	74	74	56	66
Esig	0.05	0.05	0.05	0.05	0.05	0.05	0.05	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Eout	4.15	4.45	4.95	6.0	7.15	5.9	7.45	11.2	12.5	15.7	18.6	22.0	21.8	25.3
Gain	83.0	89.0	99.0	120	143	118	149	112	125	157	186	220	218	253
% Dist.	1.2	1.5	3.1	2.8	2.1	4.0	3.0	0.6	0.5	0.8	0.6	0.8	1.9	1.3
Esig(1)	0.12	0.16	0.08	0.09	0.1	0.06	0.08	0.51	0.49	0.21	0.29	0.28	0.13	0.19
Eout	9.65	13.5	7.6	10.5	13.5	6.95	11.6	51.0	54.5	32.0	48.0	54.5	26.2	45.0
Gain	80.3	84.4	95.0	116	135	116	145	100	111	152	165	194	201	237
% Dist.	3.4	5.0	5.0	4.6	4.2	4.7	5.0	4.2	3.1	2.7	5.0	3.3	2.9	4.5

Note (1) For Self Bias Operation This is Taken at the Grid Current Point With Less than 1/4 μA. Grid Current.

Table V

Rb	Ebb = 180 VOLTS						Ebb = 300 VOLTS							
	0.1		0.22		0.47		0.1		0.22		0.47			
Rc2	0.33		0.82		1.8		0.33		0.82		1.2			
Rcf	0.22	0.47	0.22	0.47	1.0	0.47	1.0	0.22	0.47	0.22	0.47	1.0	0.47	1.0
Rk	680	680	1200	1200	1200	2500	2500	330	330	580	580	580	1200	1200
Esig	.5	.5	.37	.36	.33	.27	.26	.45	.42	.34	.34	.33	.28	.27
Eout	28	33	24	31	34	27	32	32	35	28	37	41	35	42
Gain	56	65	65	87	101	98	122	68	83	81	109	123	125	152

Table W

Rb	Ebb = 300 VOLTS						Ebb = 400 VOLTS							
	.022		.047		.10		.022		.047		.10			
Rcf	0.1	0.27	0.1	0.27	0.1	0.27	0.47	0.1	0.27	0.1	0.27	0.1	0.27	0.47
Rk	820	820	1500	1800	2700	3900	4700	820	820	1500	1800	2700	3900	4700
Ib	7.22	7.22	3.8	3.54	1.94	1.74	1.63	9.75	9.75	5.09	4.8	2.64	2.34	2.2
Ecl	-5.92	-5.92	-5.7	-6.38	-5.24	-6.88	-7.66	-8.0	-8.0	-7.64	-8.64	-7.13	-9.3	10.34
Eb	135.3	135.3	115.7	127.0	100.8	119.1	129.3	177.5	177.5	155.9	165.7	128.9	156.9	169.7
Esig	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
Eout	13.5	13.8	13.4	13.6	13.0	13.0	13.0	13.5	13.8	13.5	13.7	13.3	13.4	13.3
Gain	13.5	13.8	13.4	13.6	13.0	13.0	13.0	13.5	13.8	13.5	13.7	13.3	13.4	13.3
% Dist.	1.1	0.9	1.1	0.8	1.2	0.8	0.8	0.8	0.8	0.8	0.7	0.9	0.7	0.7
Esig(1)	4.19	4.19	4.03	4.51	3.7	4.86	5.42	5.66	5.66	5.4	6.12	5.04	6.44	7.31
Eout	56.5	58.0	54.0	61.5	48.0	63.0	69.8	76.2	78.2	73.0	83.8	66.5	85.5	97.5
Gain	13.5	13.8	13.4	13.6	13.0	13.0	12.9	13.5	13.8	13.5	13.7	13.2	13.3	13.3
% Dist.	4.8	4.4	4.6	4.4	4.8	4.6	4.8	4.9	4.4	4.8	4.5	5.0	4.7	5.0

Table X

Rb	Ebb = 90 VOLTS			Ebb = 180 VOLTS			Ebb = 300 VOLTS		
	0.1	0.27	0.47	0.1	0.27	0.47	0.1	0.27	0.47
Rc2	0.47	1.5	2.7	0.39	1.2	3.3	0.47	1.5	3.3
Rcf	0.27	0.47	1.0	0.27	0.47	1.0	0.27	0.47	1.0
Rk	1200	2200	4700	1200	1200	2700	390	1000	1000
Esig	.33	.23	.22	.61	.32	.27	.51	.43	.40
Eout	15	15	17	27	28	30	40	45	52
Gain	45	65	77	44	87	110	78	105	134
% Distortion	5	5	5	5	5	5	5	5	5

Table Y

Rb	Ebb = 180 VOLTS						Ebb = 300 VOLTS					
	0.10		0.24		0.51		0.1		0.24		0.51	
Rcf	0.10	0.24	0.24	0.51	0.51	1.0	0.10	0.24	0.24	0.51	0.51	1.0
Rk	2400	2700	4300	4700	7500	8200	1800	2000	3000	3300	5600	6200
Esig	.62	.70	.60	.70	.60	.70	1.0	1.1	1.0	1.0	1.0	1.1
Eout	18	23	24	31	28	35	35	42	43	52	50	60
Gain	29	34	40	45	47	50	33	38	44	49	51	55
% Dist.	5	5	5	5	5	5	5	5	5	5	5	5

TUBE TYPE BASING ARRANGEMENTS

BASE	TYPE	BASE	TYPE	BASE	TYPE	BASE	TYPE		
OA5	OA5	6AM	6AL6, 6BQ6GTA, GTB, 6BW5, 6CU6, 6DJ6, 6DQ6A, B, 6GW6, 12BQ6GTA, GTB, 12CU6, 12DQ6A, B, 12GW6, 17BQ6GTB, 17DQ6, A, B, 17GW6, 25BQ6GA, GT, GTB, 25DQ6A	7C	6A7, 6669	8AO	117L7/M7GT		
1AG4	1AG4	6AR	1AE4, 1AF4, 1L4, 1T4, 1U4, 5910	7CH	3BE6, 3BY6, 3CS6, 4BE6, 4CS6, 6BE6, 6BY6, 6CS6, 12AB6, 12AD6, 12AG6, 12BE6, 12CS6, 12EG6, 12FA6, 18FX6, 1217, 5750/6BE6W, 5750, 5915, A, 7032, 7036, 7502	8B	6N7, GT		
1AG5	1AG5	6AU	1AF5, 1S5	7CK	2E26, 6146, 6883, 6888, 6893	8BD	2C50, 2C52, 6AS7, G, GYB, 6BL7GT, GTA, 6BX7GT, 6DN7, 6EA7, 6SL7-GT, WGT, 6SN7GTB, WGTA, 6W4GTA, 10EG7, 10EM7, 12SL7-GT, 12SN7GTA, 13EM7, 15EA7, 5691, 5692, 5998A, 6080, 6082A, 6188, 6336A, 6394A, 6520, 6528, 7105, 7236		
1AJ5	1AJ5	6AX	1LD5	7CM	3BZ6, 3CB6, 3CF6, 3DK6, 4BZ6, 4CB6, 4DE6, 4DK6, 4EW6, 4GM6, 5EW6, 5GM6, 6AS6, 6BH6, 6BJ6, 6BZ6, 6CB6A, 6CF6, 6DB6, 6DC6, 6DE6, 6DK6, 6EW6, 6GM6, 12AW6, 12BZ6, 15EW6, 5725, 5725/6AS6W, 6661, 6662, 6676, 6954, 7056, 7732, 8136	8BF	7K7		
1AK4	1AK4	6B	41, 42, 43	7CV	4GZ5, 6AS5, 6CA5, 6CU5, 6EH5, 11C5, 12AS5, 12C5, 12CA5, 12CN5, 12CU5, 12DM5, 12ED5, 12EH5, 12R5, 17C5, 17CA5, 17R5, 25C5, 25CA5, 25EH5, 32ET5, A, 34GD5, A, 35C5, 35EH5, 40FR5, 50C5, 50CA5, 50EH5, 50FA5, 50FK5, 60FX5	8BJ	7W7		
1AK5	1AK5	6BA	3D6	7DB	6AM6, 7498	8BK	6SG7, GT, 6SH7, 12SG7, 12SH7		
1V6	1V6	6BG	6C4, 6135	7DC	1L6, 1U6	8BL	7J7, 7S7		
3C	1AU3, 1B3GT, 1G3, 1J3, 1J3A, 1K3, 1N2A	6BS	2050	7DF	3BN6, 4BN6, 6BN6, 12BN6	8BS	28D7, W, 1238		
4AA	1LE3, 1293	6BT	3AL5, 6AL5, 6EB5, 12AL5, 5726, 5726/6AL5W/6097, 6097, 6663, 6919 7055, 7631	7DK	2AF4, A, B, 2T4, 3AF4A, B, 6AF4, A, 6AN4, 6T4, 7738	8BW	7F8, W, 14F8		
4AB	2X2, 2X2A	6BW	1DN5, 1U5	7DU	6354	8BZ	7X7		
4AC	3A3	6BX	3V4	7EA	6CR6, 12CR6	8CH	6AL7GT		
4AH	1R4	6CC	6AR5	7EG	2BN4, A, 3BN4A, 4BN4, 6BN4A	8CJ	2C51, 5670, WA, 7861		
4AJ	OA3, OB3, OC3, OD3, 1265, 1266	6CH	6AM5, 6BJ5, 6516	7EJ	7001	8CK	6A07GT		
4AM	2C22	6CJ	5641	7EN	3DT6, A, 4DT6, A, 5GX6, 6DT6, A, 6GX6, 6GY6, 12DT6, 7693, 7694	8CP	1AC5, 1AD5		
4BU	OY4, OY4G	6CK	6AU5GT, 6AV5GA, 6BD5GT, 12AV-5GA, 17AV5GA, 18A5, 25AV5GA	7ES	1AN5	8CT	6BA7, 12BA7		
4C	5Z3, 80, 83, 1275	6CL	5851, 6000, 6147	7EW	2CY5, 2EA5, 2EV5, 3CY5, 3EA5, 3EV5, 4CY5, 6CY5, 6EA5, 6EV5, 7167, 7717	8DA	1S6		
4CG	6AU4GTA, 6AX4GT, A, 6CQ4, 6DA4, A, 6DE4, 6DM4, 6DQ4, 6W4GT, A, 12AX4GTA, B, 12D4, A, 12DM4, 12DQ4, 17AX4GT, A, 17D4, A, 17DE4, 17DM4, 17DQ4, 19AU4, GTA, 22DE4, 25AX4GT, 25W4GT	6CN	6BY5G, GA	7FB	12EL6	8DC	5636, 5908, 5916, 6205, 6206, 6943, 6944		
4CK	5823	6E	25Z5	7FD	12K5	8DD	5643		
4CN	5644	6F	6C6, 6D6, 78, 1221	7FL	2EN5	8DF	6AZ5		
4D	2A3, 6A3, 45, 1230, 1276	6G	75	7FP	2ER5, 2ES5, 2FH5, 2FQ5, A, 2FY5, 2GK5, 3ER5, 3ES5, 3FH5, 3FQ5, A, 3FY5, 3GK5, 6ER5, 6ES5, 6FH5, 6FQ5, A, 6FY5, 6GK5, 6ER5	8DG	6BF7, 6021, 6111, 6112, 6832, 6947, 6948, 7327, GB, 7550, 7759, 7760, 7787, 7789		
4K	1229	6Q	6AC5GT, 6C5, GT, 6J5, GT, 12J5GT, 884	7FQ	2FV6, 6FV6	8DJ	5896, 5903, 6052, 6053, 6110		
4R	OZ4, OZ4A, OZ4G	6R	6E5, 6U5	7FW	6GN6, 12GN6	8DK	6AD4, 6AK4, 5718, 5719, 5904, 5977, 6055, 6814, 6946, 7888		
4V	OA4G, 1267	6S	6AX5GT, 6X5GT, WGT, 1274	7FZ	35GL6, 50HC6	8DL	5639, 5840, 5899, 5902, 5905, 5906, 5907, 6049, 6056, 6788, 6945, 7761, 7762, 8064		
4Z	35Z3	6X	1A5GT	7GA	2FS5, 3FS5, 6FG5, 6FS5	8DM	5987		
5AB	7Y4, 7Z4	7AG	6AD6G, 6AF6G	7Q	6H6, GT, 12H6, 25Z6GT, 50AX6G, 50Y6GT, 117Z6GT	8DQ	5968		
5AC	7A4/XXL, 7B4	7AK	1LA6, 1LC6	7R	6J7, G, GT, 6K7, 12J7GT, 12K7GT, 1223	8DR	5969		
5AD	1LA4, 1LB4	7AO	1LC5, 1LG5, 1LN5	7S	5V6GT, 6DG6GT, 6EY6, 6EZ5, 6EZ6, 6F6, G, GT, 6G6G, GT, 6K6GT, 6L6, GB, GC, 6U6, GT, GTY, 6V6, GT, GTA, 6W6GT, 6Y6GA, 7EY6, 9EF6, 12A6, 12EF6, 12EN6, 12L6GT, 12V6GT, 12W6GT, 17L6GT, 25L6GT, 25W6GT, 35L6-GT, 50L6GT, 50L6GT, 1614, 5824, 5871, 5881, 5932, 6550, 7408, EL-37, KT-66, KT-88, 7581, A, 7751	8DS	5970		
5AG	1LH4	7AP	3Q5GT	7T	6L7, 6P7G, 1612	8DY	6BA5		
5AL	35Y4	7AT	1R5	7V	6Q7, GT, 6R7, 12Q7GT, 6118	8E	6B8, 12C8		
5AP	1A3	7AZ	6SF7, 12SF7	7Z	1A7GT	8EC	7212, 7358		
5AW	807, W, 5933, WA	7BA	3S4, 3Q4, 3Z4	8A	6A8, G, GT, 12A8GT	8EL	6AH4GT		
5AY	6D4	7BB	3A4	8AC	7AF7, 7F7, 7N7, 14AF7/XXD, 14F7	8ES	40A1, 40B2		
5AZ	1625	7BC	3A5	8AD	6SA7GT, GTY, 12SA7GT	8ET	6CA7, EL34		
5BO	OA2, WA, OB2, WA, OC2, 5651, WA, 6626, 6627	7BD	3CE5, 3BC5, 4BC5, 4CE5, 6AG5, 6AJ5, 6AK5, 6AN5, 6BC5, 6CE5, 35C5, 40A, 5654, 5654/6AK5W/6096, 6028, 6186, 6186/6AG5WA, 6968, 9001, 9003	8AE	7R7, 14R7	8EX	6308		
5BQ	25DK4, 35W4, 36AM3, A, 50DC4	7BE	3B7	8AL	7Q7, 14Q7	8EY	6352		
5BS	6X4, WA, 12X4	7BF	5J6, 6J6, A, WA, 19J6, 1216, 5844, 5964, 6045, 6101, 7244, A	8AN	50Y7GT	8EZ	3AW3		
5BT	6BG6G, 6CD6G, A, 6DN6, 6EX6, 19BG6GA, 21EX6, GA, GB, 25CD6-GB, 25DN6, 35CD6GA, 7867	7BH	2C21			8FU	6BU5		
5CA	5845	7BJ	6AN6			8FV	6BD4, A		
5CB	5722	7BK	3AU6, 3BA6, 4AU6, 4BA6, 6AH6, 6AK6, 6AU6, A, WB, 6BA6, W, 6BD6, 6FD6, 6HR6, 12AC6, 12AF6, 12AU6, 12BA6, 12BD6, 12BL6, 12CX6, 12CY6, 12DZ6, 12EA6, 12EK6, 12EZ6, 18FW6, 18GD6, 19HR6, 5749, 6660, 7496, 7543	7BQ	6J4, WA, 7137, 7245			8G	6C8G, 6F8G
5CE	6AB4, 6664	7BN	2D21, 2D21W	7BS	9002	8GB	6BL4		
5D	6Z4/84, 84/6Z4	7BQ	6J4, WA, 7137, 7245	7BT	3AV6, 4AY6, 6AT6, 6AQ6, 6AV6, 6BF6, 12AE6, A, 12AJ6, 12AT6, 12AV6, 12BF6, 12BK6, 12FK6, 12FM6, 12FT6, 18FY6, 18GE6	8GC	6BK4, 6BU4		
5DE	3DG4	7BS	9002	7BZ	5AQ5, 6AQ5, A, 6BF5, 6DS5, 12AQ5, 19AQ5, 35B5, 50B5, 6005, 6005/6AQ5W	8GD	6CB5A, 6CL5, 6FN5		
5L	5AR4, 5AT4, 5CG4, 5V4G, GA, 5Z4, GT, 6Z34					8GH	3B2		
5M	6F5, GT, 12F5GT					8GQ	6690		
5Q	5X4GA, 5Y4GA, GT					8GT	6CM5		
5S	6B4G					8GV	6M3		
5T	5AS4, A, 5AW4, 5AX4GT, 5AZ4, 5R4GY, GYA, GYB, 5T4, 5U4G, GA, GB, 5U4WG, WGTA, 5Y3GT, A, 5931					8HC	2B3		
5Y	1N5GT					8HY	7027, A		
5Z	1H5GT					8JB	6CK4		
6AA	7A5, 7C5, 14C5, 35A5, 50A5					8JC	6DQ5		
6AB	6SF5, 12SF5, 12SF5GT					8JP	6DZ7		
6AB8	6AB8					8JX	6GC6, 12GC6		
6AD	35Z5GT					8K	6K8, 12K8		
6AE	7B5					8KB	6FE5, 50FE5		
						8KD	5CU4		

TUBE TYPE BASING ARRANGEMENTS

BASE	TYPE	BASE	TYPE	BASE	TYPE	BASE	TYPE
8KG	7591	9CZ	12G8, 6350, 6463, 6840	9HL	6939	12AQ	2CW4, 6CW4, 7586, 8056
8KN	7355	9DA	5AN8, 6AN8, A, 10C8, 12CT8, 7258	9HN	5CZ5, 6CZ5, 6DT5, 6EM5, 6GB5, 8EM5, 12DT5, 25DT5, 27GB5, 28GB5	12AS	7587
8KS	5DJ4	9DC	4BL8, 6BL8, 9A8	9HP	6AY3, 6BA3, 6BH3, 6DW4, 12AY3, 17AY3, 17BH3, 22BH3	12BA	7688, 7689, 7690
8N	6AB7, 6AC7, 6SJ7, GT, WGT, 6SK7, GT, 6SS7, 12SJ7, GT, 12SK7, GT, 5693	9DD	6FC7, 7FC7	9HR	12DL8, 12DV8	12BF	6B10, 8B10
8Q	6SQ7, GT, 6SR7, 12SQ7, GT, 12SR7	9DJ	6BW4, 12BW4	9HV	12EM6	12BJ	6GF5, 12GE5
8R	6SA7, 6SB7Y, 12SA7	9DS	5AS8, 6AS8	9HZ	12DK7	12BL	6AX3, 12AX3
8S	6SC7, 12SC7	9DT	3A2	9JC	12DW8	12BM	6FJ7
8U	7A8	9DV	6486A	9JG	5EU8, 6EU8	12BQ	6C10, 6D10
8V	7A7, 7AG7, 7AK7, 7B7, 7C7, 7H7, 7L7, 7V7, 14A7, 14C7, 1231, 1273, 1280, 1284, 6145	9DW	5AT8, 6AT8, A	9JH	7150	12BR	5AZ3
8W	7B6, 7C6, 14B6	9DX	6AU8, A, 6AW8, A, 6BA8, 6BH8, 6CX8, 6EB8, 6GN8, A, 6HF8, 6HZ8, 6JE8, 8AU8, A, 8AW8A, 8BA8A, 8BH8, 8CX8, 8EB8, 8GN8, 8JE8, 10EB8, 10HF8, 11JE8, 7060, 7716	9JT	7199	12BU	6G11, 6AL11, 12AL11
8X	7B8	9DZ	5AV8	9JU	12DS7, A	12BW	6J11
8Y	6AG7	9E	5T8, 6T8A, 19C8, 19T8	9JY	12DU7	12BY	6K11, 6Q11, 6AV11
9A	6AX7, 7AU7, 9AU7, 12AD7, 12AE7, 12AT7, WA, 12AU7, A, 12AV7, 12AX7, A, 12AY7, 12AZ7A, 12BH7, A, 12BZ7, 12DF7, 12DM7, 12DT7, 12DW7, 12FV7, 12U7, 5751, WA, 5814, A, WA, 5963, 5965, 6189, 6189/12AU7WA, 6201, 6211A, 6679, 6680, 6681, 6851, 6955, 7025, 7058, 7062, 7318, 7489, 7490, 7492, 7494, 7728, 7729, 7730	9EC	5B8	9KA	6EZ8, 19EZ8	12CA	6M11
9AC	6S4A	9ED	6AZ8	9KG	4CM4, 6CM4	12CN	7984
9AD	5879	9EF	6CS7, 8CS7, 6DA7, 10DA7	9KH	7239	12CT	8058
9AE	5EA8, 5GH8, 5U8, 6AX8, 6EA8, 6GH8, 6J8, 6U8A, 9U8A, 19EA8, 6678, 7059, 7643, 7687, 7731	9EG	5BE8, 5DH8, 6BE8, A	9KP	6FH8	12DA	6AG11
9AG	12B4A	9EJ	6582A, 7001	9KR	6FM8, 14GT8, 14JG8, 7724	12DE8	12DE8
9AH	6V8, 19V8, 7500	9EN	6CN7, 8CN7	9KS	7360	12DG	2AH2
9AJ	4BC8, 4BQ7A, 4BS8, 4BX8, 4BZ7, 4BZ8, 4ES8, 5BK7A, 5BQ7A, 5BZ7, 5ES8, 6AQ8, 6BC8, 6BK7A, B, 6BQ7A, 6BS8, 6BX8, 6BZ7, 6BZ8, 6CG7, 6GM8, 6DJ8, 6DT8, 6ES8, 6FW8, 7DJ8, 7ES8, 8CG7, 12DJ8, 12DT8, 6922, 7057, 7803	9EP	7898	9KU	12FR8	12DM	6AR11, 11AR11
9AK	5X8, 6X8, 9X8, 19X8	9EQ	7721, 7722	9KV	12FX8, A	12DP	6AS11, 6AF11, 15AF11
9AQ	3BX6, 3BY7, 3EH7, 3EJ7, 4EH7, 4EJ7, 6BX6, 6EH7, 6EJ7, 6EL7, 12BX6, 13EC7	9ER	6BJ8, 6BN8, 8BN8	9LG	6CY7, 8CY7, 11CY7	12DQ	1AD2
9AX	6BC7, 6BJ7	9ES	6CM7, 8CM7	9LP	6EV7, 6FQ7, 8FQ7	60E3	60E3
9AZ	12AD5	9EU	6QC5, 12AB5, 6973, 7061	9LQ	6EQ7	407A	407A
9BA	7227, 7499, 6DG7	9EX	6A8, 6BM8, 6DZ8, 8DZ8, 9DZ8, 12DZ8, 17HC8, 18DZ8, 50BM8, 35DZ8, 50FY8	9LS	6EU7	FM1000	FM1000
9BD	6B3, 6V3A, 12B3	9FA	5BR8, 5FV8, 6BR8A, 6FV8, A, 9BR8, 12EC8, 19HV8	9LT	6ET7, 8ET7	1222	1222
9BF	12BV7, 12BY7, 12DQ7, 6870, 7054, 7733	9FC	4CX7, 6CH7, 6CX7	9LW	3GS8, 3H58, 4GS8, 6GS8, 6HS8	1236A	1236A
9BQ	6BK5, 12BK5, 25BK5, 50BK5	9FE	5BT8, 6BT8	9LX	1H2	1247	1247
9BS	12DF5	9FG	3BU8, 3BU8A, 6BU8	9LZ	6GW8	5642	5642
9BV	6CL6, 6677	9FH	12F8	9M	6CA4	5647	5647
9BX	6AJ4, 6AM4, 6CR4	9FJ	6BV8	9ME	35HB8	5702	5702, WA, WB
9CB	6AF3, 12AF3	9FK	17H3	9MP	6HG8, 7HG8, 8HG8	5703	5703, WA, WB
9CF	9BR7, 12BR7	9FN	6BY8	9MQ	6GM5	5704	5704
9CK	5CM6, 6CM6, 6DW5, 12CM6, 12DW5	9FR	7233	9MR	6FA7	5744	5744
9CM	50A1	9FT	6CH8	9MS	7701	5783	5783, 5787
9CQ	Ef86/6267	9FV	6854	9MX	7719	5784	5784
9CV	6BQ5, 6CW5, 6DY5, 8BQ5, 8CW5, 10BQ5, 12FB5, 15CW5, EL84/6BQ5, EL86, 7189, 7320	9FX	5CL8, A, 6CL8A, 9CL8, 19CL8A	9NM	6GJ5, 12GJ5, 17GJ5	5785	5785
9CY	5AM8, 6AM8, A	9FZ	5CM8, 6CM8, 6CS8	9NQ	6HW8	5889	5889
		9G	5686	9NX	6BF8	6187	6187
		9GB	6877	9NZ	7868	6611	6611
		9GC	12J8	9PA	6JC8	6612	6612
		9GE	5CQ8, 6CQ8	9PB	7905	6872	6872
		9GF	5CG8, 5FG7, 6CG8, A, 6FG7	9PG	20EZ7	7077	7077
		9GJ	5CR8, 6CR8	9PQ	6JU8	7241	7241, 7242
		9GM	6CU8	9PX	7695, 7754	7246	7246
		9GR	6DB5, 12DB5	9PU	6HB6, 6GK6, 16GK6	7382	7382
		9GS	12AL8	9QJ	5BC3	7430	7430
		9GT	12DK8	9T	17C8	7561	7561
		9H	5687, 6900, 7044, 7119, 7370	9U	1V2	7576	7576
		9HE	6DC8	9V	417A, 5842	7720	7720
		9HF	6DE7, 6DR7, 6EW7, 6FD7, 6FR7, 10DE7, 10DR7, 10EW7, 10FD7, 10FR7, 13DE7, 13DR7, 13FD7, 13FR7, 19DE7	9X	5847	7768	7768
		9HK	5BW8, 6BW8	9Y	1AX2, 1X2B	7841	7841
				10F	6C9, 17C9A		

EUROPEAN--AMERICAN RECEIVING TUBE REPLACEMENT CHART

AMERICAN SUBSTITUTIONS FOR EUROPEAN TUBES

European Type	American Type	Code*	European Type	American Type	Code*
1C1	1R5	ER	EF93	6BA6	ER
1D13	1A3	ER	EF94	6AU6	ER
1F2	1L4	ER	EF96	6AK5	ER
1F3	1T4	ER	EF96	6AG5	ER
1FD9	1S5	ER	EF183	6EH7	ER
1P10	3S4	ER	EF184	6EJ7	ER
1P11	3V4	ER	EH90	6CS6	ER
6D2	6AL5	ER	EK32	6A8/G/GT	NR†
6L12	6AQ8	ER	EK90	6BE6	ER
6P15	6BQ5	ER	EL37	6L6GC	NR†
8D4	6W7	NR†	EL84	6BQ5	ER
9BR8	9U8A	NR*	EL86	6CW5	ER
13D2	6SN7GTB	ER	EL90	6AQ5	ER
B36	12SN7GTA	ER	EL91	6AM5	ER
B66	6SN7GTB	ER	EL180	12BY7A	ER
B162	12AT7	ER	EZ35	6X5GT	ER
B309	12AT7	ER	EZ81	6CA4	ER
B329	12AU7	ER	EZ90	6X4	ER
B339	12AX7, 7025	ER	GZ30	5Z4	ER
B719	6AQ8	NR†	GZ32	5V4GA	ER
BPM04	6AQ5	ER	GZ33	5U4GB	NR†
D2M9	6AL5	ER	GZ34	5U4GB	NR†
D63	6H6	NR†	H63	6F5/GT	ER
D77	6AL5	ER	HAA91	12AL5	ER
D152	6AL5	ER	HABC80	19T8	ER
DA90	1A3	ER	HBC90	12AT6	ER
DAC32	1H5GT	ER	HBC91	12AV6	ER
DAF91	1S5	ER	HD14	1H5GT	ER
DAF92	1U5	ER	HD30	3B4	ER
DCC90	3A5	ER	HF93	12BA6	ER
DD6	6AL5	NR†	HF94	12AU6	ER
DF33	1N5GT	ER	HK90	12BE6	ER
DF62	1AD4	ER	HL90	19AQ5	ER
DF91	1T4	ER	HL92	50C5	ER
DF92	1L4	ER	HMO4	6BE6	ER
DF904	1U4	ER	HY90	35W4	ER
DH63 (M)	6Q7/G/GT	ER	KT32	25L6GT	NR†
DH76	12Q7/GT	NR†	KT63	6F6G	ER
DH77	6AT6	ER	KT66	6L6GC, 5881, 807*	NR†
DH81	7B6	NR†	KT71	50L6GT	NR†
DH149	7C6	ER	KTW61	6S7	NR†
DH719	6T8A	ER	KTW63	6K7/G/GT	NR†
DK32	1A7GT	ER	KTZ63	6J7/GT	NR†
DK91	1R5	ER	L63	6J5/GT	ER
DL29	3D6	ER	L77	6C4	ER
DL33	3Q5GT	ER	N14	1C5GT	ER
DL35	1C5GT	ER	N16	3Q5GT	ER
DL36	1Q5GT	ER	N17	3S4	ER
DL91	1S4	ER	N18	3Q4	ER
DL92	3S4	ER	N19	3V4	ER
DL93	3A4	ER	N77	6AL5	NR†
DL94	3V4	ER	N709	6BQ5	ER
DL95	3Q4	ER	N727	6AQ5	ER
DL98	3B4	ER	PCF82	9U8A	ER
DP61	6AK5	ER	PMO4	6BA6	ER
DY30	1B3GT	NR†	PMO5	6AK5	NR*
DY80	1X2B	NR†	QEO6/50	807	NR†
DY86	1H2	NR†	QV05/25	807	NR†
DY87	1H2	NR†	R19	1X2B	NR†
E90F	6BH6	ER	R52	5Z4	ER
E91H	6BY6	NR†	T2M05	6J6	ER
EA91	6AL5	ER	U41	1B3GT	NR†
EABC80	6T8	ER	U50	5Y3GT	ER
EB34	6H6	NR†	U52	5U4GB	ER
EB91	6AL5	ER	U70	6X5GT	NR†
EBC33	6R7	NR†	U78	6X4	ER
EBC90	6AT6	ER	U147	6X5GT	ER
EBC91	6AV6	ER	U149	7Y4	ER
EBF32	6B8	NR†	U709	6CA4	NR†
EC84	6AJ4	ER	V2M70	6X4	ER
EC90	6C4	ER	W17	1T4	ER
EC92	6AB4	ER	W63	6K7/G/GT	NR†
EC94	6AF4, 6AF4A	ER	W76	12K7/GT	NR†
EC95	6ER5	ER	W149	7B7	ER
EC97	6FQ5A	NR†	W727	6BA6	ER
ECC35	6SL7GT	NR†	X14	1A7GT	ER
ECC40	6N7/GT	NR†	X17	1R5	ER
ECC81	12AT7	ER	X63 (M)	6A8/G/GT	NR†
ECC82	12AU7	ER	X81	7S7	NR†
ECC83	12AX7, 7025	ER	X148	7S7	ER
ECC84	6BQ7A	NR†	X727	6BE6	ER
ECC85	6AQ8	ER	XC95	2ER5	ER
ECC88	6DJ8	ER	XCC189	4ES8	ER
ECC91	6J6	ER	XL84	8BQ5	ER
ECC180	6BQ7A	ER	XF183	3EH7	ER
ECC189	6ES8	ER	XF184	3EJ7	ER
ECF82	6U8	ER	YF183	4EH7	ER
ED2	6AL5	ER	YF184	4EJ7	ER
EF37, EF37A	6J7/GT	NR†	Z14	1N5GT	ER
EF39	6K7/G/GT	NR†	Z63	6J7/GT	ER
			ZD17	1S5	ER

EUROPEAN/AMERICAN EXACT REPLACEMENTS FOR EUROPEAN TUBES

European Type	**European/ American	European Type	**European/ American	European Type	**European/ American
1C2	1AC6	EC97	6FY5	N359	21A6
1FD1	1AH5	ECC84	6CW7	PABC80	9AK8
1P1	3C4	ECC85	6CM8	PC86	4CM4
6F12	6AM6	ECC88	6D18	PC84	7AN7
6F18	6EC7	ECC89	6FC7	PCC85	9AQ8
6L34	6AQ4	ECC189	6ES8	PCC88	7DJ8
6LD3	6CV7	ECF80	6BL8	PCC89	7FC7
6P9	6BM5	ECF86	6HG8	PCF80	9A8
7D9	6AM5	ECH42	6C9	PCF86	7HG8
7D10	6CH6	ECH80	6AN7	PCL82	16A8
8D3	6AM6	ECH81	6AJ8	PCL84	15DQ8
8D5	6BR7	ECH83	6DS8	PL36	25E5
8D7	6BS7	ECL80	6AB8	PL81	21A8
9D6	6CQ6	ECL82	6BM8	PL82	16A8
9P9	9BM5	ECL84	6DX8	PL83	15A6
17N8	17C8	EF41	6CJ5	PL84	15CW5
19D8	19AJ8	EF80	6BX6	PMO7	6AM6
19U3	19X3	EF81	6BH5	PY80	19X3
30C1	8A8	EF85	6BY7	PY81	17Z3
30F5	7ED7	EF86	6CF8	PY82	19Y3
30L1	7AN7	EF86	6267	R16	1T2
30P4	25GF6	EF89	6DA6	SP6	6AM6
30P12	12FB5	EF89	6DG7	U37	1T2
62DDT	6CV7	EF91	6AM6	U43	6X2
62VP	6CJ5	EF92	6CQ6	U45	31A3
63T1	6AB8	EL34	6CA7	U150	6BT4
64PT	6BX6	EL36	6CM5	U151	6X2
65ME	6BR5	EL38	6CN6	U153	17Z3
66KU	6BT4	EL41	6CK5	U154	19Y3
67PT	6CK5	EL80	6M5	U191	19CS4
141TH	14K7	EL81	6CJ6	UABC80	28AK8
171DDP	17N8	EL83	6CK6	UAF42	12S7
311SU	31A3	EL85	6BN5	UBC41	14L7
451PT	45A5	EL86	6CW5	UBF80	17N8, 17C8
B319	7AN7	EL91	6AM5	UC92	9AB4
BF61	6CK5	EL95	6DL5	UCC85	26AQ8
DAF96	1AH5	EL821	6CH6	UCH42	14K7
DC80	1E3	EQ80	6BE7	UCH81	19AJ8, 19D8
DF96	1AJ4	EY51	6X2	UCL32	50BM8
DF97	1AN5	EY80	6U3	UF41	12AC5
DH150	6CV7	EY81	6R3	UF89	12DA6
DH719	6AK8	EY82	6N3	UL41	45A5
DK92	1AC6	EY86	6S2	UL84	45B5
DK96	1AB6	EY87	6S2A	UQ80	12BE7
DL96	3C4	EY88	6AL3	UY41	31A3
EABC80	6AK8	EZ40	6BT4	UY85	38A3
EAF42	6CT7	EZ80	6V4	V61	6BT4
EBC41	6CV7	EZ91	6AV4	VP6	6CQ6
EBC80	6BD7	GZ34	5AR4	WD142	12S7
EBC81	6BD7A	HCH81	12AJ8	WD709	6N8
EBF80	6N8	HL94	30A5	X18	1AC6
EBF81	6AD8	LN152	6AB8	X20	1AC6
EBF83	6DR8	N78	6BJ5	X79	6AE8
EBF89	6DC8	N142	45A5	X719	6AJ8
EC80	6Q4	N144	6AM5	Z77	6AM6
EC81	6R4	N150	6CK5	Z152	6BX6
EC86	6CM4	N152	21A6	Z719	6X6
EC91	6AQ4	N153	15A6	Z729	EF86
EC93	6BS4	N309	15A6	ZD152	6N8
		N329	16A5		

—Basing Differs. †—Heater Characteristics Differ. ‡—Electrical Characteristics Differ.


**—The suggested replacements are principally European manufactured tubes imported for sale in this country.

— ER—Exact Replacement.
NR—Near Replacement.

Tubes coded NR may require changes in circuit wiring due to differences in basing and electrical characteristics as indicated by the accompanying qualifying notes. Suggested replacements coded ER compare identically with listed European types with respect to electrical characteristics, the type bases used and basing connections. The maximum ratings of suggested replacements compare with those of the European tubes; however, the differences between some types may be of significance in certain applications. Some types may also be especially controlled for particular characteristics.

The data shown is believed to be accurate. However, Sylvania does not assume responsibility in case of error.

Please note that all types listed may not be available from Sylvania. Consult your current price list.



SYLVANIA RECEIVING TUBE QUALITY BUILT IN FROM BEGINNING TO END


From beginning (SYLVANIA tubes are assembled from SYLVANIA made components, permitting tight initial control of quality) to end (all finished SYLVANIA tubes receive a final quality check), SYLVANIA puts all its tubes through a demanding quality control program, assuring the highest degree of reliability, the least incidence of callbacks. Product quality is the end consideration in the manufacture of SYLVANIA receiving tubes. New developments and techniques of tube design, material and manufacturing methods are originated, researched and rapidly incorporated into actual production, creating the most modern, most advanced tubes possible. Always insist on SYLVANIA.



COMPLETE TECHNICAL INFORMATION & LITERATURE


The literature below is only a partial listing of technical data and brochures available from Sylvania. Additional information may be procured from your Sylvania Distributor, or by writing Sylvania.

SYLVANIA NEWS (ET 1012) Largest and most widely read publication of its kind in the electronics industry. Features stories on advertising, merchandising and servicing. In addition, each issue contains a 4-page technical section. **SUBSCRIPTION—FREE**




ELECTRON TUBE APPLICATION NOTES (ET3959) A 56-page brochure detailing the important parameters and considerations on electronic receiving tubes. This is the most comprehensive text on the subject available.

SYLVANIA NEWS TECHNICAL SECTION BINDERS One of the most complete reference libraries you can have are the technical sections of the SYLVANIA NEWS, sturdily bound in volume form.





TECHNICAL SECTION BINDERS
No. 1341 Vol. 1 '35 to '40 incl. . . \$1
No. 1342 Vol. 2 '41 to '45 incl. . . \$1
No. 1343 Vol. 3 '46 to '49 incl. . . \$1
No. 1344 Vol. 4 '50 to '53 incl. . . \$1
No. 1345 Vol. 5 '54 to date . . . \$1
No. 1340 Add'l. binders only . . . 75c





SYLVANIA ENGINEERING DATA SERVICE The most complete and comprehensive engineering data service available with full information on nearly 2,000 types of receiving tubes, cathode ray tubes, micro-wave devices, counter tubes, and electroluminescent display devices. Initial subscription \$28 including 5 binders. Subsequent yearly maintenance fee \$5 (approximately 7 supplemental inserts per year).

SYLVANIA INDUSTRIAL NEWS (ET 2004) Published six times a year, Sylvania Industrial News keeps you up-to-date on the latest Sylvania industrial products and manufacturing techniques. Any service dealer with industrial accounts should be on the mailing list for Sylvania Industrial news. **SUBSCRIPTION—FREE**



CHARACTERISTICS OF SYLVANIA CATHODE RAY TUBES (ET1351) Provides detailed characteristics data for hundreds of CRT types—industrial and military, and TV picture tubes. Includes basing diagrams and phosphor chart. An invaluable reference for dealers and technicians. **PRICE—15¢**

SYLVANIA TECHNICAL MANUAL (ET 1901) Abbreviated engineering data on over 1,800 types of receiving tubes, cathode ray tubes. A handy desk reference. Price \$3.00 including supplemental mailings.



COUNTER TUBE HANDBOOK (ET3989) Complete technical data on Sylvania counter tubes and application information including typical circuits.

All material may be obtained by writing: SYLVANIA ELECTRIC PRODUCTS INC.
1100 MAIN STREET, BUFFALO 9, NEW YORK Or, contact your regular Sylvania Distributor.