

P6000 thru P6005 PROBE PARTS

REPLACEMENT INFORMATION

			Supplied as a Unit		Supplied as a Unit					
	Nose Ass'y	Body	Thermo-fit	Sleeve Ass'y	Locking Ring	Ass'y Base Bushing	Component Base Bushing End	Cable Ass'y End	Component Connector End	Connector
	(1)	(2)	(3)	(4)	(5)	(6)	(7)	(8)	(9)	(10)
42 "	P6000 UHF X10	Tek 010-020	206-014	204-021	166-212	105-022	358-121	175-159		131-058
	P6001 UHF X1	Tek 010-023	206-029	204-021	166-212	105-016	"	175-160		131-058
	P6002 UHF X100	Tek 010-024	206-031	204-034	166-213	105-017	"	175-161		131-058
	P6003 BNC X10	Tek 010-027	206-014	204-021	166-212	105-023	"	175-162		131-185
	P6004 BNC X1	Tek 010-028	206-029	204-021	166-212	105-019	"	175-163		131-185
	P6005 BNC X100	Tek 010-029	206-031	204-034	166-213	105-020	"	175-164		131-185
6 '	P6000 UHF X10	Tek 010-030	206-014	204-021	166-214	105-024	"	175-165		131-058
	P6001 UHF X1	Tek 010-032	206-029	204-021	166-212	105-016	"	175-166		131-058
	P6002 UHF X100	Tek 010-034	206-031	204-034	166-213	105-028	"	175-167		131-058
	P6003 BNC X10	Tek 010-031	206-014	204-021	166-214	105-025	"	175-168		131-185
	P6004 BNC X1	Tek 010-047	206-029	204-021	166-212	105-019	"	175-169		131-185
	P6005 BNC X100	Tek 010-050	206-031	204-034	166-213	105-035	"	175-170		131-185
9 '	P6000 UHF X10	Tek 010-035	206-068	204-021	166-219	105-029	"	175-171		131-058
	P6001 UHF X1	Tek 010-033	206-069	204-021	166-214	105-016	"	175-172		131-058
	P6002 UHF X100	Tek 010-043	206-031	204-034	166-213	105-031	"	175-173		131-058
	P6003 BNC X10	Tek 010-045	206-068	204-021	166-219	105-033	"	175-174		131-185
	P6004 BNC X1	Tek 010-048	206-069	204-021	166-214	105-019	"	175-175		131-185
	P6005 BNC X100	Tek 010-051	206-031	204-034	166-213	105-036	"	175-176		131-185
12 '	P6000 UHF X10	Tek 010-041	206-056	204-057	166-216	105-030	"	175-177		131-058
	P6001 UHF X1	Tek 010-042	206-069	204-021	166-214	105-016	"	175-178		131-058
	P6002 UHF X100	Tek 010-044	206-031	204-034	166-215	105-032	"	175-179		131-058
	P6003 BNC X10	Tek 010-046	206-056	204-057	166-216	105-034	"	175-180		131-185
	P6004 BNC X1	Tek 010-049	206-069	204-021	166-214	105-019	"	175-181		131-185
	P6005 BNC X100	Tek 010-052	206-031	204-034	166-215	105-037	"	175-182		131-185